The chain

01 Chip Design, EDA and IP
02 Silicon and Wafers
03 Chemicals, Gases and Photoresist
04 Lithography
05 Photomasks and Pellicles
06 Deposition and Etch
07 Metrology and Inspection
08 Foundries and Fabs
09 Memory and HBM
10 Advanced Packaging
11 Substrates and PCBs
12 Test and Assembly
13 Systems and Networking
14 Data Centers and Power

15 The Economics of AI Chips
16 Who Controls the Chain

Stage 1 of 14 · Extreme concentration · Hard to substitute

Chip Design, EDA and IP

Synopsys, Cadence and Siemens EDA make the software used to design every advanced chip. In 2025 they took over 85 percent of its $18 billion market, licensed blocks included.

Specimen 01 · Chip Design, EDA and IP

A GPU die based on Nvidia's published H100 block diagram. It is drawn at the size of one full reticle field, 26 by 33 mm, the largest area a scanner can print in one shot. H100 is a single die. The drawing adds a copper strip on one short edge to stand for the die-to-die link that two-die designs such as Blackwell carry.

In plain terms

Chip design turns an idea for a new chip into a complete blueprint. A chip holds billions of transistors, tiny electrical switches. The blueprint fixes where each one sits and how it is wired to the others. The chip runs on a clock, and a signal has to cross those wires within one tick, less than a billionth of a second. Software from three companies, Synopsys, Cadence and Siemens, lays out the blueprint, checks it and signs it off. A foundry, a factory that makes chips for other companies, accepts only designs that have passed that software's checks. The foundry prints each layer of the design onto silicon through a stencil called a mask. Changing the blueprint once the masks are made takes new masks and a few months[1].

In short

At advanced nodes, 7 nm and below, Synopsys alone has more than 90 percent of the market for static timing analysis, the check that every signal arrives in time[2]. SemiAnalysis wrote in May 2026 that no startup can replicate a complete design flow by writing it from scratch[2].

Since October 2022 a US license has been needed to export design software specially made for chips with gate-all-around transistors, a transistor design the rule calls key to processes at 3 nm and below[3]. As of 2025, the think tank CSIS found Chinese design tools still far from replacing the full range of advanced capabilities US firms offer, especially for 5 nm and 3 nm chip design[4]. But Chinese design-software companies were winning share

1 The Dark Side Of The Semiconductor Design Renaissance – Fixed Costs Soaring Due... SemiAnalysis, 24 July 2022. newsletter.semianalysis.com

2 EDA Market Primer. SemiAnalysis, 21 May 2026. newsletter.semianalysis.com

3 Implementation of Certain 2021 Wassenaar Arrangement Decisions on Four Section... Federal Register, 15 August 2022. federalregister.gov

4 The Double-Edged Sword of Semiconductor Export Controls: Electronic Design... Center for Strategic and International Studies, 6 October 2025, p. 33. csis-website-prod.s3.amazonaws.com

at older manufacturing processes, the research firm SemiAnalysis reported[2].

Design is the only stage of the supply chain that happens entirely in software. The US government has restricted it with letters to the companies that sell that software. In late May 2025 the government required a license to sell chip design software to anyone in China[5]. Cadence cut off its Chinese customers until the government lifted the requirement on 2 July[5].

Chokepoint card Chip Design, EDA and IP

Concentration

Extreme

Three or fewer firms could supply this stage today, or one firm holds more than half of it.

Substitutability

Hard

Only three complete sets of chip design software exist[6]. A fourth would have to be written from nothing and approved by a foundry[2].

Price or market size

$18 billion

world market for design software, simulation software and licensed circuit blocks in 2025[2]. SemiAnalysis put a single respin, a design revision that needs some new masks, at leading-edge nodes at $50 million to $100 million in May 2026[2]

Who leads	US	**Synopsys**	Over 90 percent of the timing-signoff market at advanced nodes as of 2026[2]
	US	**Cadence**	55 to 60 percent of the hardware emulator market at advanced nodes as of 2026[2]
	US	**Siemens EDA**	Over 85 percent of physical verification, the final layout check, at advanced nodes as of 2026[2]
	GB	**Arm**	About 50 percent of processor compute at the top cloud firms as of May 2026[7]
	US	**Broadcom**	$16.7 billion of AI semiconductor revenue in the third quarter of fiscal 2026, custom accelerators and networking combined[8]
Where it is made	US	**United States**	Synopsys, Cadence, Broadcom, Marvell and Nvidia
	GB	**United Kingdom**	Arm processor and interconnect designs licensed from Cambridge, and since 2026 its own server chip
	TW	**Taiwan**	Alchip, Global Unichip and MediaTek: design services that carry a chip to the factory
	IL	**Israel**	Annapurna Labs, the AWS design house behind Trainium and Graviton
	IN	**India**	Nearly 20 percent of the world's chip design engineers, on the Indian government's count
Why substitution is slow	Changing one tool, such as the synthesis tool that turns a design's code into logic cells, means re-running the later steps of the design[2]. The foundry that makes the chip also specifies which signoff tools its customers must use[2].		

2 **EDA Market Primer.** SemiAnalysis, 21 May 2026. newsletter.semianalysis.com

5 **Cadence Design Systems, current report on Form 8-K dated 2 July 2025.** U.S. Securities and Exchange Commission, 3 July 2025. sec.gov

6 **The Double-Edged Sword of Semiconductor Export Controls: Electronic Design...** Center for Strategic and International Studies, 6 October 2025, p. 13. csis-website-prod.s3.amazonaws.com

7 **Arm delivers record-breaking quarter and full-year results.** Arm, 6 May 2026. newsroom.arm.com

8 **Broadcom, current report on Form 8-K dated 2 September 2026.** U.S. Securities and Exchange Commission, 2 September 2026. sec.gov

Where China stands

China designs its own AI accelerators, but Huawei's most powerful chip in 2026, the Ascend 950, delivers about half the computing performance of Nvidia's H100 from 2022, on Epoch AI's estimate[9]. CSIS found that as of 2025 Chinese design tools were still far from replacing the full range of advanced capabilities US firms offer, especially for 5 nm and 3 nm chips[4].

Where the US stands


Synopsys and Cadence, the two largest design-software vendors by 2025 revenue, are American[2].

01

How a chip is designed

Figure 01.1 · Explainer, 23 seconds

How a chip is designed



1. **A blueprint.** Making a chip starts with design, which turns an idea into a complete blueprint. The blueprint fixes where each of the chip's billions of switches sits and how each one is wired to the others.
2. **One tick.** The chip works in ticks, each less than a billionth of a second. On every tick a signal leaves a register, a small store that holds one number, and it has to cross its wire to the next register before the next tick.
3. **Too far.** If the next register sits far away, the wire is long. The signal is still on its way when the next tick comes, so it arrives too late.
4. **Placed closer.** Design software from three companies, Synopsys, Cadence and Siemens, places the parts and wires them together. Here it moves the register closer, and the signal arrives in time.
5. **Checked.** The software checks that every signal arrives in time and that every shape can be printed, and a chip factory accepts only designs that pass the printing checks. The factory then prints the blueprint onto silicon through stencils, and changing it after that costs new stencils and a few months.

Note: Simplified. Not to scale. The floorplan follows a GPU die. One tick, less than a billionth of a second, is slowed to about two seconds.

2 **EDA Market Primer.** SemiAnalysis, 21 May 2026. newsletter.semianalysis.com

4 **The Double-Edged Sword of Semiconductor Export Controls: Electronic Design...** Center for Strategic and International Studies, 6 October 2025, p. 33. csis-website-prod.s3.amazonaws.com

9 **Will Huawei catch up to Nvidia by 2030?** Epoch AI, 24 September 2026. epoch.ai

Design runs in five stages, all in software, and each stage's output is the next one's input.

- **Architecture.** Engineers fix the shape of the chip: the width of the block that multiplies numbers, the amount of fast on-chip memory beside it and the number of high-bandwidth memory stacks along the chip's edges. The output is a plan.
- **RTL.** Engineers write the plan as register-transfer-level code, RTL, in the hardware language SystemVerilog. A register is a small store on the chip that holds one number. On each tick of the chip's clock, every register takes its next value at the same moment. The code says what every register holds on every tick. The output is a text description of the whole chip.
- **Verification.** A large team checks that the code does what the plan says. They run it in simulation and prove parts of it correct with mathematics. They also load it into emulators, large machines full of reprogrammable chips that behave like the design, so the chip's own software can boot before any silicon exists.
- **Physical design.** Software swaps each piece of the code for a logic cell, a small ready-made circuit the foundry has already proved it can make. It then places the cells on the chip, wires them together and proves that every signal arrives in time.
- **Tape-out.** Engineers hand the finished layout to the foundry, a step called tape-out. After tape-out, software turns the layout into pattern files for the mask shop[10]. First it pre-distorts each shape so that the shape prints as drawn, a step called optical proximity correction. Then it cuts the layout into the files a mask writer reads, a step called mask data preparation.

All that checking exists because each revision after tape-out, called a respin, needs at least some new masks[1]. In 2022 SemiAnalysis put a full mask set at more than $1 million at 28 nm and more than $10 million at 7 nm[1]. The nanometer labels name process generations, called nodes, each finer than the last, and no longer measure anything. In 2022 SemiAnalysis also expected 3 nm sets to push into the $40 million range[1]. Its May 2026 primer still puts a leading-edge mask set at $40 million, and a single leading-edge respin at $50 million to $100 million[2].

The same 2022 SemiAnalysis article reported that startups had taken chips on TSMC 7 nm, then a leading-edge process, from design to tape-out for $50 million to $75 million, everything included[1].

1 The Dark Side Of The Semiconductor Design Renaissance – Fixed Costs Soaring Due... SemiAnalysis, 24 July 2022. newsletter.semianalysis.com

2 EDA Market Primer. SemiAnalysis, 21 May 2026. newsletter.semianalysis.com

10 Unlocking post-tapeout flow scalability and performance with cloud computing. Siemens Digital Industries Software, 8 January 2025. blogs.sw.siemens.com

Figure 01.2

In 2022 SemiAnalysis forecast a 3 nm mask set at $40 million

What one photomask set costs, by node, 2022. The 28 nm and 7 nm figures are minimums, and 3 nm was a forecast



Source: SemiAnalysis, The Dark Side of the Semiconductor Design Renaissance, July 2022. SemiAnalysis's May 2026 EDA Market Primer puts a leading-edge mask set at $40 million [1]

02

GPUs, custom chips and chiplets

Merchant GPU versus custom ASIC

Nvidia designs its Blackwell GPU once and sells it to everyone, so the buyer gets mature software and a resale market. A custom accelerator, an ASIC, is built for one company's own workload. It handles a narrower range of tasks and is tuned to that workload. Google's tensor processing units (TPUs) are custom accelerators of this kind[11]. Ironwood, the seventh generation, which Google announced in April 2025, carries 192 GB of memory per chip, six times its predecessor's, and delivers twice the performance per watt[11]. In April 2026 Google announced its eighth generation as two chips, the TPU 8t for training and the TPU 8i for inference, with up to twice Ironwood's performance per watt[12].

The EDA flow

Chip design software is known as electronic design automation, or EDA. Three complete EDA flows exist, each a set of tools that covers every step from code to signoff[6]. SemiAnalysis wrote in May 2026 that no startup can replicate one by writing it from scratch[2]. Changing the synthesis tool, which swaps the code for logic cells, means re-running the steps that follow: placing and wiring the cells, signoff and physical verification[2]. Foundries also specify which signoff tools their customers must use for tape-out[2].

For chips at advanced nodes, 7 nm and below, one vendor holds most of the market inside some steps of the flow. Synopsys alone has more than 90 percent of the market for static timing analysis, the check that every signal arrives in time at the chip's rated speed[2]. In May 2026 SemiAnalysis put Siemens EDA's Calibre at more than 85 percent of physical verification, the final layout check[2]. It put Cadence's Palladium at 55 to 60 percent of hardware emulation[2].

1 The Dark Side Of The Semiconductor Design Renaissance – Fixed Costs Soaring Due... SemiAnalysis, 24 July 2022. newsletter.semianalysis.com

2 EDA Market Primer. SemiAnalysis, 21 May 2026. newsletter.semianalysis.com

6 The Double-Edged Sword of Semiconductor Export Controls: Electronic Design... Center for Strategic and International Studies, 6 October 2025, p. 13. csis-website-prod.s3.amazonaws.com

11 Ironwood: The first Google TPU for the age of inference. Google, 9 April 2025. blog.google

12 Our eighth generation TPUs: two chips for the agentic era. Google, 22 April 2026. blog.google

Figure 01.3

In 2026 each segment's leading tool held at least 55 percent

Share held by the leading vendor in each of four design-software segments at advanced nodes, 7 nm and below. Lower end of each reported range



Source: SemiAnalysis, EDA Market Primer, May 2026, table of tool-level shares at advanced nodes [2]

Buy the IP or build it

Design houses license ready-made circuit blocks, known as intellectual property or IP, including the processor cores, the interface controllers and the blocks that drive high-bandwidth memory. The block that drives high-bandwidth memory is hard to design, because its signals have to arrive in time across microscopic solder bumps into a stacked memory die.

Arm licenses processor designs. In fiscal 2026 it reported $4.92 billion of revenue, $2.61 billion of it royalties[7]. It said Arm-based designs held about 50 percent of the computing power of central processors (CPUs) at the top cloud firms[7].

In 2026 Arm also launched the Arm AGI CPU, the first finished chip that Arm sells[7]. By May 2026, servers built on it could be ordered from ASRock, Lenovo, Quanta and Supermicro[7].

RISC-V is an open instruction set, the basic list of commands a processor understands, and it needs no license. Small RISC-V processors handle control tasks on the chip, and Nvidia uses them in every GPU[13].

Chiplets

The reticle limit caps the size of a single die, one piece of silicon[14]. That limit is the largest area a scanner, the machine that prints the chip's pattern, can expose in one shot. Many large accelerators are built from chiplets, several smaller dies wired together inside one package[15]. UCIe is an open industry standard for the links between them[15]. Version 3.0 of UCIe adds two faster data rates, 48 and 64 billion transfers per second, written GT/s for gigatransfers per second[15]. In a December 2024 presentation, Broadcom described its 3.5D XDSiP platform, which stacks dies face to face and sets the stacks side by side on an interposer[14]. It said the platform packs more than 6,000 mm² of silicon and 12 high-bandwidth memory stacks into one package[14].

2 EDA Market Primer. SemiAnalysis, 21 May 2026. newsletter.semianalysis.com
7 Arm delivers record-breaking quarter and full-year results. Arm, 6 May 2026. newsroom.arm.com
13 Behind The Scenes of SHD Group's 2026 RISC-V Market Forecast. RISC-V International, 19 June 2026. riscv.org
14 3.5D XDSiP Platform Technology. Broadcom, 4 December 2024. docs.broadcom.com
15 UCIe specifications. UCIe Consortium, accessed 9 September 2026. uciexpress.org

03

Who makes the design software and custom chips

Design software, simulation software and licensed blocks made up an $18 billion market in 2025, on SemiAnalysis's count[2]. Synopsys, Cadence and Siemens EDA took more than 85 percent of it, counting Ansys as part of Synopsys[2]. No other vendor had more than 5 percent of any of the main categories of design software[2]. Siemens EDA is a US-based subsidiary of the German firm Siemens[16].


Synopsys is the largest. Its own results put revenue at $7.054 billion for the fiscal year to 31 October 2025, with Ansys, bought that July, contributing $756.6 million[17]. Cadence, whose year ends in December, took $5.297 billion in calendar 2025[18].

The two fiscal years do not line up, so any total for this market depends on which twelve months are counted. It also depends on how much of Ansys the total includes, because Ansys sells to other industries too. SemiAnalysis puts 31 percent of Ansys's business in semiconductors and high technology, 22 percent in aerospace and 18 percent in automotive[2]. It counts Synopsys at $8 billion for calendar 2025 with Ansys included[2]. On the same count Cadence is second, at $5.30 billion, and Siemens EDA third, at an estimated $2.2 billion to $2.5 billion[2].

Figure 01.4

Synopsys took 44 percent of the 2025 market, Cadence 30 percent

Share of revenue from design software, simulation software and licensed blocks, 2025. Synopsys includes part of Ansys's revenue



Source: SemiAnalysis, EDA Market Primer, May 2026, table of calendar 2025 vendor shares [2]

Chip firms such as Broadcom build custom accelerators to a customer's design and sell the finished chips. Broadcom booked $16.7 billion of AI semiconductor revenue in the third quarter of fiscal 2026, up 221 percent year over year[8]. That figure covers both its custom AI accelerators and its AI networking chips[8].

Broadcom's custom-chip customers include OpenAI and Meta. In October 2025 OpenAI and Broadcom said they would deploy OpenAI-designed accelerators drawing 10 gigawatts of power[19]. Broadcom would turn the design into silicon and supply the Ethernet networking around it[19]. In April 2026 Broadcom and Meta extended their

2 EDA Market Primer. SemiAnalysis, 21 May 2026. newsletter.semianalysis.com

8 Broadcom, current report on Form 8-K dated 2 September 2026. U.S. Securities and Exchange Commission, 2 September 2026. sec.gov

16 The Double-Edged Sword of Semiconductor Export Controls: Electronic Design... Center for Strategic and International Studies, 6 October 2025, p. 7. csis-website-prod.s3.amazonaws.com

17 Synopsys, current report on Form 8-K dated 10 December 2025. U.S. Securities and Exchange Commission, 10 December 2025. sec.gov

18 Cadence Design Systems, current report on Form 8-K dated 17 February 2026. U.S. Securities and Exchange Commission, 17 February 2026. sec.gov

19 OpenAI and Broadcom announce strategic collaboration to deploy 10 gigawatts of... Broadcom, 13 October 2025. investors.broadcom.com

partnership to multiple gigawatts of MTIA, Meta's custom chip, including what they called the industry's first 2 nm AI accelerator[20].

Marvell, another US firm, also builds custom AI chips to each customer's specifications[21]. Taiwanese design-service houses carry a customer's circuit list, the logic cells and the wires between them, all the way to a finished mask set on TSMC's newest nodes. One of them, Alchip, reported $992 million of revenue in 2025[22].

India has nearly 20 percent of the world's chip design engineers, the Indian government said in July 2025[23].

04

Design software export controls and China's own tools

In October 2025 CSIS found that only three companies, Cadence, Synopsys and Siemens, make design software that supports the entire chip design flow of more than 40 steps[6]. In late May 2025 the US Bureau of Industry and Security, the agency that issues export licenses, told the design-software vendors that sales to China now needed a license[5]. Synopsys got its letter on 29 May and a second letter lifting the requirement on 2 July[24]. CSIS found that as of 2025 Chinese design tools were still far from replacing the full range of advanced capabilities US firms offer, especially for 5 nm and 3 nm chip design[4].

Before the 2025 letters, a narrower control already applied. Since 14 October 2022, design software specially made for chips with gate-all-around transistors has needed a US export license for national-security reasons[3]. The rule calls that transistor design key to processes at 3 nm and below[3]. That license requirement covers exports to China[25]. The control carried out a December 2021 decision of the Wassenaar Arrangement, a group of countries that coordinate export controls[3].

Cadence got its letter on 23 May[5]. The letter required a license to export design software and technology classified 3D991 and 3E991 to any party in China, or to a Chinese military end user anywhere[5]. Unlike the 2022 control, the 2025 requirement came from the United States alone and took effect immediately.

Synopsys's China revenue fell from 16 percent of its total in fiscal 2024 to 12 percent in fiscal 2025[2]. SemiAnalysis links the decline to tighter export restrictions and to local design-software companies winning share at mature nodes[2]. SemiAnalysis also quoted

2 EDA Market Primer. SemiAnalysis, 21 May 2026. newsletter.semianalysis.com

3 Implementation of Certain 2021 Wassenaar Arrangement Decisions on Four Section... Federal Register, 15 August 2022. federalregister.gov

4 The Double-Edged Sword of Semiconductor Export Controls: Electronic Design... Center for Strategic and International Studies, 6 October 2025, p. 33. csis-website-prod.s3.amazonaws.com

5 Cadence Design Systems, current report on Form 8-K dated 2 July 2025. U.S. Securities and Exchange Commission, 3 July 2025. sec.gov

6 The Double-Edged Sword of Semiconductor Export Controls: Electronic Design... Center for Strategic and International Studies, 6 October 2025, p. 13. csis-website-prod.s3.amazonaws.com

20 Broadcom Announces Extended Partnership with Meta to Deploy Technology to... Broadcom, 14 April 2026. investors.broadcom.com

21 Marvell Technology, annual report on Form 10-K for the fiscal year ended 31... U.S. Securities and Exchange Commission, 11 March 2026. sec.gov

22 Alchip Technologies, financials page. Alchip Technologies, accessed 9 September 2026. alchip.com

23 India's Semiconductor Vision Gathers Momentum with 3nm Chip Design and... Press Information Bureau, Government of India, 25 July 2025. pib.gov.in

24 Synopsys, current report on Form 8-K dated 2 July 2025. U.S. Securities and Exchange Commission, 3 July 2025. sec.gov

25 Supplement No. 1 to Part 738, Title 15 -- Commerce Country Chart. Electronic Code of Federal Regulations, 30 September 2025. ecfr.gov

Synopsys's management saying that when Synopsys cannot sell to a company, that company looks for alternatives, typically local design-software and licensed-block companies[2].

In a January 2021 report built on 2019 market data, the Center for Security and Emerging Technology (CSET) at Georgetown University found that one Chinese firm, Empyrean, could reportedly run a complete design flow only for some analog and mixed-signal chips[26]. Mixed-signal chips combine analog and digital circuits. For all other chips, Chinese designers then relied on US tools[26]. The report found that other Chinese tools covered only narrow parts of the design flow or supplemented US tools, and largely did not support processes at 14 nm and below[26].

Empyrean says it has covered more of the design flow since then. Its 2025 annual report, filed in April 2026, says it now has complete design flows for analog, memory, radio-frequency and flat-panel display circuits[27]. It says it offers 80 percent of the main tools used in digital design[28]. The same report lists foundry certifications for its circuit simulator at 8, 5 and 4 nm and for its physical verification tool, the final layout check, at 28 nm[29].

China can design accelerators, but it cannot finish one at the leading edge without foreign tools, or build what it designs without foreign equipment. SMIC, China's leading foundry, makes chips for Huawei[9]. In June 2024 CSET found that SMIC's limited 7 nm capacity forced Huawei to choose between making its most advanced phone chips and its AI chips[30].

Epoch AI estimates that Huawei trails Nvidia both in what each chip can do and in how many chips it makes[9]. On Epoch's estimates, Huawei's flagship chip for 2026, the Ascend 950, delivers about half the computing performance of Nvidia's H100, which began shipping in 2022[9]. Epoch puts Nvidia's B300 at 6.75 times the 950's theoretical peak performance[9]. Epoch's median estimate is that Huawei will make about 1.5 million Ascend chips in 2026, against 5.9 million for Nvidia[9]. On those estimates, Huawei's 2026 output would carry less than 4 percent of the computing power Nvidia ships that year[9].

Epoch puts Huawei's chips three to four years behind Nvidia's until at least 2030, for three reasons[9]. SMIC cannot pack transistors as densely as TSMC, which makes Nvidia's. Chinese memory makers are only starting to produce high-bandwidth memory. And Huawei's software for programming its chips is far less mature than Nvidia's[9].

Five questions to answer from memory

1. What does chip design produce? see How it works

2 **EDA Market Primer.** SemiAnalysis, 21 May 2026. newsletter.semianalysis.com

9 **Will Huawei catch up to Nvidia by 2030?** Epoch AI, 24 September 2026. epoch.ai

26 **The Semiconductor Supply Chain - Issue Brief.** Center for Security and Emerging Technology, 21 January 2021, p. 50. cset.georgetown.edu

27 北京华大九天科技股份有限公司2025年年度报告全文. CNINFO, 27 April 2026, p. 18. static.cninfo.com.cn

28 北京华大九天科技股份有限公司2025年年度报告全文. CNINFO, 27 April 2026, p. 14. static.cninfo.com.cn

29 北京华大九天科技股份有限公司2025年年度报告全文. CNINFO, 27 April 2026, p. 15. static.cninfo.com.cn

30 **Pushing the Limits: Huawei's AI Chip Tests U.S. Export Controls.** Center for Security and Emerging Technology, 17 June 2024. cset.georgetown.edu

2. Which three companies sell the software used to design leading-edge chips? see Who makes it
3. Why is it hard for a new company to compete with Synopsys, Cadence and Siemens EDA? see The chokepoint
4. How close are Chinese design tools to replacing US tools for the newest chips? see The chokepoint
5. How far behind Nvidia is Huawei's best AI chip? see The chokepoint

---

Five things to remember

- Chip design turns an idea into a blueprint, and a factory builds only designs checked in approved software.
- Synopsys, Cadence and Siemens EDA sell the software used to design every leading-edge AI chip.
- To compete with them, a new vendor would have to write a complete set of tools and win a foundry's approval.
- China designs its own AI chips, but in October 2025 CSIS found its design software still far from replacing US tools, especially for 5 nm and 3 nm chips.
- Huawei's best AI chip trails Nvidia's by three to four years, on Epoch AI's estimate.

Sources (30)

1. B The Dark Side Of The Semiconductor Design Renaissance – Fixed Costs Soaring Due To Photomask Sets, Verification, and Validation. SemiAnalysis · 24 July 2022
   newsletter.semianalysis.com/p/the-dark-side-of-the-semiconductor
2. B EDA Market Primer. SemiAnalysis · 21 May 2026
   newsletter.semianalysis.com/p/eda-market-primer
3. A Implementation of Certain 2021 Wassenaar Arrangement Decisions on Four Section 1758 Technologies. Federal Register (Commerce Department; Industry and Security Bureau) · 15 August 2022
   www.federalregister.gov/documents/2022/08/15/2022-17125/implementation-of-certain-2021-wassenaar-arrangement-decisions-on-four-section-1758-technologies
4. A The Double-Edged Sword of Semiconductor Export Controls: Electronic Design Automation. Center for Strategic and International Studies · 6 October 2025 · p. 33
   csis-website-prod.s3.amazonaws.com/s3fs-public/2025-10/251006_Reinsch_Semiconductor_Export_0.pdf#page=33
5. A Cadence Design Systems, current report on Form 8-K dated 2 July 2025. U.S. Securities and Exchange Commission (filing by Cadence Design Systems) · 3 July 2025
   www.sec.gov/Archives/edgar/data/813672/000081367225000093/cdns-20250702.htm
6. A The Double-Edged Sword of Semiconductor Export Controls: Electronic Design Automation. Center for Strategic and International Studies · 6 October 2025 · p. 13
   csis-website-prod.s3.amazonaws.com/s3fs-public/2025-10/251006_Reinsch_Semiconductor_Export_0.pdf#page=13
7. A Arm delivers record-breaking quarter and full-year results. Arm · 6 May 2026
   newsroom.arm.com/news/arm-q4-fye26-results
8. A Broadcom, current report on Form 8-K dated 2 September 2026. U.S. Securities and Exchange Commission (filing by Broadcom) · 2 September 2026
   www.sec.gov/Archives/edgar/data/0001730168/000173016826000076/avgo-08022026x8kxex99.htm
9. A Will Huawei catch up to Nvidia by 2030?. Epoch AI · 24 September 2026
   epoch.ai/publications/huaweis-roadmap-to-2031
10. A Unlocking post-tapeout flow scalability and performance with cloud computing. Siemens Digital Industries Software · 8 January 2025
    blogs.sw.siemens.com/calibre/2025/01/08/unlocking-post-tapeout-flow-scalability-and-performance-with-cloud-computing/
11. A Ironwood: The first Google TPU for the age of inference. Google · 9 April 2025
    blog.google/innovation-and-ai/infrastructure-and-cloud/google-cloud/ironwood-tpu-age-of-inference/
12. A Our eighth generation TPUs: two chips for the agentic era. Google · 22 April 2026
    blog.google/innovation-and-ai/infrastructure-and-cloud/google-cloud/eighth-generation-tpu-agentic-era/
13. A Behind The Scenes of SHD Group's 2026 RISC-V Market Forecast. RISC-V International · 19 June 2026
    riscv.org/blog/shd-forecast-2026/
14. A 3.5D XDSiP Platform Technology. Broadcom · 4 December 2024
    docs.broadcom.com/doc/3-5d-xdsip-platform-technology
15. A UCIe specifications. UCIe Consortium · Accessed 9 September 2026
    www.uciexpress.org/specifications

16. A The Double-Edged Sword of Semiconductor Export Controls: Electronic Design Automation. Center for Strategic and International Studies · 6 October 2025 · p. 7
csis-website-prod.s3.amazonaws.com/s3fs-public/2025-10/251006_Reinsch_Semiconductor_Export_0.pdf#page=7
17. A Synopsys, current report on Form 8-K dated 10 December 2025. U.S. Securities and Exchange Commission (filing by Synopsys) · 10 December 2025
www.sec.gov/Archives/edgar/data/883241/000119312525314200/d29055dex991.htm
18. A Cadence Design Systems, current report on Form 8-K dated 17 February 2026. U.S. Securities and Exchange Commission (filing by Cadence Design Systems) · 17 February 2026
www.sec.gov/Archives/edgar/data/813672/000081367226000013/cdns02172026ex9901.htm
19. A OpenAI and Broadcom announce strategic collaboration to deploy 10 gigawatts of OpenAI-designed AI accelerators. Broadcom · 13 October 2025
investors.broadcom.com/news-releases/news-release-details/openai-and-broadcom-announce-strategic-collaboration-deploy-10
20. A Broadcom Announces Extended Partnership with Meta to Deploy Technology to Support Multi-Gigawatts of Meta's Custom Silicon, MTIA. Broadcom · 14 April 2026
investors.broadcom.com/news-releases/news-release-details/broadcom-announces-extended-partnership-meta-deploy-technology
21. A Marvell Technology, annual report on Form 10-K for the fiscal year ended 31 January 2026. U.S. Securities and Exchange Commission (filing by Marvell Technology) · 11 March 2026
www.sec.gov/Archives/edgar/data/1835632/000183563226000011/mrvl-20260131.htm
22. A Alchip Technologies, financials page. Alchip Technologies · Accessed 9 September 2026
www.alchip.com/en/Investors/financials/
23. A India's Semiconductor Vision Gathers Momentum with 3nm Chip Design and Large-Scale Talent Development Initiatives. Press Information Bureau, Government of India · 25 July 2025
www.pib.gov.in/PressReleasePage.aspx?PRID=2148393
24. A Synopsys, current report on Form 8-K dated 2 July 2025. U.S. Securities and Exchange Commission (filing by Synopsys) · 3 July 2025
www.sec.gov/Archives/edgar/data/883241/000119312525155294/d80081d8k.htm
25. A Supplement No. 1 to Part 738, Title 15 -- Commerce Country Chart. Electronic Code of Federal Regulations · 30 September 2025
www.ecfr.gov/current/title-15/subtitle-B/chapter-VII/subchapter-C/part-738/appendix-Supplement%20No.%201%20to%20Part%20738
26. A The Semiconductor Supply Chain - Issue Brief. Center for Security and Emerging Technology (CSET) · 21 January 2021 · p. 50
cset.georgetown.edu/wp-content/uploads/The-Semiconductor-Supply-Chain-Issue-Brief-1.pdf#page=50
27. A 北京华大九天科技股份有限公司2025年年度报告全文. CNINFO · 27 April 2026 · p. 18
static.cninfo.com.cn/finalpage/2026-04-28/1225217315.PDF#page=18
28. A 北京华大九天科技股份有限公司2025年年度报告全文. CNINFO · 27 April 2026 · p. 14
static.cninfo.com.cn/finalpage/2026-04-28/1225217315.PDF#page=14
29. A 北京华大九天科技股份有限公司2025年年度报告全文. CNINFO · 27 April 2026 · p. 15
static.cninfo.com.cn/finalpage/2026-04-28/1225217315.PDF#page=15
30. A Pushing the Limits: Huawei's AI Chip Tests U.S. Export Controls. Center for Security and Emerging Technology (CSET) · 17 June 2024
cset.georgetown.edu/publication/pushing-the-limits-huaweis-ai-chip-tests-u-s-export-controls/

Made by **Yashvardhan Sharma**. Corrections and questions: contact@chipsupplychain.org.

A company filings, governments, standards bodies, universities and research institutions; B SemiAnalysis, Reuters, the Financial Times and Nikkei Asia.

How to cite this chapter

> Sharma, Yashvardhan. "Chip Design, EDA and IP." *Chip Supply Chain: How AI Chips Are Made*. Edition of 29 October 2026. https://chipsupplychain.org/design-and-eda/

```
@misc{chipsupplychain2026designandeda,
  title        = {Chip Design, EDA and IP},
  author       = {Sharma, Yashvardhan},
  howpublished = {Chip Supply Chain: How AI Chips Are Made},
  year         = {2026},
  month        = {October},
  note         = {Edition of 29 October 2026},
  url          = {https://chipsupplychain.org/design-and-eda/}
}
```