

CSE 202: Spring 2017
Data Lab: Manipulating Bits
Assigned: Jan 26th, Due: Monday, February 6th, 9:00PM

1 Introduction

The purpose of this assignment is to become more familiar with bit-level representations of integers and floating point numbers. You'll do this by solving a series of programming "puzzles." Many of these puzzles are quite artificial, but you'll find yourself thinking much more about bits in working your way through them.

2 Logistics

This is an individual project. All handins are electronic. Clarifications and corrections will be communicated in-class, via email, via CourseSite or via Piazza.

3 Handout Instructions

All work must be done using the sunlab machines. They can be accessed via SSH at `sunlab.cse.lehigh.edu`. Start by navigating to the directory in which you want to store your work. Make sure the folder is not readable by your classmates! If you are unsure how to create protected space, you can use the following commands:

```
unix> mkdir cse202
unix> chmod 700 cse202
```

Download `datalab-handout.tar` from CourseSite.

Alternatively, you may copy it from `~jloew/datalab-handout.tar`

Start by copying `datalab-handout.tar` to a (protected) directory on the sunlab machines. Then give the command

```
unix> tar xvf datalab-handout.tar
```

This will cause a number of files to be unpacked in the directory. The only file you will be modifying and turning in is `bits.c`.

The `bits.c` file contains a skeleton for each of the 21 programming puzzles. Your assignment is to complete each function skeleton using only *straightline* code for the integer puzzles (i.e., no loops or conditionals) and a limited number of C arithmetic and logical operators. Specifically, you are *only* allowed to use the following eight operators:

```
! ~ & ^ | + << >>
```

A few of the functions further restrict this list. Also, you are not allowed to use any constants longer than 8 bits. See the comments in `bits.c` for detailed rules and a discussion of the desired coding style.

4 The Puzzles

This section provides some background regarding the puzzles that you will be solving in `bits.c`.

For each puzzle, the source code (`bits.c`) contains comments that describe the problem, provide some examples, detail the legal operations, specify the maximum number of operators allowed and provide the rating, or difficulty, of each puzzle.

You may also refer to the test functions in `tests.c`. These are used as reference functions to express the correct behavior of your functions, although they don't satisfy the coding rules for your functions.

4.1 Floating-Point Operations

For this part of the assignment, you will implement some common single-precision floating-point operations. In this section, you are allowed to use standard control structures (conditionals, loops), and you may use both `int` and `unsigned` data types, including arbitrary unsigned and integer constants. You may not use any unions, structs, or arrays. Most significantly, you may not use any floating point data types, operations, or constants. Instead, any floating-point operand will be passed to the function as having type `unsigned`, and any returned floating-point value will be of type `unsigned`. Your code should perform the bit manipulations that implement the specified floating point operations.

Functions `float_neg` and `float_twice` must handle the full range of possible argument values, including not-a-number (NaN) and infinity. The IEEE standard does not specify precisely how to handle NaN's, and the IA32 behavior is a bit obscure. We will follow a convention that for any function returning a NaN value, it will return the one with bit representation `0x7FC00000`.

The included program `fshow` helps you understand the structure of floating point numbers. To compile `fshow`, switch to the handout directory and type:

```
unix> make
```

You can use `fshow` to see what an arbitrary pattern represents as a floating-point number:

```
unix> ./fshow 2080374784
```

```
Floating point value 2.658455992e+36
```

```
Bit Representation 0x7c000000, sign = 0, exponent = f8, fraction = 000000
```

```
Normalized. 1.0000000000 X 2^(121)
```

You can also give `fshow` hexadecimal and floating point values, and it will decipher their bit structure.

5 Evaluation

Your score will be computed out of a maximum of 100 points based on the following distribution:

53 Correctness points.

42 Performance points.

5 Style points.

Correctness points. The 21 puzzles you must solve have been given a difficulty rating between 1 and 4. We will evaluate your functions using the `btest` program, which is described in the next section. You will get full credit for a puzzle if it passes all of the tests performed by `btest`, and no credit otherwise.

Performance points. Our main concern at this point in the course is that you can get the right answer. However, we want to instill in you a sense of keeping things as short and simple as you can. Furthermore, some of the puzzles can be solved by brute force, but we want you to be more clever. Thus, for each function we've established a maximum number of operators that you are allowed to use for each function. This limit is very generous and is designed only to catch egregiously inefficient solutions. You will receive two points for each correct function that satisfies the operator limit.

Style points. Finally, we've reserved 5 points for a subjective evaluation of the style of your solutions and your commenting. Your solutions should be as clean and straightforward as possible. Your comments should be informative, but they need not be extensive.

Autograding your work

We have included some autograding tools in the handout directory — `btest`, `dlc`, and `driver.pl` — to help you check the correctness of your work.

- **btest**: This program checks the functional correctness of the functions in `bits.c`. To build and use it, type the following two commands:

```
unix> make
unix> ./btest
```

Notice that you must rebuild `btest` each time you modify your `bits.c` file.

You'll find it helpful to work through the functions one at a time, testing each one as you go. You can use the `-f` flag to instruct `btest` to test only a single function:

```
unix> ./btest -f bitAnd
```

You can feed it specific function arguments using the option flags `-1`, `-2`, and `-3`:

```
unix> ./btest -f bitAnd -1 7 -2 0xf
```

Check the file `README` for documentation on running the `btest` program.

- **dlc:** This is a modified version of an ANSI C compiler from the MIT CILK group that you can use to check for compliance with the coding rules for each puzzle. The typical usage is:

```
unix> ./dlc bits.c
```

The program runs silently unless it detects a problem, such as an illegal operator, too many operators, or non-straightline code in the integer puzzles. Running with the `-e` switch:

```
unix> ./dlc -e bits.c
```

causes `dlc` to print counts of the number of operators used by each function. Type `./dlc -help` for a list of command line options.

- **driver.pl:** This is a driver program that uses `btest` and `dlc` to compute the correctness and performance points for your solution. It takes no arguments:

```
unix> ./driver.pl
```

Your instructors will use `driver.pl` to evaluate your solution.

6 Handin Instructions

To submit your work, simply enter:

```
unix> make submit
```

This will submit your work to a remote server. You should see a message confirming that your file was submitted successfully. You may submit more than once, but only the most recent submission will be graded.

7 Advice

- Don't include the `<stdio.h>` header file in your `bits.c` file, as it confuses `dlc` and results in some non-intuitive error messages. You will still be able to use `printf` in your `bits.c` file for debugging without including the `<stdio.h>` header, although `gcc` will print a warning that you can ignore.
- The `dlc` program enforces a stricter form of C declarations than is the case for C++ or that is enforced by `gcc`. In particular, any declaration must appear in a block (what you enclose in curly braces) before any statement that is not a declaration. For example, it will complain about the following code:

```
int foo(int x)
{
    int a = x;
    a *= 3;      /* Statement that is not a declaration */
    int b = a;   /* ERROR: Declaration not allowed here */
}
```