

1. **/topic/tracker/login/{IMEI} - Publish (When the device is connected to the internet it will publish first message on this topic)**

2024-07-09 13:03:03.999

Topic: /topic/tracker/login/863471065047747 QoS: 0

863471065047747

2024-07-09 13:03:12:920

2. **/topic/tracker/{IMEI} - Subscribe (This topic is used when sending a command to the device)**

Topic: /topic/tracker/863471065047747 QoS: 1

checking

2024-07-09 13:06:14:751

3. /topic/tracker/cmd/{IMEI} - Publish (Response from the device after command is successfully executed is published on this topic)

Topic: /topic/tracker/cmd/863471065047747 QoS: 0

SERVER: byte-iot.net:1883
REGISTRATION: NONE
IMEI: 863471065047747
ICCID: 89254035030038009000
APN: auto
SPEED LIMIT: 80km/h
ALARM SPEED: 0km/h
TIMEZONES: 12
POWER: 21.7V
ACC: connected
SPEED: 0km/h
LOCK: false
MOVE: disable
SERVICE: connected
Powered by NIOT

2024-07-09 13:08:07:968

5. `/topic/tracker/wifi/{IMEI}` - Publish (WiFi parameters are published on this topic)
Pic 1 Shows payload when No device is connected to the device WiFi

```
Topic: /topic/tracker/wifi/863471065047747  QoS: 0
{
  "imei": "863471065047747",
  "config": {
    "ssid": "4G-MIFI_A2E7",
    "hidden": false,
    "key": "12345678",
    "disabled": false,
    "channel": 6,
    "macaddr": "14:CB:49:02:A2:E7"
  },
  "clients_info": {
  }
}
```

2024-07-09 13:08:21:820

Pic 2 Is the payload when a device is connected to the device WiFi

Topic: /topic/tracker/wifi/863471065047747 QoS: 0

```
{
  "imei": "863471065047747",
  "config": {
    "ssid": "4G-MIFI_A2E7",
    "hidden": false,
    "key": "12345678",
    "disabled": false,
    "channel": 6,
    "macaddr": "14:CB:49:02:A2:E7"
  },
  "clients_info": {
    "one_client": {
      "mac": "62:82:29:CE:29:FF",
      "ip": "192.168.100.109",
      "name": "Pixel-8",
      "type": "WIFI",
      "cur_conn_time": "7"
    }
  }
}
```

2024-07-09 13:16:45:859