

You submitted this quiz on **Tue 17 May 2016 5:05 PM CST**. You got a score of **375.00** out of **400.00**. However, you will not get credit for it, since it was submitted past the deadline.

Question 1

Recall that N is the size of the data set and d is the dimensionality of the input space. The primal formulation of the linear soft-margin support vector machine problem, without going through the Lagrangian dual problem, is

Your Answer	Score	Explanation
<input type="radio"/> a quadratic programming problem with $2N$ variables		
<input checked="" type="radio"/> a quadratic programming problem with $N + d + 1$ variables	✓ 20.00	
<input type="radio"/> a quadratic programming problem with $d + 1$ variables		
<input type="radio"/> a quadratic programming problem with N variables		
<input type="radio"/> none of the other choices		
Total	20.00 / 20.00	

Question 2

Consider the following training data set:

$\mathbf{x}_1 = (1, 0), y_1 = -1$ $\mathbf{x}_2 = (0, 1), y_2 = -1$ $\mathbf{x}_3 = (0, -1), y_3 = -1$

$\mathbf{x}_4 = (-1, 0), y_4 = +1$ $\mathbf{x}_5 = (0, 2), y_5 = +1$ $\mathbf{x}_6 = (0, -2), y_6 = +1$

$\mathbf{x}_7 = (-2, 0), y_7 = +1$

Use following nonlinear transformation of the input vector $\mathbf{x} = (x_1, x_2)$ to the transformed vector $\mathbf{z} = (\phi_1(\mathbf{x}), \phi_2(\mathbf{x}))$:

$$\phi_1(\mathbf{x}) = x_2^2 - 2x_1 + 3$$

$$\phi_2(\mathbf{x}) = x_1^2 - 2x_2 - 3$$

What is the equation of the optimal separating "hyperplane" in the \mathcal{Z} space?

Your Answer	Score	Explanation
<input type="radio"/> $z_1 + z_2 = 4.5$		
<input type="radio"/> $z_1 - z_2 = 4.5$		
<input checked="" type="radio"/> $z_1 = 4.5$	✓ 20.00	
<input type="radio"/> $z_2 = 4.5$		
<input type="radio"/> none of the other choices		
Total	20.00 / 20.00	

Question 3

Consider the same training data set as Question 2, but instead of explicitly transforming the input space \mathcal{X} to \mathcal{Z} , apply the hard-margin support vector machine algorithm with the kernel function


$$K(\mathbf{x}, \mathbf{x}') = (1 + \mathbf{x}^T \mathbf{x}')^2,$$

which corresponds to a second-order polynomial transformation. Set up the optimization problem using $(\alpha_1, \dots, \alpha_7)$ and numerically solve for them (you can use any package you want). Which of the following is true about the optimal α ?

Your Answer	Score	Explanation
<input type="radio"/> there are 6 nonzero α_n		
<input type="radio"/> none of the other choices		
<input checked="" type="radio"/> $\min_{1 \leq n \leq 7} \alpha_n = \alpha_7$	✓ 20.00	
<input type="radio"/> $\max_{1 \leq n \leq 7} \alpha_n = \alpha_7$		
<input type="radio"/> $\sum_{n=1}^7 \alpha_n = 5$		
Total	20.00 / 20.00	


Question 4

Following Question 3, what is the corresponding nonlinear curve in the \mathcal{X} space?

Your Answer	Score	Explanation
<input type="radio"/> $\frac{1}{9} (8x_2^2 - 16x_2 + 6x_1^2 + 15) = 0$		
<input type="radio"/> none of the other choices		
<input checked="" type="radio"/> $\frac{1}{9} (8x_1^2 - 16x_1 + 6x_2^2 - 15) = 0$	 20.00	
<input type="radio"/> $\frac{1}{9} (8x_1^2 - 16x_1 + 6x_2^2 + 15) = 0$		
<input type="radio"/> $\frac{1}{9} (8x_2^2 - 16x_2 + 6x_1^2 - 15) = 0$		
Total	20.00 / 20.00	

Question 5

Compare the two nonlinear curves found in Questions 2 and 4, which of the following is true?

Your Answer	Score	Explanation
<input checked="" type="radio"/> The curves should be different in the \mathcal{X} space, because they are learned with respect to different \mathcal{Z} spaces	 20.00	
<input type="radio"/> none of the other choices		
<input type="radio"/> The curves should be different in the \mathcal{X} space, because they are learned from different raw data $\{(\mathbf{x}_n, y_n)\}$		
<input type="radio"/> The curves should be the same in the \mathcal{X} space, because they are learned with respect to the same \mathcal{Z} space		
<input type="radio"/> The curves should be the same in the \mathcal{X} space, because they are learned from the same raw data $\{(\mathbf{x}_n, y_n)\}$		
Total	20.00 / 20.00	

Question 6

Recall that for support vector machines, d_{vc} is upper bounded by $\frac{R^2}{\rho^2}$, where ρ is the margin and R is the radius of the minimum hypersphere that \mathcal{X} resides in. In general, R should come from our knowledge on the learning problem, but we can estimate it by looking at the minimum hypersphere that the training examples resides in. In particular, we want to seek for the optimal R that solves

(P)
$$\min_{R \in \mathbb{R}, \mathbf{c} \in \mathbb{R}^d} R^2 \quad \text{subject to } \|\mathbf{x}_n - \mathbf{c}\|^2 \leq R^2 \text{ for } n = 1, 2, \dots, N.$$

Let λ_n be the Lagrange multipliers for the n -th constraint above. Following the derivation of the dual support vector machine in class, write down (P) as an equivalent optimization problem

$$\min_{R \in \mathbb{R}, \mathbf{c} \in \mathbb{R}^d} \max_{\lambda_n \geq 0} L(R, \mathbf{c}, \lambda).$$

What is $L(R, \mathbf{c}, \lambda)$?

Your Answer	Score	Explanation
<input type="radio"/> $R^2 - \sum_{n=1}^N \lambda_n (\ \mathbf{x}_n - \mathbf{c}\ ^2 - R^2)$		
<input type="radio"/> none of the other choices		
<input checked="" type="radio"/> $R^2 + \sum_{n=1}^N \lambda_n (\ \mathbf{x}_n - \mathbf{c}\ ^2 - R^2)$	✓ 20.00	
<input type="radio"/> $R^2 - \sum_{n=1}^N \lambda_n (\ \mathbf{x}_n - \mathbf{c}\ ^2 + R^2)$		
<input type="radio"/> $R^2 + \sum_{n=1}^N \lambda_n (\ \mathbf{x}_n - \mathbf{c}\ ^2 + R^2)$		
Total	20.00 / 20.00	

Question 7

Using (assuming) strong duality, the solution to (P) in Question 6 would be the same as the Lagrange dual problem

(D)
$$\max_{\lambda_n \geq 0} \min_{R \in \mathbb{R}, \mathbf{c} \in \mathbb{R}^d} L(R, \mathbf{c}, \lambda).$$

Which of the following can be derived from the KKT conditions of (P) and (D) at the optimal (R, \mathbf{c}, λ) ?

Your Answer	Score	Explanation
-------------	-------	-------------

☐ if $\|\mathbf{x}_n - \mathbf{c}\|^2 - R^2 = 0$

☐ if $\lambda_n = 0$, then $\|\mathbf{x}_n - \mathbf{c}\|^2 - R^2 = 0$

☒ if $R \neq 0$, then $\sum_{n=1}^N \lambda_n = 1$ ✔ 20.00

☐ if $\sum_{n=1}^N \lambda_n = 0$, then $\mathbf{c} = \left(\sum_{n=1}^N \lambda_n \mathbf{x}_n \right) / \left(\sum_{n=1}^N \lambda_n \right)$

☐ none of the other choices

Total

20.00 / 20.00

Question 8

Continue from Question 7 and assume that all the \mathbf{x}_n are different, which implies that the optimal $R > 0$. Using the KKT conditions to simplify the Lagrange dual problem, and obtain a dual problem that involves only λ_n . One form of the dual problem should look like

$$(D') \quad \max_{\lambda_n \geq 0} \quad \text{Objective}(\lambda) \quad \text{subject to} \quad \sum_{n=1}^N \lambda_n = \text{constant}$$

Which of the following is $\text{Objective}(\lambda)$?

Your Answer

Score

Explanation

☒ $\sum_{n=1}^N \lambda_n (\|\mathbf{x}_n - \sum_{m=1}^N \lambda_m \mathbf{x}_m\|^2)$ ✔ 20.00

☐ $\sum_{n=1}^N \lambda_n (\|\mathbf{x}_n + \sum_{m=1}^N \lambda_m \mathbf{x}_m\|^2) + 2(\sum_{n=1}^N \lambda_n \mathbf{x}_n)^2$

☐ $\sum_{n=1}^N \lambda_n (\|\mathbf{x}_n + \sum_{m=1}^N \lambda_m \mathbf{x}_m\|^2)$

☐ none of the other choices

☐ $\sum_{n=1}^N \lambda_n (\|\mathbf{x}_n - \sum_{m=1}^N \lambda_m \mathbf{x}_m\|^2) + 2(\sum_{n=1}^N \lambda_n \mathbf{x}_n)^2$

Total

20.00 / 20.00

Question 9

Continue from Question 8 and consider using $\mathbf{z}_n = \phi(\mathbf{x}_n)$ instead of \mathbf{x}_n while assuming that all

the \mathbf{z}_n are different. Then, write down the optimization problem that uses $K(\mathbf{x}_n, \mathbf{x}_m)$ to replace $\mathbf{z}_n^T \mathbf{z}_m$ ---that is, the kernel trick. Which of the following is $\text{Objective}(\lambda)$ of (D') after applying the kernel trick?

Your Answer	Score	Explanation
<input checked="" type="radio"/> $\sum_{n=1}^N \lambda_n K(\mathbf{x}_n, \mathbf{x}_n) - 1 \sum_{n=1}^N \sum_{m=1}^N \lambda_n \lambda_m K(\mathbf{x}_n, \mathbf{x}_m)$	<div> <div>✓</div> <div>20.00</div> </div>	
<input type="radio"/> $\sum_{n=1}^N \lambda_n K(\mathbf{x}_n, \mathbf{x}_n) + 3 \sum_{n=1}^N \sum_{m=1}^N \lambda_n \lambda_m K(\mathbf{x}_n, \mathbf{x}_m)$		
<input type="radio"/> $\sum_{n=1}^N \lambda_n K(\mathbf{x}_n, \mathbf{x}_n) + 1 \sum_{n=1}^N \sum_{m=1}^N \lambda_n \lambda_m K(\mathbf{x}_n, \mathbf{x}_m)$		
<input type="radio"/> none of the other choices		
<input type="radio"/> $\sum_{n=1}^N \lambda_n K(\mathbf{x}_n, \mathbf{x}_n) - 3 \sum_{n=1}^N \sum_{m=1}^N \lambda_n \lambda_m K(\mathbf{x}_n, \mathbf{x}_m)$		
Total	20.00 / 20.00	

Question 10

Continue from Question 9 and solve the (D') that involves the kernel K , which of the following formula evaluates the optimal R ?

Your Answer	Score	Explanation
<input type="radio"/> Pick some i with $\lambda_i > 0$, and $R = \sqrt{K(\mathbf{x}_i, \mathbf{x}_i) + 2 \sum_{m=1}^N \lambda_m K(\mathbf{x}_i, \mathbf{x}_m) + \sum_{n=1}^N \sum_{m=1}^N \lambda_n \lambda_m K(\mathbf{x}_n, \mathbf{x}_m)}$		
<input type="radio"/> none of the other choices		
<input checked="" type="radio"/> Pick some i with $\lambda_i > 0$, and $R = \sqrt{K(\mathbf{x}_i, \mathbf{x}_i) - 2 \sum_{m=1}^N \lambda_m K(\mathbf{x}_i, \mathbf{x}_m) + \sum_{n=1}^N \sum_{m=1}^N \lambda_n \lambda_m K(\mathbf{x}_n, \mathbf{x}_m)}$	<div> <div>✓</div> <div>20.00</div> </div>	
<input type="radio"/> Pick some i with $\lambda_i = 0$, and $R = \sqrt{K(\mathbf{x}_i, \mathbf{x}_i) - 2 \sum_{m=1}^N \lambda_m K(\mathbf{x}_i, \mathbf{x}_m) + \sum_{n=1}^N \sum_{m=1}^N \lambda_n \lambda_m K(\mathbf{x}_n, \mathbf{x}_m)}$		
<input type="radio"/> Pick some i with $\lambda_i = 0$, and $R = \sqrt{K(\mathbf{x}_i, \mathbf{x}_i) + 2 \sum_{m=1}^N \lambda_m K(\mathbf{x}_i, \mathbf{x}_m) + \sum_{n=1}^N \sum_{m=1}^N \lambda_n \lambda_m K(\mathbf{x}_n, \mathbf{x}_m)}$		
Total	20.00 / 20.00	

Question 11

In the class, we taught the soft-margin support vector machine as follows.

$$(P_1) \quad \min_{\mathbf{w}, b, \xi} \quad \frac{1}{2} \mathbf{w}^T \mathbf{w} + C \sum_{n=1}^N \xi_n$$

$$\text{subject to } y_n (\mathbf{w}^T \mathbf{x}_n + b) \geq 1 - \xi_n,$$

$$\xi_n \geq 0.$$

The support vector machine (called ℓ_1 loss) penalizes the margin violation linearly. Another popular formulation (called ℓ_2 loss) penalizes the margin violation quadratically. In this problem, we show one simple approach for deriving the dual of such a formulation. The formulation is as follows.

$$(P'_2) \quad \min_{\mathbf{w}, b, \xi} \quad \frac{1}{2} \mathbf{w}^T \mathbf{w} + C \sum_{n=1}^N \xi_n^2$$

$$\text{subject to } y_n (\mathbf{w}^T \mathbf{x}_n + b) \geq 1 - \xi_n,$$

$$\xi_n \geq 0.$$

It is not hard to see that the constraints $\xi_n \geq 0$ are not necessary for the new formulation. In other words, the formulation (P'_2) is equivalent to the following optimization problem.

$$(P_2) \quad \min_{\mathbf{w}, b, \xi} \quad \frac{1}{2} \mathbf{w}^T \mathbf{w} + C \sum_{n=1}^N \xi_n^2$$

$$\text{subject to } y_n (\mathbf{w}^T \mathbf{x}_n + b) \geq 1 - \xi_n.$$

Problem (P_2) is equivalent to a linear hard-margin support vector machine (primal problem) that takes examples $(\tilde{\mathbf{x}}_n, y_n)$ instead of (\mathbf{x}_n, y_n) . That is, the hard-margin dual problem that involves $\tilde{\mathbf{x}}_n$ is simply the dual problem of (P_2) . Use $[[\cdot]]$ to denote the boolean function which evaluates to 1 if and only iff the inner condition is true. Which of the following is $\tilde{\mathbf{x}}_n$? (Hint: let $\tilde{\mathbf{w}} = (\mathbf{w}, \text{constant} \cdot \xi)$)

Your Answer	Score	Explanation
<input checked="" type="radio"/> $\tilde{\mathbf{x}}_n = (\mathbf{x}_n, v_1, v_2, \dots, v_N)$, where $v_i = \frac{1}{\sqrt{2C}} [[i = n]]$	✓ 20.00	
<input type="radio"/> $\tilde{\mathbf{x}}_n = (\mathbf{x}_n, v, v, \dots, v)$, where there are N components of $v = \frac{1}{\sqrt{2C}}$		
<input type="radio"/> $\tilde{\mathbf{x}}_n = (\mathbf{x}_n, v_1, v_2, \dots, v_N)$, where $v_i = \frac{1}{\sqrt{C}} [[i = n]]$		
<input type="radio"/> $\tilde{\mathbf{x}}_n = (\mathbf{x}_n, v, v, \dots, v)$, where there are N components of		

$$v = \frac{1}{\sqrt{c}}$$

☐ none of the other choices

Total	20.00 /
	20.00

Question 12

Let $K_1(\mathbf{x}, \mathbf{x}') = \boldsymbol{\phi}_1(\mathbf{x})^T \boldsymbol{\phi}_1(\mathbf{x}')$ and $K_2(\mathbf{x}, \mathbf{x}') = \boldsymbol{\phi}_2(\mathbf{x})^T \boldsymbol{\phi}_2(\mathbf{x}')$ be two valid kernels. Which of the following is always a valid kernel, assuming that $K_2(\mathbf{x}, \mathbf{x}') \neq 0$ for all \mathbf{x} and \mathbf{x}' ?

Your Answer	Score	Explanation
<input type="radio"/> none of the other choices		
<input type="radio"/> $K(\mathbf{x}, \mathbf{x}') = -K_1(\mathbf{x}, \mathbf{x}') - K_2(\mathbf{x}, \mathbf{x}')$		
<input type="radio"/> $K(\mathbf{x}, \mathbf{x}') = K_1(\mathbf{x}, \mathbf{x}') - K_2(\mathbf{x}, \mathbf{x}')$		
<input checked="" type="radio"/> $K(\mathbf{x}, \mathbf{x}') = K_1(\mathbf{x}, \mathbf{x}') + K_2(\mathbf{x}, \mathbf{x}')$	✓ 20.00	
<input type="radio"/> $K(\mathbf{x}, \mathbf{x}') = K_1(\mathbf{x}, \mathbf{x}')/K_2(\mathbf{x}, \mathbf{x}')$		
Total	20.00 / 20.00	

Question 13

Let $K_1(\mathbf{x}, \mathbf{x}') = \boldsymbol{\phi}_1(\mathbf{x})^T \boldsymbol{\phi}_1(\mathbf{x}')$ be a valid kernel. Which of the following is always a valid kernel?

Your Answer	Score	Explanation
<input type="radio"/> none of the other choices		
<input type="radio"/> $K(\mathbf{x}, \mathbf{x}') = (1 - K_1(\mathbf{x}, \mathbf{x}'))^{-1}$, assuming that \$\$\$0		
<input checked="" type="radio"/> $K(\mathbf{x}, \mathbf{x}') = (1 - K_1(\mathbf{x}, \mathbf{x}'))^2$	✗ -5.00	
<input type="radio"/> $K(\mathbf{x}, \mathbf{x}') = 1126/K_1(\mathbf{x}, \mathbf{x}')$		
<input type="radio"/> $K(\mathbf{x}, \mathbf{x}') = \exp(-K_1(\mathbf{x}, \mathbf{x}'))$		
Total	-5.00 / 20.00	

Question 14

For a given valid kernel K , consider a new kernel $\tilde{K}(\mathbf{x}, \mathbf{x}') = pK(\mathbf{x}, \mathbf{x}') + q$ for some $p > 0$ and $q > 0$. Which of the following statement is true?

Your Answer	Score	Explanation
<input type="radio"/> none of the other choices		
<input checked="" type="radio"/> For the dual of soft-margin support vector machine, using \tilde{K} along with a new $\tilde{C} = \frac{C}{p}$ instead of K with the original C leads to an equivalent g_{SVM} classifier.	✓ 20.00	
<input type="radio"/> For the dual of soft-margin support vector machine, using \tilde{K} along with a new $\tilde{C} = \frac{C}{p} + q$ instead of K with the original C leads to an equivalent g_{SVM} classifier.		
<input type="radio"/> For the dual of soft-margin support vector machine, using \tilde{K} along with a new $\tilde{C} = pC + q$ instead of K with the original C leads to an equivalent g_{SVM} classifier.		
<input type="radio"/> For the dual of soft-margin support vector machine, using \tilde{K} along with a new $\tilde{C} = pC$ instead of K with the original C leads to an equivalent g_{SVM} classifier.		
Total	20.00 / 20.00	

Question 15

For Questions 15 to 20, we are going to experiment with a real-world data set. Download the processed US Postal Service Zip Code data set with extracted features of intensity and symmetry for training and testing:

<http://www.amlbook.com/data/zip/features.train>

<http://www.amlbook.com/data/zip/features.test>

The format of each row is

digit intensity symmetry

We will consider binary classification problems of the form "one of the digits" (as the positive class) versus "other digits" (as the negative class).

The training set contains thousands of examples, and some quadratic programming packages cannot handle this size. We recommend that you consider the LIBSVM package

<http://www.csie.ntu.edu.tw/~cjlin/libsvm/>

Regardless of the package that you choose to use, please read the manual of the package carefully to make sure that you are indeed solving the soft-margin support vector machine taught in class like the dual formulation below:

$$\begin{aligned} \min_{\alpha} \quad & \frac{1}{2} \sum_{n=1}^N \sum_{m=1}^N \alpha_n \alpha_m y_n y_m K(\mathbf{x}_n, \mathbf{x}_m) - \sum_{n=1}^N \alpha_n \\ \text{s. t.} \quad & \sum_{n=1}^N y_n \alpha_n = 0 \\ & 0 \leq \alpha_n \leq C \quad n = 1, \dots, N \end{aligned}$$

In the following questions, please use the 0/1 error for evaluating E_{in} , E_{val} and E_{out} (through the test set). Some practical remarks include

- (i) Please tell your chosen package to **not** automatically scale the data for you, lest you should change the effective kernel and get different results.
- (ii) It is your responsibility to check whether your chosen package solves the designated formulation with enough numerical precision. Please read the manual of your chosen package for software parameters whose values affect the outcome---any ML practitioner needs to deal with this kind of added uncertainty.

Consider the linear soft-margin SVM. That is, either solve the primal formulation of soft-margin SVM with the given \mathbf{x}_n , or take the linear kernel $K(\mathbf{x}_n, \mathbf{x}_m) = \mathbf{x}_n^T \mathbf{x}_m$ in the dual formulation. With $C = 0.01$, and the binary classification problem of "0" versus "not 0", which of the following numbers is closest to $\|\mathbf{w}\|$ after solving the linear soft-margin SVM?

Your Answer	Score	Explanation
<input type="radio"/> 1.8		
<input type="radio"/> 1.0		
<input type="radio"/> 0.2		
<input checked="" type="radio"/> 0.6	20.00	
<input type="radio"/> 1.4		
Total	20.00 / 20.00	

Question 16

Consider the polynomial kernel $K(\mathbf{x}_n, \mathbf{x}_m) = (1 + \mathbf{x}_n^T \mathbf{x}_m)^Q$, where Q is the degree of the polynomial. With $C = 0.01$, $Q = 2$, which of the following soft-margin SVM classifiers reaches the lowest E_{in} ?

Your Answer	Score	Explanation
<input type="radio"/> ``0'' versus ``not 0''		
<input type="radio"/> ``2'' versus ``not 2''		
<input type="radio"/> ``4'' versus ``not 4''		
<input type="radio"/> ``6'' versus ``not 6''		
<input checked="" type="radio"/> ``8'' versus ``not 8''	<div><div></div><div>20.00</div></div>	
Total	20.00 / 20.00	

Question 17

Following Question16, which of the following numbers is closest to the maximum $\sum_{n=1}^N \alpha_n$ within those five soft-margin SVM classifiers?

Your Answer	Score	Explanation
<input type="radio"/> 5.0		
<input type="radio"/> 25.0		
<input type="radio"/> 10.0		
<input checked="" type="radio"/> 20.0	<div><div></div><div>20.00</div></div>	
<input type="radio"/> 15.0		
Total	20.00 / 20.00	

Question 18

Consider the Gaussian kernel $K(\mathbf{x}_n, \mathbf{x}_m) = \exp(-\gamma \|\mathbf{x}_n - \mathbf{x}_m\|^2)$. With $\gamma = 100$, and the binary classification problem of "0" versus "not 0". Consider values of C within $\{0.001, 0.01, 0.1, 1, 10\}$. Which of the following properties of the soft-margin SVM classifier strictly decreases with those five C ?

Your Answer	Score	Explanation
<input type="radio"/> $\sum_{n=1}^N \sum_{m=1}^N K(\mathbf{x}_n, \mathbf{x}_m)$		
<input type="radio"/> none of the other choices		
<input type="radio"/> E_{out}		
<input checked="" type="radio"/> the distance of any free support vector to the hyperplane in the (infinite-dimensional) \mathcal{Z} space	✓ 20.00	
<input type="radio"/> number of support vectors		
Total	20.00 / 20.00	

Question 19

Following Question 18, when fixing $C = 0.1$, which of the following values of γ results in the lowest E_{out} ?

Your Answer	Score	Explanation
<input checked="" type="radio"/> 10	✓ 20.00	
<input type="radio"/> 10000		
<input type="radio"/> 100		
<input type="radio"/> 1		
<input type="radio"/> 1000		
Total	20.00 / 20.00	

Question 20

Following Question 18 and consider a validation procedure that randomly samples 1000 examples from the training set for validation and leaves the other examples for training g_{SVM}^- . Fix $C = 0.1$ and use the validation procedure to choose the best γ among $\{1, 10, 100, 1000, 10000\}$ according to E_{val} . If there is a tie of E_{val} , choose the smallest γ . Repeat the procedure 100 times. Which of the following values of γ is selected the most number of times?

Your Answer	Score	Explanation
<input type="radio"/> 100		
<input checked="" type="radio"/> 10	20.00	
<input type="radio"/> 1		
<input type="radio"/> 1000		
<input type="radio"/> 10000		
Total	20.00 / 20.00	