

---


## STM32CubeIDE installation guide

### Introduction

This installation guide for **STM32CubeIDE** gives directions on how to install software on each of the operating systems it supports. It is primarily intended to software developers or system administrators who are about to install the **STM32CubeIDE** product.

This installation guide covers the following topics:

- System requirements
- Important information
- STM32CubeIDE installation (Windows)
- STM32CubeIDE installation (Linux)
- STM32CubeIDE installation (macOS)
- Update an STM32CubeIDE installation
- Uninstall STM32CubeIDE (Windows)
- Uninstall STM32CubeIDE (Linux)
- Uninstall STM32CubeIDE (macOS)



# 1 System requirements

STM32CubeIDE is tested and verified on the Microsoft® Windows®, Linux®, and macOS® versions listed in this chapter.

**Important:** Only 64-bit OS versions are supported.

STM32CubeIDE supports STM32 32-bit products based on the Arm® Cortex® processor.

**Note:** Arm is a registered trademark of Arm Limited (or its subsidiaries) in the US and/or elsewhere.

arm

## 1.1 Microsoft® Windows®

- Microsoft® Windows 7®
- Microsoft® Windows 8®
- Microsoft® Windows 10®

## 1.2 Linux®

- Ubuntu® 18.04
- Ubuntu® 20.04
- Fedora® 29
- Fedora® 31

**Note:** Ubuntu® is a registered trademark of Canonical Ltd.

Fedora® is a trademark of Red Hat, Inc.

## 1.3 macOS®

- macOS® 10.12 (Sierra)
- macOS® 10.14 (Mojave)
- macOS® 10.15 (Catalina)

**Note:** if the macOS® Gatekeeper reports that STM32CubeIDE is damaged, execute the following command from the terminal application: `xattr -c /Applications/STM32CubeIDE.app`.

macOS® is a trademark of Apple Inc. registered in the U.S. and other countries.

All other trademarks are the property of their respective owners.

## 1.4 Hardware requirements

The following hardware requirements apply:

- 2 Gbytes of RAM minimum. 4 Gbytes of RAM recommended
- 6 Gbytes of free hard-disk space for non STM32 MPU OpenSTLinux Distribution developers, 15 Gbytes for STM32 MPU OpenSTLinux Distribution usage

## 2 Important information

---

This chapter contains important information regarding the installation of [STM32CubeIDE](#).

### 2.1 Product installer

The latest version of the [STM32CubeIDE](#) installer can be downloaded from the STMicroelectronics web site at [www.st.com](http://www.st.com).

### 2.2 Installing from USB memory

It is not recommended to launch the [STM32CubeIDE](#) installer directly from a USB memory. Instead, copy the executable installation file from the USB memory to the local hard-disk drive of the computer and execute the installation from the hard-disk drive.

If an installation from a USB memory is still preferred, make sure that the USB memory is not write-protected and that there is at least 6 GBytes of free memory beyond the space occupied by the installation executable. The extra space is required for temporary files during the installation.

**Caution:** Do not remove the USB memory from the computer until the installation process is completely finished or the installation would fail.

### 2.3 Product upgrades

It is possible to install new versions of [STM32CubeIDE](#) in parallel with older versions.

### 3 STM32CubeIDE installation (Windows®)

This section describes how to install the STM32CubeIDE product on Microsoft® Windows®.

**Note:** The installation is done through a product installer. Make sure that the user account, from which the installer is launched, has administrative privileges.


Proceed as follows:

1. Launch the product installer (.exe file)  
`st-stm32cubeide_VERSION_ARCHITECTURE.exe`  
 where:
  - VERSION is the actual product version and build date  
 Example: 1.0.0\_2026\_20190221\_1309
  - ARCHITECTURE is the architecture of the target host computer to run STM32CubeIDE  
 Example: x86\_64

If, when launching the product installer, it reports an attempt to install a version that is already installed:


- a. Launch the register dialog by typing `regedit.exe` in the search bar
- b. Remove registry key  
`HKEY_LOCAL_MACHINE\SOFTWARE\WOW6432Node\STMicroelectronics\STM32CubeIDE`
2. During the installation process, the operating system may display a dialog stating: “Do you want to allow this app to make changes to your device?” with info “Verified publisher: STMicroelectronics Software AB”. Accept ([YES]) to let the installer continue.
3. Wait for the installer **Welcome** dialog to be displayed and click on [Next >].

Figure 1. Installer Welcome page (Windows®)




4. Read the license agreement. Click on **[I Agree]** to accept the terms of the agreement, or **[Cancel]** to abort the installation. If the agreement is accepted, the installation wizard continues.

**Figure 2. License agreement dialog (Windows®)**




5. In this dialog, the user selects the location for the installation. It is recommended to choose a short path to avoid facing Windows® limitations with too long paths for the workspace.

**Figure 3. Installer location dialog (Windows®)**




6. Wait for the **Choose Components** dialog to be displayed. Select the GDB Server components to be installed together with STM32CubeIDE. A server is needed for each type of JTAG probe used for debugging with STM32CubeIDE.

Figure 4. Selection of components dialog (Windows®)




7. Click on **[Install]** to start the installation. The drivers that were selected are installed in parallel with this installation of STM32CubeIDE from here on.

Figure 5. Installation successful (Windows®)



8. Click on **[Next]** to continue to the final step of the installation process. That is a **Confirmation** dialog informing the user that the installation is finished. Once the user clicks on **[Finish]**, the installation process is complete.

**Figure 6. Installation finished (Windows®)**



## 4 STM32CubeIDE installation (Linux®)

This section describes how to install the STM32CubeIDE product on Linux®.

**Note:** *The installation is done through a product installer. Linux® root privileges are required to complete the installation.*

The installer comes in different bundles to suit the various Linux® distributions. The bundles are named according to:

`st-stm32cubeide_VERSION_ARCHITECTURE.PACKAGE`

where:

- **VERSION** is the actual product version and build date  
Example: 1.0.0\_2026\_20190221\_1309
- **ARCHITECTURE** is the architecture of the target host computer to run STM32CubeIDE  
Example: amd64
- **PACKAGE** is the Linux® package type to be installed. The supported packages are:
  - `rpm_bundle.sh` for Fedora®/CentOS
  - `deb_bundle.sh` for Ubuntu®
  - `.sh` for generic Linux®

Proceed as follows:

1. Navigate to the location of the installer file with a command console on the host computer.
2. Enter the following command in the console window:  
`sudo sh ./st-stm32cubeide_VERSION_ARCHITECTURE.PACKAGE`  
where **VERSION**, **ARCHITECTURE** and **PACKAGE** must be entered after the selected Linux® package.
3. Follow the further instructions provided through the console window.

### Manual installation (.rpm/.deb)

For RPM-based distributions (Red Hat®, CentOS™, SUSE®, Fedora®):

```
sudo rpm -Uhv segger-jlink-udev-rules-xxxx-linux-noarch.rpm st-stlink-udev-rules-xxxx-linux-noarch.rpm st-stlink-server-xxxx-linux-amd64.rpm st-stm32cubeide-xxxx-amd64.rpm
```

For Debian-based distributions (Debian®, Ubuntu®):

```
sudo apt-get install ./segger-jlink-udev-rules-xxxx-linux-all.deb ./st-stlink-udev-rules-xxxx-linux-all.deb ./st-stlink-server-xxxx-linux-amd64.deb ./st-stm32cubeide-xxxx-amd64.deb
```

**Note:** *CentOS is a trademark of Red Hat, Inc.  
SUSE is a trademark of SUSE LLC or its subsidiaries or affiliates.*



## 5 STM32CubeIDE installation (macOS®)


This section describes how to install the STM32CubeIDE product on macOS®.

**Note:** *The installation is done through a product installer. Make sure that the user account, from which the installer is launched, has administrative privileges.*

Proceed as follows:

1. Launch the product installer (.dmg file)  
`st-stm32cubeide_VERSION_ARCHITECTURE.dmg`  
where:
  - VERSION is the actual product version and build date  
Example: 1.0.0\_2026\_20190221\_13091309
  - ARCHITECTURE is the architecture of the target host computer to run STM32CubeIDE  
Example: x86\_64
2. Read the license agreement. Click on **[Agree]** to accept the terms of the agreement, or **[Disagree]** to abort the installation. If the agreement is accepted, the installation wizard continues.

**Figure 7. License agreement dialog (macOS®)**




**Note:** *if the macOS® Gatekeeper reports that STM32CubeIDE is damaged, execute the following command from the terminal application: `xattr -c /Applications/STM32CubeIDE.app`.*

3. Wait for the installation **welcome page** to appear.


4. Double click on the .pkg file indicated with the curved arrow and text stating “Install me 1st”.

Figure 8. Installation welcome page (macOS®)



5. This installation is required and installs the *ST Link Server*. Click on the [Continue] button.


Figure 9. ST Link Server welcome page (macOS®)



6. In this dialog, select the location for the installation of the *ST Link Server*.
7. Click on [Install]. Log in to authorize the installation if prompted to do so.


8. If a warning is displayed stating "This package is incompatible with this version of macOS and may fail to install", click on **[Install Anyway]**.

**Figure 10. ST Link Server installer location dialog (macOS®)**




9. Click on **[Close]** and continue the installation of the STM32CubeIDE product.

**Figure 11. ST Link Server installation finished (macOS®)**




10. After successfully installing *ST Link Server*, drag the **STM32CubeIDE** icon to the **Applications** folder as indicated by the straight arrow.

Figure 12. STM32CubeIDE install page (macOS®)



11. Wait for the installation to finish. When done, it is possible to launch **STM32CubeIDE** from the **Launchpad** by clicking on the IDE icon.

Figure 13. Installation progress bar (macOS®)



## 6 Update an STM32CubeIDE installation


The Eclipse® update mechanism permits the quick update of available patches when STM32CubeIDE is already installed. To use this mechanism:

1. Launch STM32CubeIDE
2. Update the tool by **[Help]>[Check for updates...]**
3. Restart STM32CubeIDE
  - Either automatically if STM32CubeIDE proposes it
  - By exiting STM32CubeIDE and restarting it otherwise

By default, the update is done with the last version. If another version is needed, follow the steps below:

1. Open the *Install* dialog box as shown in [Figure 14](#) by **[Help]>[Install new software...]**


**Figure 14. Install dialog box**



2. Click on the **[Manage...]** button


3. Select [STM32CubeIDE Releases] and click on [Edit] as shown in Figure 15

Figure 15. Preferences window



4. Add the desired version number at the end of the url in the [Location] field as shown in Figure 16

Figure 16. Edit Site dialog box



**Note:** The update mechanism has the same requirements as the installation in term of administration rights. If the installation has been made with administration rights, the update must be made also with the same administration rights.

## 7 Uninstall STM32CubeIDE (Windows®)

To uninstall STM32CubeIDE, under the installation folder:

1. Launch the product uninstaller (uninstall.exe)
2. Wait for the uninstaller dialog box and click on **[Uninstall]**

**Note:**

*In Windows®, the removal of the installation directory instead of using the uninstall procedure prevents further installation. In this case, delete registry key*

*HKEY\_LOCAL\_MACHINE\SOFTWARE\WOW6432Node\STMicroelectronics\STM32CubeIDE\VersionToS  
uppress using regedit.exe.*

## 8 Uninstall STM32CubeIDE (Linux®)

The uninstallation of STM32CubeIDE depends on the distribution. Uninstall STM32CubeIDE according to the step below corresponding to the distribution used:

- For any distribution or if the distribution is not known:  
`sudo /opt/st/stm32cubeide_XXXX/uninstall.sh`
- For RPM-based distributions (such as Red Hat®, CentOS™, SUSE®, Fedora® or others):  
`sudo rpm -e st-stm32cubeide_XXXX st-stlink-udev-rules st-stlink-server segger-jlink-udev-rules`
- For Debian-based distributions (such as Debian®, Ubuntu® or others):  
`sudo apt-get remove st-stm32cubeide-XXXX st-stlink-udev-rules st-stlink-server segger-jlink-udev-rules`



---

## 9 Uninstall STM32CubeIDE (macOS®)

---

To uninstall STM32CubeIDE:

1. Locate the version of STM32CubeIDE to uninstall in the *Applications* folder in the *Finder*
2. Drag the STM32CubeIDE app to uninstall to the trash
3. To delete the app permanently, choose **[Finder]>[Empty Trash]**

## Revision history

**Table 1. Document revision history**

Date	Version	Changes
18-Apr-2019	1	Initial version.
3-Nov-2020	2	<p>Added:</p> <ul style="list-style-type: none"> <li>Update an STM32CubeIDE installation</li> <li>Uninstall STM32CubeIDE (Windows)</li> <li>Uninstall STM32CubeIDE (Linux)</li> <li>Uninstall STM32CubeIDE (macOS)</li> </ul> <p>Updated:</p> <ul style="list-style-type: none"> <li>System requirements</li> <li>STM32CubeIDE installation (Linux)</li> </ul>

## Contents

<b>1</b>	<b>System requirements</b>	<b>2</b>
1.1	Microsoft® Windows®	2
1.2	Linux®	2
1.3	macOS®	2
1.4	Hardware requirements	2
<b>2</b>	<b>Important information</b>	<b>3</b>
2.1	Product installer	3
2.2	Installing from USB memory	3
2.3	Product upgrades	3
<b>3</b>	<b>STM32CubeIDE installation (Windows®)</b>	<b>4</b>
<b>4</b>	<b>STM32CubeIDE installation (Linux®)</b>	<b>8</b>
<b>5</b>	<b>STM32CubeIDE installation (macOS®)</b>	<b>9</b>
<b>6</b>	<b>Update an STM32CubeIDE installation</b>	<b>13</b>
<b>7</b>	<b>Uninstall STM32CubeIDE (Windows®)</b>	<b>15</b>
<b>8</b>	<b>Uninstall STM32CubeIDE (Linux®)</b>	<b>16</b>
<b>9</b>	<b>Uninstall STM32CubeIDE (macOS®)</b>	<b>17</b>
	<b>Revision history</b>	<b>18</b>
	<b>Contents</b>	<b>19</b>
	<b>List of tables</b>	<b>20</b>
	<b>List of figures</b>	<b>21</b>

## List of tables

Table 1.	Document revision history . . . . .	18
----------	-------------------------------------	----

## List of figures

Figure 1.	Installer <b>Welcome</b> page (Windows®) . . . . .	4
Figure 2.	License agreement dialog (Windows®) . . . . .	5
Figure 3.	Installer location dialog (Windows®) . . . . .	5
Figure 4.	Selection of components dialog (Windows®) . . . . .	6
Figure 5.	Installation successful (Windows®) . . . . .	6
Figure 6.	Installation finished (Windows®) . . . . .	7
Figure 7.	License agreement dialog (macOS®) . . . . .	9
Figure 8.	Installation welcome page (macOS®) . . . . .	10
Figure 9.	ST Link Server welcome page (macOS®) . . . . .	10
Figure 10.	ST Link Server installer location dialog (macOS®) . . . . .	11
Figure 11.	ST Link Server installation finished (macOS®) . . . . .	11
Figure 12.	STM32CubeIDE install page (macOS®) . . . . .	12
Figure 13.	Installation progress bar (macOS®) . . . . .	12
Figure 14.	<i>Install</i> dialog box . . . . .	13
Figure 15.	<i>Preferences</i> window . . . . .	14
Figure 16.	<i>Edit Site</i> dialog box . . . . .	14

**IMPORTANT NOTICE – PLEASE READ CAREFULLY**

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, please refer to [www.st.com/trademarks](http://www.st.com/trademarks). All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2020 STMicroelectronics – All rights reserved