UNIT 2 · TOPIC 2.4

Detecting Physical Attacks

Assignment, Answer Key

Teacher answer key, 30 points total.

Practice Questions

2.4.a · Access logs and monitoring

1. An access log shows badge #1042 granted entry to the server room at 02:17 on a Saturday. What is the PRIMARY concern? (1 pt)

- ○ A. The badge reader malfunctioned overnight
- ○ B. Anti-passback was not enabled on that reader
- ○ C. The SIEM platform failed to generate an alert
- **● D. After-hours access to a restricted area by a valid credential**

Why: After-hours valid access to a restricted door is an alert-worthy anomaly regardless of credential validity, it may indicate a stolen or cloned badge.

2. Which of the following log patterns are direct indicators of a potential physical security breach? Select ALL that apply. (2 pts)

- **■ A. Seven ACCESS DENIED events for badge #0099 within 45 seconds**
- □ B. Badge #0210 granted at lobby at 08:32, then at server room at 08:34
- **■ C. Badge #0210 granted at lobby at 08:32, then at data center 40 miles away at 08:45**
- □ D. Badge #0055 granted at lobby at 09:05 on a Tuesday

Why: Seven denials in 45 seconds is a repeated-denial burst (rule 0). The same badge appearing 40 miles away within 13 minutes is a location inconsistency (rule 2). The other events are normal.

3. What does the anti-passback feature in an access control system detect? (1 pt)

- ○ A. Intrusions through windows and emergency exits
- ○ B. After-hours access by cleaning staff
- **● C. A credential being used to enter without a prior exit record, suggesting badge sharing**
- ○ D. Repeated failed attempts on a single reader

Why: Anti-passback tracks entry/exit state per credential. A badge that enters twice without an exit in between triggers an alert, indicating the badge may have been passed to a second person.

4. Name the type of platform that aggregates access logs from multiple readers and applies detection rules in real time. (1 pt)

Acceptable answers: siem; security information and event management; siem platform

Why: A SIEM (Security Information and Event Management) platform centralizes log data and evaluates rules to generate alerts.

5. Why are physical access logs described as a detective control rather than a preventive control? (1 pt)

- ○ A. They require a human analyst to be watched at all times
- ○ B. They are only useful during forensic investigation, not real-time monitoring
- **● C. They record events after they occur and help discover breaches rather than block them**

○ D. They replace the need for badge readers and cameras

Why: Detective controls identify that something happened; preventive controls stop it from happening. Logs record events after the fact, limiting discovery time rather than preventing entry.

2.4.b · Alarm systems

6. A homeowner arms their system in ARMED_AWAY mode and the front-door contact sensor trips 10 seconds later while they are still walking out. What should happen? (1 pt)

○ A. The panel immediately dispatches police

○ B. The siren sounds locally but the sensor is permanently disabled

● C. The trip is treated as expected behavior because it falls within the exit delay

○ D. The system automatically switches to ARMED_STAY

Why: The exit delay gives the occupant a grace period to leave after arming; a trip inside that window is expected, not an intrusion.

7. Why is an armed alarm system classified as a detective control rather than a preventive control? (1 pt)

○ A. It requires a monthly monitoring fee

● B. It notices and reports an intrusion in progress but cannot physically stop entry

○ C. It only works when connected to the internet

○ D. It replaces the need for door locks entirely

Why: An alarm can only detect and respond to an event that is already happening; it does not create a physical barrier the way a lock does.

8. Which of the following are true about panic/duress buttons? Select ALL that apply. (2 pts)

□ A. They are always triggered by a burglary in progress

■ B. They can be used for personal-safety emergencies unrelated to a break-in

■ C. They bypass normal arm-state checks

■ D. They typically escalate straight to dispatch without cross-zone verification

Why: Panic buttons are general duress signals (medical emergency, threat, robbery, etc.), work regardless of arm state, and escalate directly to dispatch since a human deliberately triggered them.

9. What is the purpose of cross-zone verification in an alarm system? (1 pt)

○ A. To extend the exit delay automatically

○ B. To disable sensors that trip too often

● C. To require two independent sensors/zones to trip within a short window before treating the event as high-confidence

○ D. To identify which employee armed the system

Why: Cross-zone verification reduces false dispatches by requiring corroboration from a second independent sensor or zone before an event is treated as a likely real intrusion.

10. Name the alarm system component that is a staffed facility receiving panel signals and deciding whether to contact police. (1 pt)

Acceptable answers: monitoring center; central station; monitoring station; central monitoring station

Why: The monitoring / central station receives the signal, attempts verification, and dispatches when warranted.

11. A door contact sensor trips 900 seconds after the system was armed, with no other zone corroborating the event within the verification window. How should this be classified? (1 pt)

- **● A. LOCAL_ONLY**
- ○ B. FALSE_ALARM
- ○ C. SUPPRESSED
- ○ D. DISPATCH

Why: Well past the exit delay, so it is a real trip, but with no cross-zone corroboration it stays LOCAL_ONLY rather than auto-escalating to dispatch.

2.4.c · Motion detectors and sensor-based detection

12. What does a passive infrared (PIR) sensor actually detect? (1 pt)

- ○ A. A reflected microwave signal bounced off a moving object
- ○ B. The exact body temperature of anyone in the room
- **● C. A change in infrared (heat) radiation across segments of its field of view**
- ○ D. Sound waves generated by footsteps

Why: PIR sensors are passive, they emit no energy, and detect a change (delta) in infrared radiation as a heat source moves across detection segments, not an absolute temperature reading.

13. A microwave motion sensor detects movement using which underlying physics principle? (1 pt)

- ○ A. Infrared radiation change
- **● B. Doppler shift in a reflected signal**
- ○ C. Barometric pressure change
- ○ D. Capacitive touch sensing

Why: Microwave (and ultrasonic) sensors emit a signal and measure the frequency shift, Doppler shift, in the reflection caused by a moving object.

14. Why do dual-technology sensors (PIR + microwave) reduce false positives compared to a single-technology sensor? (1 pt)

- **● A. They require both technologies to indicate motion at roughly the same time (AND-logic), and the two technologies' false-trigger causes rarely overlap**
- ○ B. They have a wider detection cone than any single sensor
- ○ C. They are more expensive, which guarantees higher build quality
- ○ D. They ignore all heat sources entirely

Why: Dual-tech sensors use AND-logic: both elements must agree. Since a PIR false-positive cause (e.g. sunlight) rarely also produces a Doppler shift, and a microwave false-positive cause (e.g. vibration) rarely also produces an infrared delta, requiring both sharply cuts nuisance alerts.

15. Which of the following are known causes of motion-sensor false positives? Select ALL that apply. (2 pts)

- **■ A. Sunlight moving across a window**
- □ B. A person walking directly toward the sensor
- **■ C. HVAC vent airflow**
- **■ D. A pet moving through the room**

Why: Sunlight, HVAC airflow, and pets are all classic false-positive causes for motion sensors. A person walking through the zone is exactly the true detection the sensor exists to catch.

16. A dual-technology sensor reports: PIR element cause = 'hvac_airflow', microwave element cause = 'person'. What should the system conclude? (1 pt)

○ A. TRUE DETECTION, because the microwave element saw a person

○ B. TRUE DETECTION, because at least one element always overrides the other

● **C. FALSE POSITIVE, because AND-logic requires both elements to independently indicate a person, and the PIR element's cause is a known false-positive**

○ D. The event should be discarded and never logged

Why: Dual-tech AND-logic requires BOTH elements to agree the cause is a genuine person. Since the PIR element's cause is HVAC airflow (a known false-positive cause), the event is a false positive even though the microwave element reported a person.

17. What is the main risk of setting a motion sensor's sensitivity too low? (1 pt)

○ A. It will trigger constantly on pets and insects

● **B. It may miss a genuine slow or partial intrusion, such as someone reaching through a cracked window**

○ C. It will draw more electrical power

○ D. It will stop working entirely after a few weeks

Why: Lowering sensitivity suppresses nuisance triggers, but it also raises the threshold for detecting real motion, which can cause a genuine slow or partial intrusion to go undetected.

18. Name the term for the limited field of view a motion sensor can actually observe, outside of which (or behind an obstruction) it cannot detect motion. (1 pt)

Acceptable answers: detection cone; coverage pattern; field of view; coverage cone

Why: A sensor's detection cone (or coverage pattern) is analogous to a camera's field of view, anything outside it is a blind spot.

Coding Assignments (Python 3)

2.4.a · Access logs and monitoring

3 pts · auto-graded on the site

Coding problem, 2.4.a: Access log anomaly detector

Skill: Detect Attacks · **Maps to:** 2.4.A · **Language:** Python 3 (pytest)

Problem

You are building the detection engine for a physical access control monitoring system at Crestfield Analytics. Given a list of timestamped access log entries, identify every badge ID that triggers at least one of three alert rules:

- **Rule 0, Repeated denial burst:** 5 or more ACCESS DENIED events for the same badge within any 60-second sliding window.
- **Rule 1, After-hours valid access to a restricted door:** any GRANTED entry at a door whose name starts with `"restricted-"` between 22:00 and 05:59 (inclusive, using the entry's local time).
- **Rule 2, Location inconsistency:** the same badge granted at two different doors within a gap of 10 minutes (600 seconds) where those two doors are listed as geographically separated in a provided `far_pairs` set of frozensets.

Function contract

Implement `solve(entries, far_pairs)` in `starter.py` (see `interface.md` / `blackbox.yaml`).

Input

- `entries`: `list[dict]`, each dict has: - `"ts"`: `int`, Unix timestamp (seconds) - `"badge"`: `str`, badge identifier e.g. `"B-0101"` - `"door"`: `str`, door identifier e.g. `"restricted-server-room-A"` - `"outcome"`: `str`, `"GRANTED"` or `"DENIED"`
- `far_pairs`: `set[frozenset]`, each element is a frozenset of two door names that are geographically far apart.

Output

A **sorted list of unique badge ID strings** that triggered one or more rules. Empty list if no alerts.

Examples

```
entries = [
    {"ts": 1710230400, "badge": "B-0101", "door": "lobby", "outcome": "DENIED"},
    {"ts": 1710230410, "badge": "B-0101", "door": "lobby", "outcome": "DENIED"},
    {"ts": 1710230420, "badge": "B-0101", "door": "lobby", "outcome": "DENIED"},
    {"ts": 1710230430, "badge": "B-0101", "door": "lobby", "outcome": "DENIED"},
    {"ts": 1710230440, "badge": "B-0101", "door": "lobby", "outcome": "DENIED"},
]
far_pairs = set()
solve(entries, far_pairs)  ->  ["B-0101"]

entries2 = [
    {"ts": 1710288001, "badge": "B-0202", "door": "restricted-vault", "outcome": "GRANTED"},
]
# ts 1710288001 = 2024-03-13 02:00:01 UTC  (after-hours)
far_pairs2 = set()
solve(entries2, far_pairs2)  ->  ["B-0202"]
```

Constraints

- Deterministic, offline, standard library only.
- Treat all timestamps as UTC when checking hour for after-hours (hour in {22,23,0,1,2,3,4,5}).
- Must pass all cases in `tests.py` (visible + hidden).

How to run

```
cd problem && python -m pytest tests.py -q
```

Reference solution:

```
from typing import List, Set, FrozenSet, Dict
import datetime


def solve(entries: List[Dict], far_pairs: Set[FrozenSet]) -> List[str]:
    flagged = set()

    by_badge: Dict[str, List[Dict]] = {}
    for e in entries:
        by_badge.setdefault(e["badge"], []).append(e)

    after_hours = {22, 23, 0, 1, 2, 3, 4, 5}

    for badge, evts in by_badge.items():
        evts_sorted = sorted(evts, key=lambda x: x["ts"])

        denials = [e["ts"] for e in evts_sorted if e["outcome"] == "DENIED"]
        for i in range(len(denials)):
```

```
            window_end = denials[i] + 60
            count = sum(1 for ts in denials[i:] if ts <= window_end)
            if count >= 5:
                flagged.add(badge)
                break

        for e in evts_sorted:
            if e["outcome"] == "GRANTED" and e["door"].startswith("restricted-"):
                hour = datetime.datetime.utcfromtimestamp(e["ts"]).hour
                if hour in after_hours:
                    flagged.add(badge)
                    break

        granted = [e for e in evts_sorted if e["outcome"] == "GRANTED"]
        for i in range(len(granted) - 1):
            a, b = granted[i], granted[i + 1]
            if a["door"] != b["door"] and (b["ts"] - a["ts"]) <= 600:
                pair = frozenset({a["door"], b["door"]})
                if pair in far_pairs:
                    flagged.add(badge)
                    break

    return sorted(flagged)
```

2.4.b · Alarm systems

3 pts · auto-graded on the site

Coding problem, 2.4.b: Alarm event classifier

Skill: Detect Attacks · **Maps to:** 2.4.B · **Language:** Python 3 (pytest)

Problem

You are building the triage logic for an alarm control panel at Crestfield Analytics. Given a timestamp-ordered stream of sensor events (one per zone trip), classify each event using the arm-state, exit-delay, and cross-zone verification rules taught in the lesson:

- **SUPPRESSED**, the system was `"DISARMED"` when the event occurred (does not apply to panic buttons, see below).
- **FALSE_ALARM**, the event's sensor is `"contact"` or `"glass_break"`, the system was armed, and the event happened less than `exit_delay_sec` seconds after the zone was armed (still inside the exit-delay grace period).
- **LOCAL_ONLY**, a real trip (armed, past the exit delay) that has no corroborating trip in a *different* zone within `verify_window_sec` seconds. Only the local siren sounds.
- **DISPATCH**, either (a) the sensor is `"panic"` (a panic/duress button always dispatches, regardless of arm state or timing), or (b) a real trip that has a corroborating real trip in a different zone within `verify_window_sec` seconds (cross-zone verification).

Function contract

Implement `solve(events, exit_delay_sec=45, verify_window_sec=120)` in `starter.py` (see `interface.md` / `blackbox.yaml`).

Input

- `events`: `list[dict]`, each with: - `"ts"`: `int`, Unix timestamp (seconds) the event occurred - `"zone"`: `str`, zone/door identifier, e.g. `"front-door"` - `"sensor"`: `str`, one of `"contact"`, `"glass_break"`, `"panic"` - `"arm_state"`: `str`, one of `"DISARMED"`, `"ARMED_AWAY"`, `"ARMED_STAY"` - `"since_armed_sec"`: `int`, seconds elapsed between arming and this event (ignored for `"panic"` and when `arm_state == "DISARMED"`)

- `exit_delay_sec`: `int`, default `45`, grace period after arming.

- `verify_window_sec`: `int`, default `120`, max gap (in `ts`) between two different-zone real trips for cross-zone verification to apply.

Output

A `list[str]` of classifications, **one per input event, in the same order as the input**. Each entry is one of `"SUPPRESSED"`, `"FALSE_ALARM"`, `"LOCAL_ONLY"`, `"DISPATCH"`.

Examples

```
events = [
    {"ts": 1000, "zone": "front-door", "sensor": "contact",
     "arm_state": "ARMED_AWAY", "since_armed_sec": 10},
]
solve(events)  ->  ["FALSE_ALARM"]

events2 = [
    {"ts": 1000, "zone": "z1", "sensor": "panic",
     "arm_state": "DISARMED", "since_armed_sec": 0},
]
solve(events2)  ->  ["DISPATCH"]

events3 = [
    {"ts": 1000, "zone": "z1", "sensor": "contact",
     "arm_state": "ARMED_AWAY", "since_armed_sec": 300},
    {"ts": 1050, "zone": "z2", "sensor": "glass_break",
     "arm_state": "ARMED_AWAY", "since_armed_sec": 305},
]
solve(events3)  ->  ["DISPATCH", "DISPATCH"]
```

Constraints

- Deterministic, offline, standard library only.

- Events may be given in any timestamp order in the list; the output order must match the **input** order (do not re-sort the output).

- Cross-zone verification: two real trips (armed, past exit delay) in **different** zones with `abs(ts_a - ts_b) <= verify_window_sec` corroborate each other. A real trip may be corroborated by more than one other zone; any single qualifying pair is enough to promote it to DISPATCH. Same-zone repeats never corroborate each other.

- `since_armed_sec >= exit_delay_sec` counts as past the exit delay (boundary is inclusive on the "past delay" side, i.e. exactly `exit_delay_sec` is a real trip, not a false alarm).

- Must pass all cases in `tests.py` (visible + hidden).

How to run

```
cd problem && python -m pytest tests.py -q
```

Reference solution:

```
from typing import List, Dict


def solve(events: List[Dict], exit_delay_sec: int = 45, verify_window_sec: int = 120) -> List[str]:
    n = len(events)
    base = [None] * n
```

```
    for i, e in enumerate(events):
        if e["sensor"] == "panic":
            base[i] = "PANIC"
        elif e["arm_state"] == "DISARMED":
            base[i] = "SUPPRESSED"
        elif e["since_armed_sec"] < exit_delay_sec:
            base[i] = "FALSE_ALARM"
        else:
            base[i] = "REAL"

    real_indices = [i for i in range(n) if base[i] == "REAL"]

    result = [""] * n
    for i, e in enumerate(events):
        if base[i] == "PANIC":
            result[i] = "DISPATCH"
        elif base[i] == "SUPPRESSED":
            result[i] = "SUPPRESSED"
        elif base[i] == "FALSE_ALARM":
            result[i] = "FALSE_ALARM"
        else:
            corroborated = False
            for j in real_indices:
                if j == i:
                    continue
                if events[j]["zone"] == e["zone"]:
                    continue
                if abs(events[j]["ts"] - e["ts"]) <= verify_window_sec:
                    corroborated = True
                    break
            result[i] = "DISPATCH" if corroborated else "LOCAL_ONLY"

    return result
```

2.4.c · Motion detectors and sensor-based detection

3 pts · auto-graded on the site

Coding problem, 2.4.c: Motion-sensor event classifier

Skill: Detect Attacks · **Maps to:** 2.4.B, 2.4.C · **Language:** Python 3 (pytest)

Problem

You are building the automated triage logic for a facility's motion-sensor monitoring system at Crestfield Analytics. Given a list of motion-sensor trigger events, classify each one as a **TRUE_DETECTION** (a real person likely caused it) or a **FALSE_POSITIVE** (a known nuisance cause, sunlight, HVAC airflow, a pet, an insect, vibration, or foliage, likely caused it), and return the IDs of the events that are true detections.

Single-technology sensors (`pir`, `microwave`, `ultrasonic`) report one cause tag. A **dual-technology** sensor reports two independent cause tags, one from its PIR element, one from its microwave element, and only counts as a true detection when **both** elements agree the cause is genuine (AND-logic). This mirrors the lesson: a dual-tech sensor exists specifically to suppress the false-positive causes that fool a single technology, so if *either* element's cause is a known false-positive cause, the whole event is a false positive.

Function contract

Implement `solve(events, false_positive_causes)` in `starter.py` (see `interface.md` / `blackbox.yaml`).

Input

- `events`: `list[dict]`, each dict has: - `"id"`: `str`, event identifier, e.g. `"EVT-001"` - `"sensor_type"`: `str`, `"pir"`, `"microwave"`, `"ultrasonic"`, or `"dual-tech"` - single-tech events also have `"cause"`: `str` - dual-tech events instead have `"cause_pir"`: `str` and `"cause_mw"`: `str`

- `false_positive_causes`: `set[str]`, known false-positive cause tags, e.g. `{"sunlight", "hvac_airflow", "pet", "insect", "vibration", "foliage"}`

Output

A **sorted list of unique event ID strings** that classify as TRUE_DETECTION. Empty list if none.

Examples

```
events = [
    {"id": "EVT-001", "sensor_type": "pir", "cause": "person"},
    {"id": "EVT-002", "sensor_type": "pir", "cause": "sunlight"},
]
fp = {"sunlight", "hvac_airflow", "pet", "insect", "vibration", "foliage"}
solve(events, fp)  ->  ["EVT-001"]

events2 = [
    {"id": "EVT-010", "sensor_type": "dual-tech", "cause_pir": "person", "cause_mw": "person"},
    {"id": "EVT-011", "sensor_type": "dual-tech", "cause_pir": "hvac_airflow", "cause_mw": "person"},
]
solve(events2, fp)  ->  ["EVT-010"]
```

Constraints

- Deterministic, offline, standard library only.

- Every event has the fields required for its `sensor_type` as described in `interface.md`.

- Must pass all cases in `tests.py` (visible + hidden).

How to run

```
cd problem && python -m pytest tests.py -q
```

Reference solution:

```
from typing import Dict, List, Set


def solve(events: List[Dict], false_positive_causes: Set[str]) -> List[str]:
    true_detections = []

    for e in events:
        sensor_type = e["sensor_type"]

        if sensor_type == "dual-tech":
            pir_ok = e["cause_pir"] not in false_positive_causes
            mw_ok = e["cause_mw"] not in false_positive_causes
            is_true = pir_ok and mw_ok
        else:
            is_true = e["cause"] not in false_positive_causes

        if is_true:
            true_detections.append(e["id"])

    return sorted(set(true_detections))
```