

Technical Support Handbook

Self-help for mobile, home internet, TV and devices

Document ZT-TS-2026-04. Customer service: 0800 12 345 (free, 24/7). From abroad: +359 2 900 1234.
Web: zarya.example

Contents

1. Before you contact support
2. Home internet: no connection
3. Home internet: slow Wi-Fi
4. Mobile data and APN settings
5. SIM, PIN and PUK
6. eSIM activation
7. Moving your number to Zarya (porting)
8. Zarya TV problems
9. Reporting a fault and repair times
10. Device repair and warranty

1. Before you contact support

Most problems can be fixed in a few minutes. Before you contact support, check the Service Status page in the Zarya app for known outages in your area, restart your device, and make sure your invoice is paid. Planned maintenance is usually done between 01:00 and 05:00 and announced in the app at least 48 hours in advance.

2. Home internet: no connection

If none of your devices can connect to the internet, follow these steps in order:

- Check that the router is on and the power light is green.
- Look at the fiber light (marked PON). If it is red or blinking red, the fiber signal is lost. Check that the green fiber cable is plugged in and not bent. Do not look into the fiber cable.
- Restart the router: unplug the power for 30 seconds, plug it back in, and wait 3 minutes.
- If it still does not work, do a factory reset (see below) and wait 5 minutes.
- If the PON light is still red, report a fault in the Zarya app or call 0800 12 345.

Factory reset of the Zarya Home Wi-Fi 6 router

Press and hold the RESET button on the back of the router with a paper clip for 10 seconds, until all lights blink. The router restarts with factory settings. The default Wi-Fi name and password are printed on the label on the bottom of the router. A factory reset removes your custom Wi-Fi name, password and port forwarding rules.

3. Home internet: slow Wi-Fi

Speeds over Wi-Fi are always lower than over a cable. To check your real speed, connect a computer with an Ethernet cable and run a test at speedtest.zarya.example. A result of at least 80% of your plan speed over a cable is normal.

- Place the router in a central, open spot, not inside a cabinet or behind the TV.
- Use the 5 GHz network (name ending in -5G) for devices close to the router. It is faster but has a shorter range than 2.4 GHz.
- Thick walls, mirrors and microwave ovens reduce Wi-Fi signal.
- For homes larger than 90 square meters or with more than one floor, add a mesh unit (3 EUR per month).
- Restart the router at least once a month.

The router admin page is at <http://192.168.1.1>. The admin password is printed on the router label. From there you can change the Wi-Fi name and password, set up a guest network, and enable parental controls.

4. Mobile data and APN settings

Mobile data settings are sent to your phone automatically. If mobile data does not work, check the APN settings manually.

Setting	Value
APN name	Zarya Internet
APN	internet.zarya

Setting	Value
Username / password	Leave empty
MMS APN	mms.zarya
MMSC	http://mms.zarya.example

On iPhone, APN settings are usually locked and set by the carrier profile; update iOS and restart the phone instead. On Android, go to Settings, Network and internet, SIMs, Access Point Names.

5. SIM, PIN and PUK

If you enter the wrong PIN three times, the SIM card is blocked and asks for the PUK code. The PUK is printed on the plastic card your SIM came in. You can also find it in the Zarya app under My services, SIM, Show PUK, or get it by calling 0800 12 345 from another phone after identity verification. If the PUK is entered wrong 10 times, the SIM is permanently blocked and must be replaced (5 EUR).

6. eSIM activation

eSIM is available for all postpaid and prepaid plans on compatible phones. You can order an eSIM in the Zarya app, in a store, or when you sign a contract online. You receive a QR code by email.

- Connect the phone to Wi-Fi.
- iPhone: Settings, Mobile Service, Add eSIM, Use QR Code. Android: Settings, Network and internet, SIMs, Download a SIM.
- Scan the QR code. Each QR code can be used only once.
- Activation takes up to 15 minutes. Restart the phone after it finishes.

If you change phones, you need a new QR code. Moving an eSIM to a new phone is free once a month, then 5 EUR per transfer. iPhone users can also use eSIM Quick Transfer between two iPhones.

7. Moving your number to Zarya (porting)

You can keep your phone number when you move from another Bulgarian operator to Zarya. Sign a Zarya contract in a store or online and fill in the porting request. You do not need to contact your old operator. Porting is free.

Porting takes up to 3 working days from the request. The switch happens at night between 02:00 and 06:00, and your phone may have no service for up to 2 hours during that window. You receive an SMS on your old SIM the day before the switch. After the switch, insert the new Zarya SIM.

A porting request can be rejected if the number is not registered to the person signing, if there are unpaid bills with the old operator older than 60 days, or if the old contract has a lock period. Early termination fees from your old operator still apply.

8. Zarya TV problems

- Black screen with 'No signal': check that the TV is on the correct HDMI input.
- Error TV-104 'Service not available': restart the Zarya TV box by unplugging it for 30 seconds.
- Picture freezes: check your internet speed. TV in HD needs at least 10 Mbps per screen.
- Forgot the parental PIN: the default is 0000. Reset it in the Zarya app under TV, Settings.

9. Reporting a fault and repair times

Report a fault in the Zarya app, at zarya.example/support, or by phone at 0800 12 345 (free, 24/7). You get a ticket number starting with INC. Zarya commits to the following repair times:

Problem	Target repair time
Fiber home internet down	24 hours (Sofia, Plovdiv, Varna); 48 hours elsewhere
5G Home internet down	48 hours
Mobile network outage in an area	8 hours
TV not working, internet working	24 hours
Technician visit for slow speed	Within 3 working days

If Zarya misses the target repair time for home internet, the customer receives a credit of 1/30 of the monthly fee for each full day of delay, up to the full monthly fee. The credit is applied automatically on the next invoice.

10. Device repair and warranty

Devices bought from Zarya have a 24-month legal warranty. Bring the device with its invoice to any Zarya store. Repairs take up to 14 days. During the repair, you can borrow a replacement phone for free if your device is under warranty. Damage from water, falls or unauthorized repair is not covered. Zarya Device Care insurance (3.99 EUR per month) covers accidental damage with a 39 EUR excess per claim.