

Ultimate Basic v1.5.7 — Language Manual

Complete language and CLI reference for Ultimate Basic, a BASIC-like language that compiles directly to 6502 machine code for the Commodore 64. Output: `.prg` files (VICE or real hardware), `.crt` cartridge images, and `.d64` disk images.

For a short project overview and build instructions see `README.md`.

© 2026 Zsolt Tarczali

Building the `ub` compiler and the command-line options are covered in [README.md](#). This manual documents the Ultimate Basic language itself.

Language reference

Variables and constants

All variables must be declared with `var` before use. Using an undeclared variable in an expression, assignment, `for / loop` counter, `inc / dec`, `input`, or `read` statement produces a compile-time error.

```
var x = 10           # 8-bit integer (default)
var ptr: word = $0400 # 16-bit - two zero-page bytes, usable as 16-bit address
var f: float = 3.5    # Q8.8 fixed-point - hi byte = integer, lo byte = fraction
var msg = "HELLO"     # string variable (pointer to inline PETSCII data)
var s: string = "TEXT" # string with explicit type
var scores = array(10) # byte array, 10 elements stored at $C000+
var moments = array_word(8) # word array, 8 word elements stored at $C000+
const BORDER_ADDR = $D020 # compile-time constant (substituted inline, no ZP slot)
```

Keywords and identifiers are **case-insensitive**: `PRINT`, `Print`, and `print` are all valid.

Type	Width	Notes
<code>int</code>	8-bit	default for numeric literals
<code>word</code>	16-bit	two ZP bytes; can be used as address in <code>poke / peek</code>
<code>float</code>	16-bit Q8.8	hi byte = integer part (0–255), lo byte = fractional part
<code>string</code>	pointer	ZP pair → null-terminated PETSCII in code segment
<code>array(N)</code>	N bytes	byte elements; lives at <code>\$C000+</code> , not in ZP
<code>array_word(N)</code>	N×2 bytes	word (16-bit) elements; lives at <code>\$C000+</code> , not in ZP
<code>array(R, C, ...)</code>	∏dims bytes	multi-dimensional (row-major); index <code>arr[r, c]</code>
<code>array_word(R, C, ...)</code>	∏dims×2 bytes	multi-dimensional word array (row-major)

Reserved words

The following identifiers are **keywords** — they cannot be used as variable, constant, subroutine, function, parameter, or label names. All matching is case-insensitive (`END`, `end`, `End` all collide). Using a reserved word as a name usually produces a confusing error (a `var` line silently fails to declare, or an expression like `for i = 1 to times` folds to `Number(0)`) — so pick a different name.

Declaration & control flow

```
var, const, sub, fn, type, endtype, return, call,
label, goto, gosub,
if, then, else, end, select, case,
for, next, loop, times, to, step, while, repeat, until,
break, continue, inc, dec, bye, exit, rem
```

Music

`tune` (block keyword; the lines inside - `speed`, `inst`, `order`, `pat` - are not reserved)

Types & type-related

```
int, word, float, string, array, array_word
```

Print & I/O

```
print, spc, tab, at, input, chr$, str$, hex, bin,
open, close, load, save, data, read, include, incbin
```

(also `dec` — listed above as the decrement statement; the same token is used for the `dec(n, width)` print format)

Math & string built-ins

```
abs, min, max, clamp, sgn, mod, rnd, sin, cos,
and, or, xor, not, bnot, shl, shr,
len, asc, val, str_to_int, numstr
```

Memory & timing

```
poke, peek, poke16, peek16, fill, memcpy, drawmem,
wait, raster, delay, sys, asm
```

Screen & text

```
cls, fast, color, text, border, bg, screen, cursor,
lowercase, uppercase, display, on, off, scroll,
speed, badlines, turbo
```

Bitmap & block graphics

```
graphics, gcls, flip, plot, plot4, mplot,
mline, mrect, mcircle,
line, circle, circle4, rect, paint, erase,
pen, multi, block
```

Sprites

```
sprite, sprdef, sprite_frame, sprite_x, sprite_y, sprhit, sprbghit,
box_hit, chardef, charset, org, expand, priority
```

Sound & music

```
sid, sound, sfx, volume, music, play, pause, resume, stop
```

Input devices

`getch`, `inkey`, `waitkey`, `joy`, `mouse_x`, `mouse_x_hi`, `mouse_y`, `mouse_btn`

Interrupts & vectors

`irq`, `irq_exit`, `nmi`, `nmi_exit`, `cia_timer`, `onerr`

Character maps & images

`map`, `map_tile`, `map_color`, `koala`, `show`, `hide`

REU (RAM expansion)

`reu`, `reudet`, `stash`, `fetch`

Style pitfalls — names that *look* free but are reserved

These common English words look like innocent identifiers but are already grabbed by the lexer. Rename to avoid silent breakage:

Reserved	Suggested rename
<code>end</code>	<code>stop_at</code> , <code>finish</code> , <code>last</code>
<code>stop</code>	<code>stop_at</code> , <code>halt</code>
<code>times</code>	<code>count</code> , <code>n</code> , <code>iters</code>
<code>screen</code>	<code>scraddr</code> , <code>screen_addr</code>
<code>border</code> , <code>bg</code> , <code>text</code>	<code>border_addr</code> , <code>bg_col</code> , <code>text_col</code>
<code>clamp</code>	<code>cap</code> , <code>bound</code>
<code>line</code> , <code>circle</code> , <code>rect</code>	<code>ln</code> , <code>circ</code> , <code>box_r</code>
<code>data</code> , <code>read</code>	<code>bytes</code> , <code>next_byte</code>
<code>load</code> , <code>save</code> , <code>open</code> , <code>close</code>	<code>load_file</code> , ...
<code>map</code> , <code>show</code> , <code>hide</code>	<code>tilemap</code> , <code>reveal</code> , <code>conceal</code>
<code>play</code> , <code>pause</code> , <code>resume</code> , <code>stop</code> , <code>volume</code>	<code>play_song</code> , <code>vol</code>
<code>int</code> , <code>float</code> , <code>word</code> , <code>string</code>	<code>n_int</code> , <code>speed_f</code> , <code>addr</code> , <code>msg</code>

Symbolic tokens (`+` `-` `*` `/` `=` `==` `!=` `<` `>` `<=` `>=` `:` `,` `;` `(` `)` `[` `]` `#` `$` `%` `@` `)` are naturally not usable in identifiers.

Comments

```
# hash comment
rem this is also a comment
var x = 5 # inline comment
var x = 5 : var y = 6 # colon separates statements on one line
```

Operators

```

x = x + 1
y = a * b - c / 2
z = x and 15          # bitwise AND
w = a or b            # bitwise OR
v = a xor b           # bitwise XOR
m = x shl 3           # shift left
n = x shr 2           # shift right
r = x mod 40          # 8-bit modulo (remainder); SEC/SBC/BCS loop
b = bnot x            # bitwise NOT: x XOR 255 (complement all 8 bits)

```

Comparisons: `==` `!=` `<` `>` `<=` `>=` (return 1/0)

Increment / Decrement

```

inc x                # x = x + 1 (INC zp - single instruction)
dec x                # x = x - 1 (DEC zp - single instruction)

```

For `word` variables carry is handled: `inc` uses `INC lo; BNE skip; INC hi`; `dec` uses `LDA lo; BNE skip; DEC hi; DEC lo`.

Compound Assignments

```

x += 5              # x = x + 5
x -= 3              # x = x - 3
x *= 2              # x = x * 2
x /= 4              # x = x / 4
x and= 15           # x = x and 15 (bitwise AND)
x or= 64            # x = x or 64 (bitwise OR)
x xor= 255          # x = x xor 255 (bitwise XOR)
x shl= 2            # x = x shl 2
x shr= 1            # x = x shr 1

```

Print

```

print "HELLO"
print x
print x, y, "text"
print                # blank line

```

```

print spc(5)           # print 5 space characters
print tab(20), "VALUE" # move cursor to column 20, then print
print "A", spc(3), "B" # mix freely

print "A=" + a         # string + numeric var
print s1 + s2          # two string vars → sequential print
print "Hello " + "World" # two literals → compile-time fold
print chr$(13)         # print by PETSCII code

```

chr\$

```

print chr$(65)         # output character with PETSCII code 65 ('A')
var c = chr$(n)        # store byte value n in variable c
print ">" + chr$(42)    # usable in string concat

```

Branching

```

if x == 1 then
  print "YES"
else
  print "NO"
end

```

Select / Case

```

select x
case 1:
  print "ONE"
case 2:
  print "TWO"
else:
  print "OTHER"
end

```

`select expr` evaluates the expression once and compares it against each `case` value in order. The first matching case body is executed and control jumps to after `end`. The optional `else:` body runs if no case matches. All values must be 8-bit (0–255).

Loops

```

loop 5                # counted loop (5 iterations)
  print "HI"
end

times 5              # alias for loop N ... end
  print "HI"
end

loop                # infinite loop
  x = x + 1
  if x == 5 then continue end # skip to next iteration
  if x == 100 then break end
end

var i = 0
for i = 1 to 10      # for..next (preferred)
  if i == 5 then continue end # skip to increment step
  print i
next

for i = 0 to 20 step 2
  print i
next i              # variable name after 'next' is optional

for i = 10 to 1 step -1  # counting down – negative constant step is supported
  print i
next

for i = 20 to 0 step -2  # terminates correctly at i = 0 (11 iterations)
  print i
next i

var i = 0
loop i = 1 to 10      # legacy loop..end syntax – identical code
  print i
end

while x < 100
  x = x + 1
end

repeat              # do-while: body runs at least once
  x = x + 1
until x == 100      # exits when condition is true

```

Direction rules for `for / loop` :

Case	Behavior
<code>for i = 1 to 10</code> (default <code>step +1</code> , <code>from ≤ to</code>)	counts up, standard
<code>for i = 0 to 20 step 2</code> (positive <code>step</code> , <code>from ≤ to</code>)	counts up by 2
<code>for i = 10 to 1 step -1</code> (negative constant <code>step</code>)	counts down; body runs for <code>i = 10, 9, ..., 1</code>
<code>for i = 20 to 0 step -2</code> (down to zero)	terminates at <code>i = 0</code> by detecting the ADC underflow (<code>C=0</code>) after the decrement; no infinite loop
<code>for i = 10 to 1</code> (no <code>step</code> , <code>from > to</code>)	compile-time error: <code>for-loop: from (10) > to (1) with default step +1 loops 0 times – use 'step -1' to count down</code>

The compiler picks the exit-branch encoding at compile time based on the sign of a constant `step`:

- Positive `step` (or default `+1`) → exit when `var > to` (unsigned `CMP + BCC / BEQ` fall-through to `JMP exit`).
- Negative constant `step` → exit when `var < to` (unsigned `CMP + BCS` to body), **plus** a post-increment `BCS loop_top ; JMP exit` that catches the wrap when `var` underflows below 0. That extra pair of instructions is what keeps `for i = N to 0 step -k` finite.

Non-constant `step` values (e.g. from a variable or expression) are treated as positive at compile time; if you need count-down with a runtime `step` value, split the loop or use a `while` construct.

Labels and goto

```
label main_loop
  x = x + 1
  if x < 10 then goto main_loop end
```

Forward `goto` (label defined later) is fully supported.

`gosub label / return` jump to a label and return back (JSR / RTS at machine code level).

The label must be a `label name` statement, not a `sub` — it has no parameters and shares the same zero-page scope. `gosub` supports forward references (label defined after `gosub`).

```
gosub draw_border
...
label draw_border
  # ... draw something ...
  return           # RTS – returns to the instruction after gosub
```

Subroutines

```

sub greet()
  print "HELLO!"
end

sub set_color(col)
  color border col
  color text col
end

greet()           # call with parens
call greet        # call keyword (no parens)
set_color(6)

```

Parameters are passed via dedicated zero-page slots. No recursion (slots are static).

Typed parameters are supported: `sub draw(x, y:int)` or `sub copy(src:string)` — string parameters receive a 2-byte pointer so the callee can index the source string via `src[i]`.

Functions (return values)

```

fn square(x)
  return x * x
end

fn add(a, b)
  return a + b
end

fn clamp(val, lo, hi)
  if val < lo then return lo end
  if val > hi then return hi end
  return val
end

var s = square(9)           # s = 81 — fn call as expression
var c = clamp(joy, 0, 39)   # c = clamped value
print add(10, 20)          # 30 — usable inline in print

```

Functions support an optional `: word` return type for 16-bit values:

```

fn get_addr(): word
  return $C000
end

```

```

var ptr: word = get_addr() # ptr = $C000
poke ptr, 42              # STA (ptr),Y – valid indirect addressing
var v = peek(ptr)         # LDA (ptr),Y

```

`fn` is emitted in pass 2 (same as `sub`), so function bodies are never executed at startup. Forward references are fully supported.

Arrays

```

var scores = array(8)      # 8 bytes at $C000
                           # (all arrays are zero-filled once at program start – new in 1.5.7)

scores[0] = 100            # constant index → STA $C000
scores[i] = 99             # variable index → STA (ptr),Y
var v = scores[i]         # LDA (ptr),Y
print scores[2]           # usable inline in print

var moments = array_word(8) # 16 bytes (8×2) at $C000+

moments[0] = $1234         # constant index → STA $C000 (lo), STA $C001 (hi)
moments[i] = $5678         # variable index → ASL A for stride; (ptr),Y × 2
var t: word = moments[1]   # LDA $C002, LDA $C003

```

Multi-dimensional arrays (new in 1.5.3)

Arrays may be declared with more than one dimension. They are stored **row-major** and indexed with a comma-separated subscript list. The total size is the product of all dimensions.

```

var grid = array(8, 8)    # 8×8 = 64 bytes at $C000
grid[1, 0] = 11           # row 1, col 0 → flat index 1*8+0 = 8 → STA $C008
grid[0, 1] = 22           # row 0, col 1 → flat index 1 → STA $C001
grid[r, c] = 33           # variable → computes r*8 + c, then STA (ptr),Y
var v = grid[r, c]        # LDA (ptr),Y

var wm = array_word(4, 4) # 4×4 word array = 32 bytes
wm[1, 2] = $ABCD          # element 1*4+2 = 6 → bytes $C00C/$C00D

const ROWS = 3
const COLS = 5
var m = array(ROWS, COLS) # dimensions may be compile-time constants

```

Row-major layout means the last subscript is contiguous: `grid[r, c]` sits at `base + r*COLS + c`. Any number of dimensions is supported (`array(a, b, c)`). When every subscript is a constant the address is folded at compile time to a single absolute store/load; a variable subscript emits the `row*stride + col` computation and an indexed `(ptr),Y` access. A single subscript into a multi-dimensional array is still allowed and treated as a flat/linear index (`grid[10]`). Dimensions must be compile-time constants (literals or `const` s), and the array must be declared before it is indexed.

Struct types (`type ... endtype` , new in 1.5.4)

Define a fixed layout of named fields with `type` , then allocate an array of instances the same way as a regular array. Field access uses `arr[idx].field` and works for both constant and variable indices.

```
type TEntity
  var x: int      # 1 byte
  var y: int      # 1 byte
  var hp: word    # 2 bytes → element size = 4
endtype

const N = 8
var enemies: TEntity = array(N)  # allocates N × 4 = 32 bytes at $C000

enemies[0].x = 5
enemies[0].y = 10
enemies[0].hp = $0100
var v = enemies[0].hp             # read back — LDA $C002 / LDA $C003

var i: int = 2
enemies[i].x = 42                 # variable index → idx * elem_size + offset

# Float field (Q8.8 fixed-point)
type TBall
  var bx: int      # 1 byte
  var by: int      # 1 byte
  var vel: float   # 2 bytes Q8.8 → element size = 4
endtype

var balls: TBall = array(3)
balls[0].vel = 1.5                # stores Q8.8: hi=1, lo=128
var f: float = balls[0].vel       # read float field into float variable
print balls[0].vel                # prints "1.50"
```

Rules and constraints:

- Field types: `int` (1 byte), `word` (2 bytes LE), `float` (2 bytes Q8.8).
`string` and nested `type` fields are not yet supported.
- Element size = sum of field widths (declaration order, no padding).

- Storage lives at `$C000+` alongside regular arrays, and shows up in the memory map as an ordinary array of the total byte size.
- Constant index → `LDA/STA absolute` at compile time.
- Variable index → shift-and-add multiply for `idx * elem_size`, then indexed `(ptr),Y` access. Element sizes that are powers of two (1, 2, 4, 8, 16) use bare `ASL A` chains; other sizes emit a short shift-add sequence via two scratch zero-page bytes.
- Sub / fn parameters of a struct type are not yet supported — pass the array and an index instead, e.g. `sub move(idx: int) ... enemies[idx].x = ...`.
- Default field values (`var fire: int = 2` inside the type) are parsed for compatibility with the proposal but not yet initialized at allocation time.
- Only one subscript is allowed on a struct-typed array; multi-dimensional struct arrays are not supported (use a computed flat index).

See `examples/type_demo.ub`.

16-bit (word) variables

```
var ptr: word = $0400    # two ZP bytes: lo=$00 hi=$04
poke ptr, 6             # STA (ptr),Y
var v = peek(ptr)       # LDA (ptr),Y
```

16-bit products (fixed in 1.5.7). A product assigned to a `word` keeps all 16 bits, also when neither factor is a `word`:

```
var score: word = 0
var level = 3
score += 300 * level    # 900 (before 1.5.7 this was truncated to 8 bits: 44)
score = score + 100 * level
var big: word = 100 * level + 900
```

Bitmap graphics

```
graphics on             # VIC-II hires bitmap mode (320×200, 1bpp); bitmap at $2000
graphics on multi       # VIC-II multicolor bitmap mode (160×200, 2bpp, 4 colours/cell)
graphics off            # return to text mode

gcls                   # clear bitmap (fills $2000-$3FFF) + set video matrix colors

plot x, y              # set pixel at (x, y); x: 0-319, y: 0-199
plot erase x, y         # clear pixel (AND ~mask)
plot xor x, y           # toggle pixel (EOR mask) — flicker-free animation
```

```

circle x, y, r          # midpoint circle centered at (x, y) with radius r; clips off-screen points
line x1, y1, x2, y2     # Bresenham line from (x1,y1) to (x2,y2); x: 0-319, y: 0-199
line erase x1, y1, x2, y2 # clear pixels along the line (AND ~mask)
line xor x1, y1, x2, y2  # toggle pixels along the line (EOR mask)
rect x1, y1, x2, y2      # draw rectangle outline (4 edges); x: 0-319, y: 0-199
rect erase x1, y1, x2, y2 # clear rectangle outline (AND ~mask)
rect xor x1, y1, x2, y2  # XOR rectangle outline (EOR mask)
paint x, y               # 4-connected flood fill from (x, y); fills clear pixels bounded by set
ones

color pen c              # set the hires drawing color (0-15); see below

# — Multicolor bitmap (graphics on multi, 160x200) —
mplot x, y, color        # set multicolor pixel (x: 0-159, y: 0-199, color: 0-3)
mline x1, y1, x2, y2, color # multicolor line
mrect x1, y1, x2, y2, color # multicolor rectangle outline
mcircle x, y, r, color   # multicolor circle

```

Both `graphics on` variants blank the display (`LDA $D011 / AND #$EF / STA $D011`) while switching VIC registers, then re-enable it in the target mode — prevents mode-switch glitches.

`x` may be the full `0-319` range. Coordinates above 255 are handled automatically (the helper adds the 9th X bit), so `plot`, `line`, `circle` and `rect` all reach the right edge of the screen. Use a `word` variable when an X coordinate can exceed 255.

Hires drawing color — `color pen`

In hires mode (320x200) color is **per 8x8 cell**, held in the video matrix (high nibble = foreground, low nibble = background), not per pixel. `color pen c` sets a persistent foreground color (0-15) that `plot`, `line`, `rect`, `circle` and `paint` stamp into the cell of every pixel they draw; the cell's background nibble is preserved. It stays in effect until the next `color pen`. The default is white (1), so programs that never call `color pen` look exactly as before.

```

graphics on
gcls
color pen 2          # red
line 0, 0, 100, 100
color pen 6          # blue
circle 160, 100, 40
display on

```

Multicolor shapes — `mline` / `mrect` / `mcircle`

In multicolor mode (`graphics on multi`, 160x200) each pixel picks one of four color sources via a 2-bit value (`%00` background `$D021`, `%01` screen hi nibble, `%10` screen lo nibble, `%11` color RAM). `mplot` sets a single such pixel; `mline`, `mrect` and `mcircle`

draw shapes the same way — the trailing `color` argument is the 2-bit source (0-3), and the actual colors come from the cell palette (screen / color RAM) exactly as for `mplot`.

```
graphics on multi
gcls
mcircle 80, 100, 40, 1
mrect 10, 10, 150, 190, 2
mline 0, 0, 159, 199, 3
display on
```

`mline` / `mrect` / `mcircle` reuse the same Bresenham / midpoint routines as their hires counterparts, plotting each pixel through `mplot`; off-screen points ($x \geq 160$ or $y \geq 200$) are skipped.

Double-buffered bitmap (flicker-free)

```
graphics on double      # double-buffered hires bitmap (320×200)
gcls                    # clears the HIDDEN back buffer
line 0, 0, 319, 199     # all drawing (plot/line/circle/rect/paint/gcls) goes to the back buffer
flip                    # show the drawn buffer; redirect drawing to the other one
graphics off            # back to text mode (restores VIC bank 0)
```

`graphics on double` keeps **two** complete hires bitmaps and shows only finished frames, eliminating flicker without any XOR tricks — each frame you `gcls`, draw, then `flip`.

Buffer	Bitmap	Video matrix	VIC bank	\$DD00 low bits
A (front, shown first)	\$2000	\$0400	bank 0	%11
B (back, drawn first)	\$6000	\$4400	bank 1	%10

- All pixel commands write through a runtime **draw base** (a zero-page byte), so they automatically target whichever buffer is currently hidden.
- `flip` waits for the lower border (raster ≥ 251) before switching the VIC bank, so the swap is **tear-free**, then points the draw base at the now-hidden buffer.
- Typical loop: `gcls` → draw the frame → `flip`. Call `display on` once after the first `flip` so the first shown buffer is already complete.

Requirements / limits:

- Hires only (not `multi`). Sprites are not fetched from the back buffer's VIC bank.
- The back buffer uses `$4000–$7FFF` (matrix `$4400`, bitmap `$6000–$7FFF`), so the program's machine code must stay below `$4400`. Most demos are only a few KB, so this is automatic; very large programs cannot use double buffering.

- On a stock 1 MHz C64 the per-frame full `gcls` (8 KB) limits the frame rate; on the Commodore 64 Ultimate raise `speed` for smooth high-rate animation.

See `examples/cube_demo.ub` — a tumbling 3D wireframe cube rendered flicker-free.

Block graphics (80×50)

```
graphics on block      # 80×50 block-pixel mode (text mode + custom 4-pixel charset @ $2800)
graphics off          # return to text mode
gcls                  # clear block playfield: screen RAM $0400-$07FF + color RAM $D800-$DBFF

plot4 x, y            # set block pixel at (x, y); x: 0-79, y: 0-49
plot4 erase x, y       # clear block pixel at (x, y)
circle4 x, y, r        # draw midpoint circle in block pixels; clips to 80×50
```

A chunky low-res mode layered on standard 40×25 text. A 16-character custom charset copied to `$2800` encodes a 2×2 quadrant grid per character (bit3=TL, bit2=TR, bit1=BL, bit0=BR), so each text cell holds 2×2 block pixels → an effective 80×50 grid. No bitmap RAM is used (`$2000-$3FFF` stays free), making it faster than hires bitmap. `plot4` OR's the quadrant bit into the cell so overlapping pixels accumulate; `plot4 erase` clears it. `circle4` uses the same block-pixel helper to draw an outline circle in the 80×50 coordinate space. `gcls` clears both screen and color RAM.

See `examples/block_demo.ub`.

Screen and color

```
cls                  # clear screen (KERNAL $E544)
cls fast             # fast fill: screen RAM + color RAM + HOME

color text 14        # text color register $0286
color border 6       # $D020
color bg 0           # $D021
color pen 2          # hires drawing color (0-15) for plot/line/rect/circle/paint

screen 0, 0, 65      # write char 65 ('A') to screen RAM at col 0, row 0 ($0400)
screen 10, 5, ch     # col 10, row 5 — col/row can be variables
screen 5, 3, 42, 7   # char 42 at col 5, row 3, color 7 (writes color RAM $D800 too)
screen x, y, ch, col # all four arguments as variables

display on           # re-enable VIC display ($D011 DEN bit)
display off          # blank display

lowercase            # CHR$(14) → switch VIC-II to lowercase/uppercase charset
uppercase            # CHR$(142) → switch VIC-II back to uppercase/graphics charset

cursor 20, 10        # move cursor to col 20, row 10 (KERNAL PLOT $FFF0)
cursor x, y          # column from variable x (0-39), row from y (0-24)
```

```

print at 20, 10, "HELLO" # cursor(20,10) + print in one statement (no trailing newline)
print at x, y, "Score:", score # any mix of exprs
print at 0, 0 # position only (no text, no newline)

scroll x 3 # set horizontal fine scroll: $D016 bits 0-2 = 3 (0-7)
scroll y 2 # set vertical fine scroll: $D011 bits 0-2 = 2 (0-7)
scroll x n # value can be a variable or expression (masked to bits 0-2)
scroll x 7 narrow # set fine scroll and force 38-column mode (hide edge column)
scroll x 0 wide # set fine scroll and restore 40-column mode
scroll row 12 left # shift screen RAM row 12 left by one character

```

`lowercase` emits `LDA #$0E; JSR $FFD2` at runtime. String literals compiled after `lowercase` have their case swapped automatically — uppercase source chars are stored in the PETSCII lowercase slot (`$61+`) and lowercase source chars in the uppercase slot (`$41+`) — so `"Hello World"` source displays as **Hello World** on screen.

`uppercase` emits `LDA #$8E; JSR $FFD2` and reverts to direct mapping. `cls` does **not** reset the charset mode.

`scroll x n` writes `(n AND 7)` into bits 0-2 of `$D016` (preserving bits 3-7).

`scroll x n narrow` writes the fine-scroll bits and clears `$D016` bit 3 (38-column mode).

`scroll x n wide` writes the fine-scroll bits and sets `$D016` bit 3 (40-column mode).

`scroll y n` writes `(n AND 7)` into bits 0-2 of `$D011` (preserving bits 3-7).

`scroll row R left` shifts one constant screen row left; write the new rightmost character with `screen 39, R, ch`.

Useful for smooth hardware scrolling: decrement each frame from 7 down to 0, shift screen RAM, reset to 7.

`screen col, row, char [, color]` writes directly to screen RAM (`$0400 + row*40 + col`) and optionally to color RAM (`$D800 + row*40 + col`). Constant col/row: address computed at compile time.

Ultimate 64 — CPU Speed

```

speed 4 # set CPU to 4 MHz (reads $D031, updates bits 0-3, writes back)
speed 48 # 48 MHz (maximum speed on U64)
speed max # same as speed 48 (alias)
speed off # back to 1 MHz (alias for speed 1)

badlines on # enable badline timing ($D031 bit 7 = 0, default C64 behaviour)
badlines off # disable badline timing ($D031 bit 7 = 1, more CPU cycles)

var t = turbo() # 1 if turbo is active (bits 0-3 of $D031 != 0), 0 if at 1 MHz

```

Available MHz values: `1, 2, 3, 4, 5, 6, 8, 10, 12, 14, 16, 20, 24, 32, 40, 48`.

Constant values are rounded down to the nearest available speed at compile time.

Variable values are treated as a raw speed index (0–15) and OR'd into bits 0-3 of `$D031`.

\$D031 index	MHz (U64)	MHz (U64 Elite-II)
0	1	1

\$D031 index	MHz (U64)	MHz (U64 Elite-II)
3	4	4
6	8	10
11	20	24
15	48	64

Requires **U64 Turbo Control** set to `U64 Turbo Registers` or `Turbo Enable Bit` in the U64 config menu. On a regular C64 or emulator without the register, the `poke` to `$D031` is silently ignored.

Keyboard

```

var key = getch()      # busy-wait on $FFE4 until key; returns PETSCII code
var k    = inkey()      # non-blocking: returns PETSCII code, or 0 if no key pressed
waitkey              # wait until any key is pressed (CIA1 matrix scan; works during IRQ)
var k    = waitkey()    # same but returns raw $DC01 column bits (0 bit = key pressed)
var j = joy(2)          # read joystick port 2; returns inverted bits 0-4
var j = joy(1)          # read joystick port 1
                        # bit0=up(1) bit1=down(2) bit2=left(4) bit3=right(8) bit4=fire(16)

var mx = mouse_x()      # 1351 mouse: accumulated X position (helper: charge+delay+delta)
var my = mouse_y()      # 1351 mouse: accumulated Y position (EOR #$FF inverted)
var mb = mouse_btn()    # mouse buttons: reads $DC01 - bit0=left (fire), bit1=right (up pin)

```

`mouse_x()` / `mouse_y()` internally run a helper subroutine that handles: CIA1 `$DC00` capacitor charging, ~516-cycle delay, SID POT X/Y register read (`$D419` / `$D41A`), signed 7-bit delta computation, Y-axis `EOR #$FF` inversion, and accumulated position tracking (permanent ZP state, 8 bytes). The helper samples POT twice per frame. `mouse_y()` does **not** call the helper (only `mouse_x()` does) — it just reads the cached `accum_y` to avoid double-update.

The helper maintains a 9-bit X accumulator (`accum_x` + `accum_x_hi` with carry/borrow). Use `var sx: word = mouse_x()` — the compiler stores both lo and hi bytes, so the `sprite` command correctly handles `$D010` for X positions beyond 255.

The helper stores its state in ZP (`$02` – `$09`). The init flag must be zero before the first call — zero the area with `fill $02, 7, 0` early in your program. Also disable CIA1 interrupts (`poke $DC0D, $7F`) to prevent the KERNAL IRQ from touching `$DC00` during keyboard scanning — that disturbs the POT reading.

See `examples/mouse_demo.ub` for a working 1351 mouse demo with sprite tracking and button feedback.

Exit

```
bye                # JSR $E544 (clear screen), clear STOP flag, RTS to BASIC
exit              # alias for bye
```

Timing

```
wait 50            # wait 50 raster-line transitions (~3.2 ms)
wait raster 100    # spin until $D012 == 100 (raster-split effects)
delay 1            # wait 1 PAL frame (1/50 s ≈ 20 ms)
delay 20           # wait 20 frames ≈ 0.4 s; n can be a variable (0-255)
```

`delay N` counts N complete PAL frames using raster line 200 as the frame boundary.

SID Sound

```
sound 0, $1CAD, 25  # voice 0, freq $1CAD (≈ middle C PAL), 25 frames duration
sound 1, freq_word, 50 # voice 1, freq from word var, 50 frames (1 s at 50 Hz)
sound 2, 0, 0       # voice 2, silence

sid volume 15       # master volume full ($D418 = $0F); range 0-15
sid volume 0        # silence (master volume = 0)
sid stop            # zero all 25 SID registers ($D400-$D418) — complete silence
```

`sound <channel>, <freq>, <duration>` — duration in PAL frames (1/50 s each). **sound blocks:** the program waits until the note has finished (use `sfx` below inside a game loop).

Fixed ADSR: attack/decay `$09`, sustain/release `$F0`, sawtooth waveform.

Master volume `$D418` always set to `$0F`.

Fixed in 1.5.7: the wait loop watched raster line 0, which `$D012` (low 8 bits only) shows twice per frame (lines 0 and 256), so every note lasted **half** as long as requested — and two branches were patched over their opcode, which crashed the program for any duration other than 0.

`sound` now waits on raster line 200 exactly like `delay`.

`sid volume N` writes N to `$D418`. Bits 0-3 = volume (0-15), bits 4-7 = filter mode.

`sid stop` emits a 10-byte zero-fill loop — faster than 25 individual pokes.

Non-blocking sound effects (`sfx`) — new in 1.5.7

```

sound 0, $2000, 25      # BLOCKS: the program waits 25 frames here
sfx 0, $2000, 25        # returns at once; the note fades out by itself
sfx 1, $0500, 8, 128    # optional wave: 16 triangle, 32 saw (default), 64 pulse, 128 noise
sfx 0, freq_word, 4, 16 # freq may be a constant, a word var or an 8-bit expression

```

`sfx <channel>, <freq>, <frames> [, <wave>]` programs one SID voice and returns immediately, so it is safe inside a game loop. There is no gate-off timer: the envelope is set to attack 0 / sustain 0 / release 0 and the **decay** is chosen at compile time from `frames` (1 frame = 20 ms, nearest SID decay time: 6, 24, 48, 72, 114, 168, 204, 240, 300, 750, 1500, 2400 ms ...), so the note dies away over roughly that time. It re-triggers the voice each call (gate off, then on) and sets master volume `$0F`.

`channel` (0-2), `frames` (1-255) and `wave` must be compile-time constants.

Music playback

`music play/stop/pause/resume` is a high-level alternative to the manual `sys sid_init` / `cia_timer` setup. Requires a prior `load sid` statement (defines `sid_init` / `sid_play`).

```

load sid "tune.sid"      # embed SID file (defines sid_init / sid_play)

music play               # initialise sub-tune 0 + start CIA1 50 Hz IRQ
music play 1             # start from sub-tune 1 (song number 0-based)
music stop               # stop playback + zero all 25 SID registers ($D400-$D418)
music pause              # disable CIA1 timer A IRQ (music freezes, SID unchanged)
music resume             # re-enable CIA1 timer A IRQ (continues from pause point)

```

Statement	Effect
<code>music play [n]</code>	call <code>sid_init(n)</code> , configure CIA1 timer A at 19 656 cycles (~50 Hz PAL), install IRQ wrapper
<code>music stop</code>	disable CIA1 IRQ + zero all 25 SID registers
<code>music pause</code>	disable CIA1 IRQ (SID output remains frozen)
<code>music resume</code>	re-enable CIA1 IRQ (continues from pause point)

The IRQ wrapper (emitted once at the end of the program) does: ACK CIA1 timer A → `JSR sid_play` → `JMP $EA81`.

Sprites

```

sprite 0, x, y, $2000    # sprite 0: set X, Y position and data pointer
sprite 0, x, y           # without data pointer (keeps existing)
sprite on 0              # enable sprite 0 ($D015 |= bit0)

```

```

sprite off 0          # disable sprite 0 ($D015 &= ~bit0)
sprite color 0, 7      # sprite 0 color = yellow ($D027)
sprite multicolor 0, on # enable multicolor mode for sprite 0 ($D01C |= bit0)
sprite multicolor 0, off # disable multicolor mode ($D01C &= ~bit0)
sprite expand x 0, on  # double width ($D01D |= bit0)
sprite expand x 0, off # normal width ($D01D &= ~bit0)
sprite expand y 0, on  # double height ($D017 |= bit0)
sprite expand y 0, off # normal height ($D017 &= ~bit0)
sprite priority 0, on  # behind background ($D01B |= bit0)
sprite priority 0, off # in front of background ($D01B &= ~bit0)
var h = sprite_hit()   # sprite-sprite collision ($D01E, cleared on read)
var b = sprite_bg_hit() # sprite-background collision ($D01F, cleared on read)
var x = sprite_x(0)    # read sprite 0 X position (lo byte, $D000)
var y = sprite_y(0)    # read sprite 0 Y position ($D001)
sprite_frame 0, $2000   # select one static sprite image
sprite_frame 0, $2000, frame # select an animation frame from a frame sequence

```

X supports full 9-bit range (0–319): use a `word` variable for runtime values > 255.

Sprite data pointer: `data_addr` must be 64-byte aligned; stored as `addr >> 6` at `$07F8+id`.

Sprite animation with `sprite_frame`

`sprite_frame` is the command used to change the displayed image of a sprite during animation. It changes only the sprite's data pointer; it does **not** move the sprite, enable it, or advance frames automatically.

Store the animation images consecutively, with each 63-byte sprite image occupying one 64-byte-aligned slot. Pass the zero-based animation frame as the third argument:

```

sprite_frame sprite_id, first_frame_address, frame_number

```

For example, with a base address of `$2000`, frame 0 uses `$2000`, frame 1 uses `$2040`, frame 2 uses `$2080`, and so on. The program controls animation timing and wrapping:

```

var frame = 0
loop
  sprite_frame 0, $2000, frame
  frame = frame + 1
  if frame == 4 then frame = 0 end
  delay 5
end

```

The two-argument form, `sprite_frame id, address`, simply selects one static sprite image and remains backward compatible. Sprite position is still controlled by `sprite id,x,y`.

Software bounding-box collision

```
var touching = box_hit(left1, top1, right1, bottom1,
                        left2, top2, right2, bottom2)
```

`box_hit()` performs an axis-aligned bounding-box (AABB) test and returns `1` when the two rectangles overlap or touch, otherwise `0`. Unlike `sprite_hit()` and `sprite_bg_hit()`, it does not read or clear VIC-II collision registers. The eight arguments are arbitrary 8-bit expressions, so boxes may be smaller than the visible sprite artwork or may describe non-sprite game objects. Coordinates are inclusive; keep `left <= right` and `top <= bottom`.

Sprite definition

```
sprdef 0
    $00,$3C,$00, $00,$FF,$00, $03,$FF,$C0, $07,$FF,$E0,
    $0F,$FF,$F0, $0F,$FF,$F0, $1F,$FF,$F8, $1F,$FF,$F8,
    $1F,$FF,$F8, $0F,$FF,$F0, $0F,$FF,$F0, $07,$FF,$E0,
    $03,$FF,$C0, $00,$FF,$00, $00,$3C,$00, $00,$00,$00,
    $00,$00,$00, $00,$00,$00, $00,$00,$00, $00,$00,$00,
    $00,$00,$00
end
```

`sprdef id ... end` embeds 63 sprite bytes at the next 64-byte-aligned address in the code segment, emits a `JMP` over them, and automatically sets `$07F8+id = data_addr >> 6`.

To use the same shape for multiple sprites, read back the pointer:

```
var pg = peek($07F8)    # pointer set by sprdef 0
poke $07F9, pg          # copy to sprites 1-7
```

Character tile maps (`.ubmap`)

```
map load "levels/world.ubmap"
map draw map_x, map_y      # draw a 40x25 viewport to screen/color RAM

var tile = map_tile(x, y)  # read character code from the map
map set x, y, 42           # change character code in writable map data
```

```
var shade = map_color(x, y) # read cell color (0 when map has no color data)
map color x, y, 7          # change cell color when color data is present
```

`map load` resolves the filename relative to the `.ub` source file, validates it at compile time, and embeds its character and optional color arrays in writable program RAM. A later `map load` replaces the active map for subsequent map commands.

`map load` also accepts a VisualAssembler `me-map .bin` export directly:

```
map load "map-multicolor.bin"
```

The first 1000 bytes become the 40×25 character map and the next 1000 bytes become cell colors. Multicolor mode and `$D021-$D023` are read from the VisualAssembler metadata trailer, so no `.ubmap` conversion is required.

`map draw map_x, map_y` copies a 40×25 viewport beginning at the specified map cell to screen RAM `$0400` and, when present, color RAM `$D800`. The map must contain the whole requested viewport: keep `map_x <= width-40` and `map_y <= height-25`. Coordinates and dimensions are currently 8-bit (0–255).

Normal maps clear the text multicolor bit in `$D016`. Multicolor maps set it and load their three global colors into `$D021`, `$D022`, and `$D023`. Character maps contain character codes, not charset pixels; combine them with `charset / chardef` or another charset-loading method. In multicolor text mode, cell colors 8–15 select multicolor characters according to the VIC-II rules.

UBMP version 1 binary format

All multibyte integers are little-endian:

Offset	Size	Meaning
0	4	ASCII magic <code>UBMP</code>
4	1	Version, currently <code>1</code>
5	1	Flags: bit 0 = color array present, bit 1 = multicolor text mode
6	2	Map width, 1–255 cells
8	2	Map height, 1–255 cells
10	1	Background 0 (<code>\$D021</code>), low nibble used
11	1	Multicolor 1 (<code>\$D022</code>), low nibble used
12	1	Multicolor 2 (<code>\$D023</code>), low nibble used
13	width×height	Row-major character codes
following	width×height	Optional row-major color nibbles when flag bit 0 is set

An UBMP file must have the exact length implied by its header. Invalid magic, version, dimensions, or length produces a compile-time error.

Koala Painter image import

```
koala load "pictures/title.kla" # validate and embed at compile time
koala show                     # enter bitmap multicolor mode
koala hide                     # return to the default text display
```

`koala load` accepts a standard 10003-byte Koala file (`$6000` load address plus 10001 data bytes) or a raw 10001-byte payload. Paths are relative to the `.ub` file. The payload contains 8000 bitmap bytes, 1000 screen bytes, 1000 color nibbles, and one background-color byte.

The compiler stores it at `$6000-$8710`. `koala show` copies the bitmap to `$2000`, the screen matrix to `$0400`, colors to `$D800`, and enables bitmap multicolor mode. `koala hide` clears bitmap/multicolor mode and restores the default text layout.

Generated code and helpers must finish below `$2000`, because the displayed bitmap overwrites `$2000-$3F3F`; the compiler reports an error otherwise. Koala import cannot currently be combined with `load sid` in the same program.

Code layout: `org` — new in 1.5.7

```
sub a() ... end           # subs/fns are placed one after another from the end of the main body
org $4000                 # the next subs/fns continue at $4000; $xxxx-$3FFF stays zero-filled
sub b() ... end
incbin "font.bin", $3800 # data can live in the gap ($3800-$3FFF is a whole VIC charset slot)
```

`org addr` goes **between sub/fn definitions** (it is ignored in the main body and only acts in the second pass). Subroutines never fall through into each other, so the skipped bytes are just zero-filled and reserved: an `incbin "f", addr` that lies wholly inside the gap is written into it, and `charset on` does not count the gap as code. The zero bytes are part of the `.prg`. `org` below the current code end is a compile-time error. Everything generated after the last sub (helpers, `data` tables) follows the last sub, i.e. lands above the gap.

Custom charset (`charset on` / `charset off` new in 1.5.7)

```
charset $3800             # set base address for chardef (default $3800)

chardef 65                # redefine character 65 ('A')
    $18,$3C,$66,$7E,$66,$66,$66,$00
```

```

end

chardef 66          # fewer than 8 bytes are zero-padded
    $7C,$66,$7C,$66,$7C
end

```

`charset base` sets the destination address used by all subsequent `chardef` statements. `chardef id ... end` embeds 8 bytes inline in the code segment (preceded by a `JMP` to skip over them), then copies them to `charset_base + id*8` at runtime. Values must be compile-time constants written as `$xx` or decimal. **% binary literals are not supported** by the lexer (the manual said so before 1.5.7 — that was wrong).

`charset addr` only sets the `chardef` destination; it emits no code. To make the VIC-II use the set, switch it on (and off again when you are done):

```

charset $3800
chardef 1  $FF,$81,$81,$81,$81,$81,$81,$FF end # box border
charset on      # VIC-II reads characters from $3800 (screen matrix untouched)
...
charset off     # back to the ROM set ($1800 if `lowercase` is active, else $1000)

```

`charset on` read-modify-writes `$D018` bits 1-3 from the last `charset addr` (default `$3800`); the screen-matrix bits are preserved. The address must be a multiple of `$800` inside VIC bank 0 (`$0000-$3FFF`), otherwise it is a compile-time error. Both statements use the `charset addr` that was compiled last, so keep the directive in the main program body (subroutine bodies are compiled after it). The equivalent raw write is `poke $D018, $1A` for `$2800` or `poke $D018, $1E` for `$3800`.

Overlap check. `charset on` claims the whole 2 KB set and every `chardef` its 8 bytes. If the generated code reaches into that area the build stops with

```

the program code ($080D-$xxxx) overlaps the charset area $2800-$2FFF; move the charset
...

```

Large programs therefore need the set above the code (`charset $3800`) — or use `org` (above) to let the code continue above the set. Data placed in an `org` gap (`incbin ..., addr`) is not counted as code.

Memory

```

poke $D020, 2          # STA $D020
poke addr_var, 6        # STA (addr_var),Y - if addr_var is word type
var v = peek($D012)     # LDA $D012
var v = peek(addr_var)  # LDA (addr_var),Y - if addr_var is word type

var w: word = peek16($C000) # read 16-bit little-endian: lo=$C000, hi=$C001

```

```
poke16 $0314, $EA81      # write 16-bit little-endian: lo→$0314, hi→$0315
poke16 ptr, w            # word var as address; word var as value
```

peek16(addr) reads two consecutive bytes (lo, hi) as a word. poke16 writes lo then hi.

Disk I/O

```
load "PROGRAM"           # KERNAL LOAD: loads file from device 8 to its native address
load "DATA", $C000       # loads file to a specific address
load "DATA", ptr         # addr from word variable

save "DATA", $C000, 4096 # KERNAL SAVE from $C000, 4096 bytes → device 8
save "PROG", start, len  # addr and len from word/int variables
```

load calls KERNAL SETNAM + SETLFS + LOAD (\$FFBD / \$FFBA / \$FFD5).

Without address: secondary address 0 (file's own 2-byte header used as load address).

With address: secondary address 1 (file loaded to specified location).

save calls SETNAM + SETLFS + SAVE (\$FFBD / \$FFBA / \$FFD8). Requires both addr and len.

Tracker tunes (tune)

```
tune                      # optional: tune at $C800 (default $8000)
  speed 6                 # frames per row (50 Hz PAL)
  inst 0, $41, $09, $F0, $0800, $0064, $27, $1F
  inst 1, $10, $08, $A8, $0400, $0000, $00, $0F
  order 0, 1, 0           # pattern order (patterns may repeat)
  pat 0, 0, "C-4 00", "...", "E-4 00 V24", "...", "G-4 00", "... .. C00"
  pat 0, 1, "C-2 01", "...", "...", "...", "G-2 01 F03"
end
music play                # or: sys sid_init / irq handler calling sys sid_play
```

tune ... end describes a 3-voice tracker tune in plain text (the same cell notation the Visual Assembler SID editor shows) and builds the player **at compile time**. It defines sid_init / sid_play exactly like load sid, so music play, music stop, music pause and music resume (and a manual irq handler calling sys sid_play) work unchanged.

Line	Meaning
speed N	Frames per tracker row (1-255).
inst id, ctrl, ad, sr, pw, cutoff, resfilt,	One instrument: control register (waveform bits; the gate bit is added by the player), attack/decay, sustain/release, 12-bit pulse width, 11-bit filter cutoff, resonance/filter-routing

Line	Meaning
modevol	byte (\$D417) and mode/volume byte (\$D418).
order p, p, ...	Pattern order. Lines accumulate, up to 255 steps.
pat p, v, "cell", ...	Up to 32 rows for voice v (0-2) of pattern p (0-7). Missing rows are empty.

A **cell** is NOTE INST FX: C-4 , D#3 , Eb2 or ... for no note, a two-digit hex instrument (.. to leave it), and an optional effect - Vxy vibrato (x = hold rows, y = depth), Uxx / Dxx slide up / down, C note cut, Fxx set speed. An effect-only cell can be written as "... .. F06" or just "F06" .

Notes on the player:

- All player state lives **inside the blob** (absolute addressing) - it uses no zero page, so it cannot collide with UltimateBasic variables or temporaries, and it keeps working when the program returns to BASIC.
- The blob is placed at a fixed address (default \$8000 , or tune at \$addr) and the .prg is padded up to it, like load sid . Keep it clear of your code, arrays (\$C000+) and any bitmap/charset memory. A tune needs about 1.3 KB plus 12 bytes per row-column of data.
- At most 8 patterns (32 rows each); the order list can repeat them freely.
- music play uses the CIA1 timer at 50 Hz; do not combine it with another load sid / tune (the last one wins).

SID Music

```
load sid "tune.sid"           # embed SID music at its native load address
load sid "tune.sid", $2000    # override: embed at $2000 regardless of SID header
```

load sid reads a PSID or RSID file at **compile time**, strips the header, and appends the raw music bytes to the output .prg . After load sid , two compile-time constants become available:

Constant	Description
sid_init	Init routine address — call once with A = song number (0-based)
sid_play	Play routine address — call every frame (50 Hz PAL) from an IRQ handler

Both constants work anywhere a constant address is accepted: sys , irq , poke , expressions.

Typical usage:

```
load sid "music.sid"

sub music_irq()
    poke $D019, $FF    # ACK VIC raster IRQ
    sys sid_play        # advance one frame of music
    irq_exit           # JMP $EA81: restore A/X/Y + RTI (proper IRQ exit)
```

```

end

sys sid_init, 0      # initialise SID chip: A=0 → first sub-tune
irq music_irq, $C0   # raster IRQ at line $C0 → 50 Hz on PAL

sid volume 15        # master volume on

```

Notes:

- SID data is placed **after** all generated code, padded with zeros up to the load address. The compiler warns if the SID load address would overlap generated code.
- PSID v1 and v2 are supported. If the SID header's load address is 0, the first two data bytes are used as the address (PRG-style, little-endian).
- Only one `load sid` per program is meaningful (the last one wins).

Serial channel file I/O

```

open 1, 8, 2, "MYFILE" # open logical file 1, device 8, secondary 2, name "MYFILE"
open 2, 4, 7           # open printer (device 4), no filename
open ch, dev, sec      # channel, device, secondary from variables

print# 1, "HELLO"      # send "HELLO"+CR to logical file 1
print# ch, x, "text"    # any mix of vars, strings – same as print but to file

close 1                # close logical file 1
close ch               # channel from variable

```

`open` calls `SETNAM ($FFBD) + SETLFS ($FFBA) + OPEN ($FFC0)`. Without a filename, `SETNAM` is called with length 0.

`print#` routes output via `CHKOUT ($FFC9)`, `CHROUT` per char (+ trailing CR), then `CLRCHN ($FFCC)`.

`close` puts the channel number in A and calls `CLOSE ($FFC3)`.

Input

```

input score           # read up to 3 digits from keyboard → 8-bit int var
input "Name: ", name  # optional prompt string, then read line → string var
input "Score: ", score # prompt + int input

```

`input` uses KERNAL BASIN (`$FFCF`) for blocking, echoed line input with DEL support.

- **Int var**: accepts only 0 – 9, max 3 chars; converts to 8-bit value on CR.
- **String var**: accepts up to 30 chars; stores as null-terminated string; ZP pair updated.

Float / Fixed-Point

`float` variables use Q8.8 fixed-point format: the high byte is the integer part (0–255) and the low byte is the fractional part (0/256 ... 255/256).

```
var f: float = 3.5      # 3.5 → hi=3, lo=128 (= 0x0380)
var g: float = 0        # integer 0 is promoted to 0.0 automatically

f = 1.5                # Q8.8 literal assignment
f = f + 1.5            # 16-bit Q8.8 arithmetic (result: 3.0)
f = f + g              # float + float

var n = int(f)         # extract integer part (hi byte) → 8-bit int
print f               # prints as "N.DD" (e.g. 3.5 → "3.50", 1.25 → "1.25")
```

Operation	Example	Notes
Literal	<code>3.5</code> , <code>0.25</code> , <code>1.0</code>	parsed as Q8.8 at compile time
Integer promotion	<code>f = 5</code>	stores 5.0 (hi=5, lo=0)
Add/sub	<code>f + 1.5</code> , <code>f - g</code>	16-bit Q8.8 arithmetic
Extract int	<code>int(f)</code>	returns hi byte as 8-bit int
Print	<code>print f</code>	format "N.DD", always 2 fractional digits

Caveat: Arithmetic overflow wraps at 255.255 (no saturation). Multiplication and division of two float variables are not yet supported — use `int()` + integer arithmetic for those cases.

Printing float expressions (fixed in 1.5.7). `print` of an arithmetic expression that involves a `float` (for example `print a / 10` with `a: float = 1`) now prints the Q8.8 result as `N.DD`. Before 1.5.7 it printed the raw 16-bit value as an integer (`25` instead of `0.09`). The fraction is truncated, not rounded: $1/10 = 25/256$ prints as `0.09`.

Math functions

```
var a = abs(x - 20)      # two's-complement absolute value
var b = min(x, 39)       # 8-bit minimum
var c = max(x, 0)        # 8-bit maximum
var s = sgn(score)       # 0 = zero, 1 = positive (1-127), $FF = negative (128-255)
var r = rnd()            # LCG pseudo-random 0-255; seed from raster line
var r = rnd(10)          # LCG pseudo-random 0-9 (rnd() mod n; result 0..n-1)
var s = sin(angle)       # sine: angle 0-255 (full circle), returns 0-255 (center=128)
var c = cos(angle)       # cosine = sin(angle+64)
var v = clamp(x, 0, 39)  # 8-bit unsigned clamp: result = max(lo, min(hi, val))
```

```
print hex(n)           # print as 2-digit uppercase hex
print bin(n)           # print as 8-bit binary string
```

String functions

```
var n = len(msg)        # length of null-terminated string var (0-255)
var c = asc(msg)        # PETSCII code of first character (0 if empty)
var c = asc("A")        # compile-time: constant PETSCII code
var n = val(s)          # runtime: parse decimal PETSCII string → 8-bit int (e.g. "042" → 42)
var c = msg[i]          # string character at index i: PETSCII code of msg[i]
msg[i] = c              # write PETSCII byte c to string at index i — STA (ptr),Y
msg[0] = 72             # constant index → LDY #0; STA (ptr),Y
```

Number formatting

```
print hex(n)           # print as 2-digit uppercase hex
print bin(n)           # print as 8-bit binary string
print dec(n, 4)        # right-justified decimal in a field of 4 chars (e.g. 42 → " 42")
print dec(n, width)    # width can also be a variable
```

`dec(n, width)` pads the number on the left with spaces to fill `width` characters.

If the number has more digits than `width`, it is printed without padding (no truncation).

In non-print contexts `dec(n, w)` evaluates to `n` unchanged (same as `hex/bin`).

REU (RAM Expansion Unit)

```
var ok = reu_present()  # 1 if REU detected, 0 if not (write/read test on $DF04)
var ok = reudet()       # alias for reu_present()

reu stash c64addr, bank, reu_addr, len # copy C64 → REU
reu fetch c64addr, bank, reu_addr, len # copy REU → C64
reu swap c64addr, bank, reu_addr, len # swap between C64 and REU
```

`reu_present()` performs a write/read-back test on REU register `$DF04`. Without an REU the write is lost (open bus), so the read-back differs — reliably detects presence without touching any side-effecting command register.

Parameter	Width	Notes
c64addr	16-bit	C64 RAM start — constant, <code>word</code> var, or 8-bit expr
bank	8-bit	REU bank number (0–7 for a 512 KB unit)
reu_addr	16-bit	Offset within the REU bank
len	16-bit	Bytes to transfer (0 = 65 536 in REU hardware)

REU registers: `$DF01` command (`$B0` stash / `$B1` fetch / `$B2` swap),
`$DF02–$DF03` C64 addr, `$DF04–$DF05` REU offset, `$DF06` bank, `$DF07–$DF08` length.
 Transfer is synchronous (CPU halted during DMA).
 Requires a real REU or VICE: **Settings** → **Hardware** → **RAM Expansion Module**.

Memory utilities

```

fill screen 32          # fill screen RAM $0400–$07FF with value 32 (space char)
fill color 1            # fill color RAM $D800–$DBFF with value 1 (white)

fill $0400, 1000, 32    # fill 1000 bytes starting at $0400 with value 32
fill addr, 256, 0       # addr can be word var
fill ptr, len_word, val # all operands can be expressions / word vars

memcpy $C000, $0400, 256 # copy 256 bytes from $C000 → $0400
memcpy src_ptr, dst_ptr, 40 # word vars for source and destination

drawmem $C000, $0400, 8, 10, 40 # blit 8×10 rect from $C000 → screen at $0400, stride 40
drawmem src_ptr, dst_ptr, w, h, 40 # word vars for src/dst

```

Both `fill` and `memcpy` support 16-bit lengths (0–65535). Use `word` variables for lengths > 255.

`drawmem src, dst, width, height, stride` copies a 2-D rectangular block. `src` is read linearly (packed rows); `dst` advances by `stride` bytes between rows — use 40 (\$28) for the C64 screen or color RAM (40 columns). Width, height and stride are all 8-bit values.
`src` and `dst` may be constants, `word` variables, or 8-bit expressions.

Raster IRQ

```

irq my_handler          # raster IRQ at line 0, handler = sub name or address
irq my_handler, 100     # raster IRQ at raster line 100
irq $C800, 200          # handler at fixed address
irq addr_word           # handler address from a word variable

```

Sets up a raster IRQ via the BASIC soft vector (`$0314` / `$0315`): disables CIA1 timer IRQ, ACKs pending VIC IRQ, writes raster line to `$D012`, enables VIC raster IRQ (`$D01A=$01`), writes handler address, and re-enables interrupts.

The handler **must** end with `sys $EA81` (KERNAL end-of-IRQ) — plain `RTS` or `RTI` will corrupt the stack. ACK the VIC IRQ first:

```
sub my_handler()
  poke $D019, $FF      # ACK VIC IRQ
  # ... work here ...
  sys $EA81             # JMP to KERNAL end-of-IRQ
end
```

Forward references are supported (`irq my_handler` before the sub is defined).

NMI handler

```
nmi my_nmi              # set NMI vector $0318/$0319 to handler sub or address

sub my_nmi()
  # ... NMI work here ...
  nmi_exit              # JMP $FE47 - proper NMI exit (restores A/X/Y + RTI)
end
```

`nmi handler` writes the handler address to the NMI soft vector (`$0318 / $0319`). The hardware NMI vector at `$FFFA` points to the KERNAL NMI routine which branches through `$0318` . The handler **must** end with `nmi_exit` (emits `JMP $FE47`) — using plain `RTI` will corrupt the stack. Forward references supported.

CIA1 timer IRQ

```
cia_timer 19656, my_handler  # CIA1 timer A: fires every 19656 cycles (~50 Hz PAL)
cia_timer period, handler    # period can be a variable or expression
```

Sets up CIA1 timer A as a periodic IRQ source via the BASIC soft vector (`$0314 / $0315`):

1. SEI — disable interrupts
2. `$DC0D = $7F` — disable all CIA1 IRQs
3. Load 16-bit period lo→ `$DC04` , hi→ `$DC05`
4. Write handler address to `$0314 / $0315`
5. `$DC0D = $81` — enable CIA1 timer A IRQ
6. `$DC0E = $01` — start timer A in continuous mode
7. CLI — re-enable interrupts

The handler must end with `irq_exit` (or `sys $EA81`) and should ACK the CIA1 IRQ:

```

sub my_handler()
  poke $DC0D, $01      # ACK CIA1 timer A IRQ (read also clears it)
  # ... work here ...
  irq_exit             # JMP $EA81: restore A/X/Y + RTI
end

```

PAL timing: clock = 985 248 Hz. Period for 50 Hz = 985 248 / 50 = 19 705 cycles ≈ \$4CC9 . Forward references supported.

Error handling

```

onerr goto err_handler  # set KERNAL I/O error vector ($0300/$0301) to a label

...

label err_handler
  print "I/O ERROR"
  bye

```

`onerr goto label` writes the label address (lo, hi) to KERNAL locations \$0300 and \$0301 .

When a KERNAL I/O error occurs (e.g. a failed `load` or `open`) the KERNAL executes `JMP ($0300)` , which branches to the label. Forward references (label defined after `onerr goto`) are supported.

Compile-time file embedding (`incbin` skip / length new in 1.5.7)

```

incbin "sprites.bin"          # embed raw binary bytes at current code position
incbin "charset.bin", $2000   # embed at an absolute address, padding as needed
incbin "font.prg", $3C00, 2    # ...skipping the first 2 bytes (e.g. a .prg load address)
incbin "big.bin", $4000, 16, 256 # ...skip 16 bytes, then take at most 256 bytes
include "defs.ub"             # inline another .ub source file (lexed+parsed in place)

```

`incbin "file", addr, skip [, length]` drops the first `skip` bytes of the file (typically the 2 byte load address of a `.prg`) and optionally takes at most `length` bytes; `skip` and `length` are constants, and a `skip` beyond the end of the file is an error. The address form requires the target to be above the generated code — or inside an `org` gap.

Data / Read

```
data 1, 2, 3, 255      # constant byte table
read varname           # load next byte into varname (auto-declares if needed)
```

All `data` values are collected at compile time. A 2-byte ZP pointer is automatically allocated and initialised at program start. Each `read` advances the pointer.

Inline assembly

```
sys $FFD2              # JSR $FFD2
sys $FFD2, 7           # LDA #7 ; JSR $FFD2 (pass byte value in A register)
irq_exit               # JMP $EA81 - proper IRQ handler exit (restore A/X/Y + RTI)
asm $EA, $EA           # inline raw bytes (NOP NOP) - legacy form
asm {
    ; Full 6502 mnemonics and addressing modes
    LDA #$07           ; immediate
    STA $0286          ; absolute
    LDA $50            ; zero-page ($50 ≤ $FF → ZP auto-selected)
    STA $0400,X         ; absolute,X indexed
    LDA ($50),Y         ; (indirect),Y
    LDA ($50,X)         ; (indirect,X)
    JSR $FFD2          ; subroutine call
    JMP $C000           ; absolute jump
    JMP ($FFFC)        ; indirect jump

    CLC
    ADC #1
    SEC
    SBC #1

    TAX                ; implied / transfer
    ASL A              ; accumulator (also just: ASL)
    LSR A
    ROL
    ROR

    ; Branches - operand is an absolute address; offset is computed automatically
    BNE loop           ; forward or backward branch to local label
    BEQ done

loop:
    NOP
done:
    RTS

    ; #<label / #>label - lo / hi byte of a label address
    LDA #<handler
    STA $0314
```

```

LDA #>handler
STA $0315

; * - current assembly location
JMP *

; Raw hex bytes (backward-compatible with old asm { $xx ... } syntax)
$EA $EA          ; two NOP bytes
}

```

Addressing modes:

Syntax	Mode	Bytes	Example
(no operand)	Implied	1	NOP , RTS
A	Accumulator	1	ASL A , LSR
#value	Immediate	2	LDA #\$07
\$zz (0–255)	Zero-page	2	LDA \$50
\$zz,X	ZP,X	2	LDA \$50,X
\$zz,Y	ZP,Y	2	LDX \$50,Y
\$xxxx	Absolute	3	LDA \$0400
\$xxxx,X	Absolute,X	3	LDA \$0400,X
\$xxxx,Y	Absolute,Y	3	LDA \$0400,Y
(\$xxxx)	Indirect	3	JMP (\$FFFC)
(\$zz,X)	(Indirect,X)	2	LDA (\$50,X)
(\$zz),Y	(Indirect),Y	2	LDA (\$50),Y
label	Relative	2	BNE label (branches only)

- \$zz (1–2 hex digits, value ≤ 255) selects zero-page if the instruction supports it; otherwise auto-upgrades to absolute. Use \$00xx (4 digits) to force absolute.
- Branch operands are absolute addresses; the relative byte offset is computed automatically.
- Local labels (name:) are scoped to the asm { } block. Forward branches resolved in pass 2.
- #<label / #>label yield the lo / hi byte of a label's address.
- * yields the current instruction address, so JMP * assembles as a self-loop.
- Lines starting with \$, % , or a digit are emitted as raw bytes (backward-compatible).
- Inside asm { } , comments are ; or // to end of line. (# is the immediate prefix, not a comment.)

Mixing asm { } with subroutine parameters

Parameter names are **not accessible** inside asm { } blocks. Use UltimateBasic statements to move values into known locations before the asm { } block:

```
sub set_colors(border_col, bg_col)
  poke $D020, border_col  # UltimateBasic resolves the ZP address
  poke $D021, bg_col
  asm {
    ; values are already in $D020 / $D021
    LDA $D020
  }
end
```

For routines whose entire body is assembly — especially IRQ handlers that must cross-reference each other — put all handlers in a **single top-level `asm { }` block** in the main program. Labels in the same block share scope, so `irq1` and `irq2` can reference each other freely. See `examples/raster_irq_demo.ub`.

String ↔ integer

```
numstr score, $0340      # writes "042\0" at $0340 (always 3 digits, zero-padded)
var n = str_to_int("42") # compile-time: Expr::Number(42)

print str$(score)        # print 8-bit int as 3-digit decimal string ("000"-"255")
print "Score: " + str$(score) # usable in string concat print context
var s: string = str$(n)   # assign str$() result to a string var (shared static buffer)
```

`str$(n)` converts an 8-bit value to a 3-character decimal string (always 3 digits with leading zeros, e.g. `5` → `"005"`, `42` → `"042"`, `255` → `"255"`) followed by a null terminator. The result pointer is stored in a permanent ZP pair allocated at compile time.

Note: `str$(n)` uses a single shared 4-byte static buffer. Calling `str$(n)` again overwrites the previous result. For concurrent display of multiple values, use `numstr` to write to separate absolute addresses.

Examples

File	Description
<code>examples/features.ub</code>	const, label/goto, poke/peek, rnd, math functions
<code>examples/new_features.ub</code>	sub params, arrays, word vars, string vars
<code>examples/bitmap_demo.ub</code>	320×200 bitmap, plot, graphics on/off
<code>examples/block_demo.ub</code>	80×50 block graphics, plot4, circle4, graphics on block
<code>examples/joystick_demo.ub</code>	joystick reading, sprite movement

File	Description
examples/mux_demo.ub	raster sprite multiplexer (3 windows × 8 sprites = 24)
examples/orbit_demo.ub	24-sprite orbit with pulsating radius and random colors
examples/plasma_demo.ub	plasma-effect bitmap with raster bar border animation
examples/sprite_data.ub	sprdef shape data (included by other demos)
examples/sprite_mux_orbit.ub	24-sprite orbit demo with sprdef + precomputed positions
examples/sprite_orbit_demo.ub	8 hardware sprites in circular orbit via sin/cos table
examples/reu_bitmap_demo.ub	REU stash/fetch with bitmap graphics
examples/sid_music_demo.ub	SID music player with raster IRQ and keyboard exit
examples/tenprint.ub	5 TENPRINT maze implementations with menu; demos lowercase charset mode
examples/countdown_demo.ub	Count-down for..next with negative step, incl. for i = 20 to 0 step -2
examples/countdown_errors_demo.ub	Compile-time error for default-step from > to
examples/explicit_demo.ub	--explicit CLI-flag demo with fully typed var , sub , fn
examples/explicit_errors_demo.ub	Loose code that builds without --explicit , errors with it

CLI reference

```
ub build <input.ub> [OPTIONS]

-o, --output <file>  Output .prg or .crt file (default: <input>.prg)
-v, --verbose         Show zero-page layout and code hex dump
--no-stub            Skip the BASIC SYS stub (code loads at $0801)
--debug             Also produce .sym, .dbg and .vs debugger files
--asm               Also produce a readable 6502 codegen .asm listing
--d64 [file]         Also produce a .d64 disk image;
                     without a filename defaults to <output>.d64
--add <file>         Add an extra file to the .d64 disk image;
                     may be repeated for multiple files
--explicit           Require :type on every var / sub-param / fn-param
-h, --help          Show help
```

CRT export

Ultimate Basic can also write a Magic Desk type-19 cartridge image when the output filename ends in `.crt`:

```
ub build demo.ub -o demo.crt
```

The compiler wraps the generated PRG in a banked CRT container using the same layout as VisualAssembler's CRT export: a 64-byte cartridge header, an 8×8K Magic Desk image, and a boot loader in bank 0 that copies the PRG payload into C64 RAM before jumping to the program entry point. The `.prg` and `.d64` paths continue to work as before.

Explicit-type mode

Pass `--explicit` to force every declaration site to carry a `:type` annotation:

```
ub build game.ub --explicit
```

Without the flag, Ultimate Basic accepts both `var x = 5` (type inferred from the initializer or defaulted to `int`) and `var x: int = 5`. With the flag, only the annotated form compiles — the loose form becomes a compile-time error.

What it enforces:

Declaration form	Without <code>--explicit</code>	With <code>--explicit</code>
<code>var name = expr</code> (no <code>:type</code>)	ok — type inferred	error
<code>var name: int = expr</code> (or word/float/string)	ok	ok
<code>var arr = array(N)</code>	ok — implicitly <code>array</code>	ok — unchanged
<code>var arr = array_word(N)</code>	ok — implicitly <code>array_word</code>	ok — unchanged
<code>const NAME = value</code>	ok	ok — unchanged
<code>sub foo(a, b)</code> (untyped params)	ok	error per untyped param
<code>sub foo(a: int, b: int)</code>	ok	ok
<code>fn foo(a): int</code> (untyped param)	ok	error on the param
<code>fn foo(a: int): int</code>	ok	ok

Constants and array declarations are always accepted — their type is fixed by the declaration form, so `:type` would be redundant.

Example error output:

```
$ ub build myprog.ub --explicit
Compilation errors:
```

```
line 14: 'explicit' mode: 'var loose' has no type — use 'var loose: int|word|float|string'
line 16: 'explicit' mode: parameter 'a' has no type — use 'a: int|word|float|string'
```

The flag is a build-time switch — nothing in the source needs to change to opt in or out. Add it to your Makefile / build script to enforce typed style project-wide, or drop it for exploratory scripts. See `examples/explicit_demo.ub` and `examples/explicit_errors_demo.ub`.

Debug files

Use `--debug` to generate debugger symbols together with the program:

```
ub build demo.ub --debug
```

The compiler writes the files next to the `.prg`, using the output file's stem:

File	Format and purpose
<code>demo.sym</code>	KickAssembler-compatible symbol source, suitable for importing into assembler source
<code>demo.dbg</code>	C64Debugger/RetroDebugger KickAssembler debug-dump containing the program segment and labels
<code>demo.vs</code>	VICE monitor command file containing <code>al</code> commands for address labels

All three exports include `program_start`, `program_end`, variables, arrays, subroutines, and BASIC labels known after code generation. For example, load the VICE symbols with its `-moncommands demo.vs` command-line option or the monitor's `ll "demo.vs"` command.

The current `.dbg` export provides segment and address-symbol information. It does not yet include instruction-to-source-line mappings for source-level stepping.

Assembly codegen listing (new in 1.5.2)

Use `--asm` to write a readable 6502 source listing next to the PRG:

```
ub build demo.ub --asm
```

For an output named `demo.prg`, this creates `demo.asm`. The listing is produced from metadata collected while Ultimate Basic generates the machine code; it is not merely a disassembly of the completed PRG. It contains:

- `; UB:` comments marking the generated byte range of each emitting UB statement;
- named constants for zero-page variables and `$C000+` arrays, including their types/sizes;

- final names and addresses for subroutines and BASIC labels;
- generated `loc_XXXX` labels for relative branches and in-program `JMP / JSR` targets;
- normal 6502 mnemonics and operands, with compiler symbols substituted where known;
- the exact C64 address and emitted bytes beside every instruction;
- compiler-generated helpers and embedded code in their final memory order;
- `.byte` output for bytes that do not decode as supported 6502 instructions.

Compiler helpers receive descriptive names such as `ub_helper_plot`, `ub_helper_line_erase`, `ub_helper_print_hex`, and `ub_helper_music_irq`. Known embedded data—including `data` statements, map character/color arrays, sprite and character definitions, the sine table, load filenames, `incbin` files, SID music, and Koala payloads—is emitted as named `.byte` regions. Long zero-filled address gaps use KickAssembler's `.fill` directive.

Example excerpt:

```
.label x                = $02 ; int

* = $080D

ub_start:
    cld                    ; $080D: D8
    ; UB: var x
    lda #$01               ; $080E: A9 01
    sta x                  ; $0810: 85 02
```

The address/byte comments make the listing easy to compare with the `.prg`. The output uses KickAssembler syntax (`.label`, `.byte`, `.fill`, and `* = origin`) so it can be assembled again; machine-code comments do not affect the result.

`--add` requires `--d64`. The compiled `.ub` program is always the first file on the disk; each `--add` file is appended after it. File names on the disk are derived from the source file stem, uppercased (e.g. `music.prg` → `MUSIC`).

After a successful build the compiler always prints a memory map:

```
demo.ub → demo.prg (386 bytes)

Load:    $080D - $0989

Variables (zero page):
    score    ZP:$08    byte
    lives    ZP:$0A    byte
    msg      ZP:$0C    string
    ptr      ZP:$0E    word

Subroutines:
```

```
greet    $0900
show     $0912

Arrays ($C000+):
sprites  $C000    8 bytes
```

With `-v` the output additionally shows the internal ZP allocations and a full hex dump.

Known limitations

Feature	Limitation
Integer arithmetic	8-bit unsigned (0–255); <code>word</code> vars hold 16-bit values
Zero page budget	Permanent zero page is <code>\$02–\$4F</code> (78 bytes): every variable and sub/fn parameter takes 2 bytes, every running <code>for</code> loop 2 more (given back when the loop ends, if its body declared no variables). Running out is a compile-time error (<code>out of zero page</code> , new in 1.5.7); before, it silently overwrote the scratch area. Reuse variables in big programs
Binary literals	Only <code>\$hex</code> and decimal; <code>%</code> binary literals are not supported
Subroutines	No recursion — ZP parameter slots are statically allocated
String vars	Read-only after init; assignment replaces the pointer, not the data
String concat runtime	<code>s1 + s2</code> prints sequentially — no heap allocation or length tracking
<code>rnd()</code> / <code>rnd(n)</code>	Simple LCG, not cryptographic; period = 256
<code>abs()</code> / <code>sgn()</code> / <code>min()</code> / <code>max()</code>	8-bit values only; <code>abs</code> / <code>sgn</code> treat values as signed (bit 7 = negative → <code>abs</code> two's-complements, <code>sgn</code> returns <code>\$FF</code>); <code>min</code> / <code>max</code> are unsigned (0–255)
<code>plot</code>	Out-of-range pixels are silently clipped ($Y \geq 200$ or $X \geq 320 \rightarrow$ no-op)
<code>mplot</code>	No bounds checking — x must be 0–159, y must be 0–199
<code>mline</code> / <code>mrect</code>	Multicolor; x: 0–159, y: 0–199. Off-screen pixels wrap (no clipping) — keep coordinates in range
<code>mcircle</code>	Multicolor; clips off-screen points ($x \geq 160$ or $y \geq 200$ are skipped)
<code>color pen</code>	Hires only; sets the foreground nibble of touched cells (background preserved). Has no effect in block mode (<code>plot4</code> / <code>circle4</code>)
<code>rect</code>	No bounds checking — x: 0–319, y: 0–199; $x1 \leq x2$ and $y1 \leq y2$ not enforced (degenerate/inverted rects produce undefined output)
<code>plot4</code>	No bounds checking — x must be 0–79, y must be 0–49 (block mode)
<code>circle4</code>	Clips off-screen block pixels; useful radius is roughly 0–49 in 80×50 block mode
<code>chr\$</code>	No PETSCII↔ASCII mapping — n is passed as-is to CHROUT
<code>music play</code>	Requires <code>load sid</code> ; only one CIA1 wrapper is emitted (last <code>music play</code> wins)

Feature	Limitation
<code>graphics on</code> <code>double</code>	Hires only; uses <code>\$4000-\$7FFF</code> for the back buffer, so program code must stay below <code>\$4400</code> ; not combinable with sprites or multicolor
Error reporting	Compile-time only; <code>onerr goto</code> handles KERNAL I/O errors at runtime