

ZYVORAI LABS · CUSTOMER DOCUMENTATION

relay-edge

Getting Started

2026-08-29

Full stack order: [Relay stack day-0 onboarding](#).

1. Open `https://<edge-host>:18086/ui/` (accept self-signed TLS).
2. Complete the **Get started** panel: Health → Auth (if required) → Wire publish → Probe → Lab.
3. In **Configure**, set `gateway_base_url` to your **pubsub host** (or clear it and set `relay_base_url` for direct).
Paste JWT. Enable TLS insecure for lab certs. **Save**, then **Probe**.
4. Run Lab **Store → Send → Receive**.

Do **not** put laptop `127.0.0.1` in peer URLs when Relay or pubsub run on another machine.

Area	Purpose
Configure	Runtime gateway/Relay URLs, JWT, browser API token
Self-test lab	Health, Store, Send, Receive, simulator shortcuts
Logs	Admin ring buffer
Fire-water / Remote edge / Fleet	Simulator control rooms
Docs	In-app stack docs + first-time setup link

1. **Store → Send → Receive** — Lab creates domain rows, publishes stamped `crop.advisory` , shows path.
2. **Simulator** — Seed → Publish into Relay → scenario → SSE stream.
3. **Full stack e2e** — From a workstation with remote URLs:

```
set -a && source config/lab-stack.env && set -a
/scrips/e2e-stack.sh
```