

%运行前, 确保“LPfilter.m”和“Npulse.m”文件被存放在同一目录中

```
clear all
```

```
%生成Nyquist pulse
```

```
T_s = 25e-12;  
beta = 0.5;  
samp_freq = 10e12;  
T = 1/samp_freq;  
t = (-20000:20000)*T;  
[t,h] = Npulse(t,T_s,beta);
```

```
%生成pulses train
```

```
repeat_freq = 1e10;  
    impulse_func = zeros(samp_freq/repeat_freq,1);  
    impulse_func(1) = 1;  
repeat_times = 100;  
    conv_train = [];  
    for count=1:repeat_times-1  
        conv_train = [conv_train;impulse_func];  
    end  
    conv_train(end+1) = 1;  
h_train = conv(conv_train,h, 'same');
```

```
%ideal MZM
```

```
V_pi = 2;           %amplitude of N pulse set 1  
h_train_bias = h_train + V_pi;  
MZM_train = 1/2 + 1/2*cos(h_train_bias/V_pi*pi);    %transfer function  
MZM_train_short = MZM_train(1:90e3);    %尾部信号不整齐, 截取掉, 以防影响差分序列的第一个值  
dif_MZM = MZM_train_short - circshift(MZM_train_short,1);
```

```
    plot(MZM_train_short)  
    hold on
```

```
%filter parameter
```

```
num_tap=11;  
tap_inter = 100;  
%filter initialization  
weights=zeros(1,num_tap);  
weights(1)=1
```

```
%training iteration
```

```
for count=1:10000  
%initialize  
EQL_train_buffer=zeros(1,num_tap);  
h_train_buffer=zeros(1,num_tap);  
%pre-compensate  
for bit=1:length(h_train)-tap_inter*(num_tap-1)  
    h_train_buffer=transpose(h_train(bit:tap_inter:bit+(num_tap-1)*tap_inter));  
    h_train_prec(bit)= weights * transpose(h_train_buffer);  
end
```

```
%data channel
```

```
hLP_train = filter(LPfilter,h_train_prec);  
[align,lags] = xcorr(hLP_train,h_train);  
shift=find(align==max(align))-find(lags==0);
```

```
hLP_train_align = hLP_train(shift+2001:end);
%actual MZM
V_pi = 2;           %amplitude of N pulse set 1
hLP_train_bias = hLP_train_align + V_pi-0.1;
LP_MZM_train = 1/2 + 1/2*cos(hLP_train_bias/V_pi*pi);    %transfer function
LP_MZM_short = LP_MZM_train(1:90e3);
dif_LP_MZM = LP_MZM_short - circshift(LP_MZM_short,1);    %差分序列
%display
    plot(LP_MZM_short)
%input selection
eql_train = dif_LP_MZM;
comp_train = dif_MZM;
%adaptive algorithm
for bit=1:length(eql_train)-tap_inter*(num_tap-1)
    EQL_train_buffer=eql_train(bit:tap_inter:bit+(num_tap-1)*tap_inter);
    pointer = EQL_train_buffer(1);
    error(bit)= comp_train(bit) - pointer;
    mu=(MZM_train_short(bit)-LP_MZM_short(bit));    %23为放大系数, 经验值, 过小影响收敛速度, 过大程序会直接炸
    weights=weights + 2 * mu * error(bit) * EQL_train_buffer;
end
%progress monitor
weights
count
end
```