

Example	Format	Type	Opcode (dec)	Funct (dec)
add \$t0, \$t1, \$t2	rd, rs, rt	R	0	32
sub \$t0, \$t1, \$t2	rd, rs, rt	R	0	34
and \$t0, \$t1, \$t2	rd, rs, rt	R	0	36
or \$t0, \$t1, \$t2	rd, rs, rt	R	0	37
nor \$t0, \$t1, \$t2	rd, rs, rt	R	0	39
sll \$t0, \$t1, 2	rd, rt, shamt	R	0	0
srl \$t0, \$t1, 2	rd, rt, shamt	R	0	2
slt \$t0, \$t1, \$t2	rd, rs, rt	R	0	42
jr \$ra	rs	R	0	8
addi \$t0, \$t1, 10	rt, rs, imm	I	8	—
beq \$t1, \$t2, label	rs, rt, offset	I	4	—
bne \$t1, \$t2, label	rs, rt, offset	I	5	—
lw \$t0, 4(\$t1)	rt, offset(rs)	I	35	—

sw \$t0, 4(\$t1)	rt, offset(rs)	I	43	—
andi \$t0, \$t1, 15	rt, rs, imm	I	12	—
ori \$t0, \$t1, 15	rt, rs, imm	I	13	—
j label	target	J	2	—
jal label	target	J	3	—