

SR Characteristics Equation:

Q_n	S	R	Q_{n+1}
0	0	0	0
0	0	1	0
0	1	0	1
0	1	1	X
1	0	0	1
1	0	1	0
1	1	0	1
1	1	1	X

K-map

	$R'Q_n'$	$R'Q_n$	RQ_n	RQ_n'
S'	0	0	x	1
S	1	0	x	1

$$Q_{n+1} = S + Q_n R'$$

JK Characteristics Equation:

Q_n	J	K	Q_{n+1}
0	0	0	0
0	0	1	0
0	1	0	1
0	1	1	1
1	0	0	1
1	0	1	0
1	1	0	1
1	1	1	0

K-map

	$J'K'$	$J'K$	JK	JK'
Q'	0	0	1	1
Q	1	0	0	1

$$Q_{n+1} = JQ' + K'Q$$

D Characteristics Equation:

Q_n	D	Q_{n+1}
0	0	0
0	1	1
1	0	0
1	1	1

K-map

	D'	D
Q'	0	1
Q	0	1

$$Q_{n+1} = D$$

T Characteristics Equation:

Q_n	D	Q_{n+1}
0	0	0
0	1	1
1	0	1
1	1	0

K-map

	T'	T
Q'	0	1
Q	1	0

$$Q_{n+1} = TQ' + T'Q$$

$$= T \oplus Q$$