EASYJTAG PLUS & UFI BOX ISP 1-BIT SOLDERING REFERENCE

In-System Programming Connection & Signal Integrity | Sheet 1 of 1

ISP 6-WIRE CONNECTION GUIDE

Connecting Motherboard Directly to Flasher Box

CMD (Command Line): Connect to 100-Ohm series resistor near eMMC | Length < 8cm

CLK (Clock Line): High frequency line (up to 24MHz) | Must be shortest wire (< 6cm)

DAT0 (Data Line 0): 1-bit bidirectional data line | Diode reading: 650mV

VCC (NAND Core): 2.8V - 3.3V external supply from box or USB charger

VCCQ (I/O Buffer): 1.8V logic supply | Never exceed 1.95V on modern eMMC

GND (Ground): Solder with thick wire (0.2mm) to broad PCB shield ground

CONFIDENTIAL - SALEN MOBILE GURU CHIP-LEVEL HARDWARE LAB