

The Clock [3600,60,1]: Designed Not to Be Diophantine

A Didactic Comparison and Structural Analysis

Bilal El Issaoui, Amsterdam, 2026

Abstract

This paper presents a systematic comparison between two number system architectures: the (25,12)-system, an engineered Diophantine representation system, and the clock [3600,60,1], the canonical sexagesimal positional system. While both employ modular arithmetic, they do so with fundamentally different purposes, mechanisms, and structural consequences. The (25,12)-system is designed to satisfy the D^3 conditions (Foundation + Chain), enabling multiple representations, ladder structures, and optimal representation counting. The clock is designed for universal uniqueness: one and only one (H,M,S)-triple per time value T. We demonstrate that the clock's coefficients (3600, 60, 1) are not a "failed" attempt at Diophantine structure, but rather the correct design for a positional system where carry/overflow, not modular congruence, governs transitions. The 12-hour cycle metaphor shares the modular principle with the (25,12)-system; the structural system [3600,60,1] does not. This distinction is essential for understanding why engineered Diophantine systems and canonical positional systems are structurally incomparable.

§1 Purpose: Designed Optimization versus Universal Uniqueness

Why read this: before going into the mathematics, it matters to know that both systems serve a different purpose. Without that distinction, the difference in structure would seem arbitrary.

Property	(25,12)-system (19,9,3,3,1 / 25,12)	Clock [3600,60,1]
Origin	Engineered: coefficients chosen <i>so that</i> Foundation and Chain hold	Pre-existing, ancient (Babylonian sexagesimal)
Purpose	Minimal/optimal representation counting and generation	One unique time indication per moment
Degree of freedom	Multiple (A,B)-pairs possible per N	Exactly one (H,M,S)-triple per T
System type	Diophantine representation system	Canonical positional system
Number of representations	Variable: $R(N) \geq 0$; some N have multiple	Exactly one for every T within domain
Frobenius boundary	263 (largest non-representable number)	None; every T is representable
Ladder structure	Yes: $A = A_0 + 12k$, $B = B_0 - 25k$	No; no multiple solutions

Core message: The coefficients of the (25,12)-system are chosen *so that* Foundation and Chain hold. That is a **design choice** aimed at counting/generating representations. The clock is not designed for that purpose. It is designed for unique, error-free time registration. **Different purposes $\Rightarrow$ different structural requirements.**

§2 The Mod Operation: Global-Single versus Local-Cascading

Why read this: this is the technical core of the entire paper. The difference between "one global mod step" and "a chain of local mod steps" explains almost everything that follows.

Both systems use $N \bmod q$, but **not in the same way**.

§2.1 (25,12)-system: One Global Operation

Foundation ($c_1 \equiv 1 \bmod c_2$):
 $A_0 = N \bmod c_2$

This is **one global operation** on the original number N . Because $c_1 \equiv 1 \pmod{c_2}$, B vanishes completely from the equation modulo c_2 :

$$N = c_1 \cdot A + c_2 \cdot B \equiv 1 \cdot A + 0 \cdot B \equiv A \pmod{c_2}$$

Therefore A_0 is **determined in one step**, directly from N itself. It does not matter how large N is: the mod operation immediately yields the smallest coefficient.

Fact 2.1 (Direct Determinability): For every $N \geq (c_1-1)(c_2-1)$, $A_0 = N \bmod c_2$ is the smallest non-negative coefficient for which $N = c_1 \cdot A + c_2 \cdot B$ has a non-negative solution.

§2.2 Clock: A Chain of Local Moduli

Clock decomposition:
 $S = T \bmod 60$ (mod on the units layer)
 $M = \lfloor (T \bmod 3600) / 60 \rfloor$ (division *after* a mod)
 $H = \lfloor T / 3600 \rfloor \bmod 24$ (composition of division and mod)

Here there is **no global q** . Each layer has its own modulus (60, 60, 24), and the mod step always operates on the **remainder from the previous layer**. Not directly on T .

This is what is meant by "**cascade modularity**": a chain of mod/div pairs, **no single congruence** that decomposes the entire number in one blow.

§2.3 The Concrete Difference in One Sentence

	(25,12)-system	Clock
Scope of mod	Global: $A_0 = N \bmod c_2$ for <i>every</i> N , a property of the entire number	Local: $S = T \bmod 60$ only for the seconds layer ; says nothing about H or M without first dividing away higher layers
Analogue of A_0 ?	Yes: A_0 captures in one step the full structure of N (modulo c_2)	No: there is no single number that captures in one step the full (H,M,S) -structure of T
Mod as	Structural decomposer : determines the entire system	Isolation mechanism : separates one layer from the rest

§3 Why Foundation Does Not Hold for the Clock, and Need Not Hold

Why read this: this directly refutes the idea that the clock is a "failed" Diophantine system. Not having Foundation is a feature here, not a shortcoming.

Foundation requires $c_1 \equiv 1 \pmod{c_2}$.
For the clock: $3600 \bmod 60 = 0$, **not 1**.
This is **not a design flaw**. It is precisely what you need for a pure positional system.

A positional system with radix g works precisely because every power of g is **divisible by the previous one**:

$$60^2 = 3600 \text{ is divisible by } 60$$

$$60^1 = 60 \text{ is divisible by } 60^0 = 1$$

This guarantees that there is **no overlap or ambiguity** between positions. That is the **opposite purpose** of Foundation, which is designed to **explicitly structure multiple representations** (the ladder $A_0, A_0+12, A_0+24, \dots$).

Fact 3.1 (Conflicting Purposes):

- Foundation ($c_1 \equiv 1 \pmod{c_2} \Rightarrow$ multiple representations possible (ladder)
- Positional system (g^k divisible by $g^{k-1} \Rightarrow$ exactly one representation)

These two properties are **mathematically incompatible** in one system. The clock consciously chooses the latter.

§4 The $13 \equiv 1 \pmod{12}$ Connection: Metaphor versus Structure

Why read this: this prevents a common mistake, namely thinking that the 12-hour clock metaphor is the same as the clock structure [3600,60,1]. It is not.

The clock **as metaphor** (the 12-hour dial) illustrates cyclic reduction:

$$13 \equiv 1 \pmod{12} \Rightarrow 13:00 = 1:00 \text{ (PM)}$$

This is the same **modular thought** as $25 \equiv 1 \pmod{12}$ in the (25,12)-system. But:

	Clock metaphor (12-hour cycle)	Clock structure [3600,60,1]	(25,12)-system
Principle	$13 \equiv 1 \pmod{12}$	$60 \equiv 0 \pmod{12}, 3600 \equiv 0 \pmod{12}$	$25 \equiv 1 \pmod{12}$
Modular contribution	Only hours count modulo 12	Only seconds count modulo 12 ($S = T \pmod{12}$)	Coefficient A carries all modular information ($N \equiv A \pmod{12}$)
Representation	Multiple hours for same "mod 12" class	Exactly one (H,M,S) per T	Multiple (A,B)-pairs per N

Important distinction: The metaphor ($13 \equiv 1 \pmod{12}$) **shares** the modular principle with the (25,12)-system. The structure [3600,60,1] **does not**. The shared element is "mod as isolation mechanism", not " $N \pmod{q}$ as global, ladder-generating congruence."

§5 Comparison of the "Engine"

Why read this: here you see concretely why the (25,12)-system answers in a single step, while the clock deliberately cannot and does not want to.

§5.1 The "Engine" of the (25,12)-system

The (25,12)-system rests on the **non-trivial congruence** $c_1 \equiv 1 \pmod{c_2}$. This property makes c_1 the "engine" of the system:

$$N = 25A + 12B \Rightarrow N \equiv A \pmod{12}$$

Since $12B \equiv 0 \pmod{12}$ and $25 \equiv 1 \pmod{12}$, B vanishes completely from the equation modulo 12. The smallest coefficient $A_0 = N \pmod{12}$ is therefore **directly determined in one step**.

Theorem 5.1 (Direct Determinability of A_0):

For all $N \geq 264$: the smallest non-negative A for which $N = 25A + 12B$ has a non-negative solution is $A_0 = N \pmod{12}$. (This follows from Fact 2.1 with $c_1=25, c_2=12$: (c_1-1))

$(c_2-1) = 24 \cdot 11 = 264$, exactly one more than the Frobenius boundary 263.)

§5.2 The "Engine" of the Clock

The clock has **no modular engine** in its coefficients. Transitions between positions proceed via **carry/overflow**:

- **Seconds:** $S = T \bmod 60$; when $S \geq 60$, carry propagates to minutes
- **Minutes:** $M = \lfloor T/60 \rfloor \bmod 60$; when $M \geq 60$, carry propagates to hours
- **Hours:** $H = \lfloor T/3600 \rfloor \bmod 24$; when $H \geq 24$, carry propagates to days

Fact 5.2 (Cascade Modularity): The clock uses a **cascaded modular system** where each position has its own modulus (60, 60, 24), in contrast to the (25,12)-system which uses a **single modulus** (12) for the entire structure.

§6 Formula Summary

§6.1 Clock System (Canonical Positional)

Definition 6.1 (Clock Representation):

For every $T \in \mathbb{N}_0$, the **unique** solution:

$$\begin{aligned} T &= 3600 \cdot H + 60 \cdot M + S \\ H &= \lfloor T/3600 \rfloor \bmod 24, \quad M = \lfloor (T \bmod 3600)/60 \rfloor, \quad S = T \bmod 60 \end{aligned}$$

with $0 \leq H < 24$, $0 \leq M < 60$, $0 \leq S < 60$.

§6.2 (25,12)-system (Diophantine)

Definition 6.2 ((25,12)-Representation):

For $N \in \mathbb{N}$, with smallest coefficient:

$$\begin{aligned} N &= 25 \cdot A + 12 \cdot B, \quad A, B \geq 0 \\ A_0 &= N \bmod 12 \\ R(N) &= \lfloor (\lfloor N/25 \rfloor - A_0)/12 \rfloor + 1 \quad (\text{if } \lfloor N/25 \rfloor \geq A_0; \text{ else } R(N) = 0) \end{aligned}$$

And the complete ladder: $A_k = A_0 + 12k$, $B_k = (N - 25 \cdot A_k)/12$ for $k = 0, 1, \dots, k_{\max}$.

§7 Structure Comparison Table

Property	(25,12)-system	Clock [3600,60,1]
System type	Diophantine representation system	Canonical positional system
Structural condition	$p \equiv 1 \pmod{q}$, i.e. $25 \equiv 1 \pmod{12}$	$g^k, g^{k-1}, \dots, g$, i.e. $60^2, 60^1, 60^0$
Ratio of successive coefficients	$25/12 \approx 2.083$ (non-integer)	60 (constant, integer)
Number of representations per N	Variable: $R(N) \geq 0$; some N have multiple	Exactly one for every T within domain
Modular property	$N \equiv A \pmod{12}$; coefficient A is directly determined	$T \equiv S \pmod{60}$; only lowest position counts
Frobenius boundary	263 (largest non-representable number)	None; every T is representable
Ladder structure	Yes: $A = A_0 + 12k$, $B = B_0 - 25k$	No; no multiple solutions
Cyclic group structure	$\mathbb{Z}/12\mathbb{Z}$ via residue $r = N \bmod 12$	$\mathbb{Z}/60\mathbb{Z}$ (minutes/seconds), $\mathbb{Z}/24\mathbb{Z}$

		(hours)
Historical analogue	Digital root (base 9)	Sexagesimal system (Babylonian mathematics)
Mod operation	Global-single: $A_0 = N \bmod 12$	Local-cascading: $S = T \bmod 60$, then M, then H
Purpose of design	Optimization of representation counting/generation	Unique, error-free time registration

§8 Common Ground and Fundamental Differences

§8.1 What They Share

- Both are based on a **fixed coefficient set** that decomposes N/T into sub-layers.
- Both use **modular arithmetic** as an isolation mechanism for one layer.
- Both can be illustrated with the **cyclic-reduction metaphor** ($13 \equiv 1 \bmod 12$ for the 12-hour dial), but that is a property of the **metaphor**, not of the structure [3600,60,1] itself.

§8.2 Where They Fundamentally Differ

(25,12)-architecture	Clock architecture
Designed to realize the D³ conditions (Foundation + Chain) for optimal representation counting	Exposes a universal, pre-existing positional structure serving a different purpose (uniqueness)
Coefficients are design variables , chosen to guarantee desired properties	Coefficients are given , fixed by historical convention (Babylonian sexagesimal)
Multiple representations are desired and structured (ladder)	Multiple representations are undesired and excluded (carry/overflow)
Mod is global and structural : determines the entire system	Mod is local and functional : isolates one layer

§9 Literature Comparison: Known versus New

Why read this: this section separates what already existed in the mathematical literature from what this work adds.

Already known: the Frobenius problem (largest non-representable number), counting multiple representations, positional systems (sexagesimal, decimal, binary), and the digital root as a residue mod 9.

New in this work: the Foundation condition ($c_1 \equiv 1 \bmod c_2$) not as a description after the fact but as a design principle beforehand; the ladder structure as a method to generate all representations (not just count them); the Diophantine representation system as a deliberate alternative to positional systems; and the generalization of the digital-root principle to any (p, q) pair with $p \equiv 1 \bmod q$.

In short: the existing literature describes what happens for given coefficients. This work inverts the question: choose coefficients so that desired properties are guaranteed to arise.

Aspect	Known in literature	New in D ³ / A-C Coupling
Frobenius problem	Classical: largest non-representable number $g(a_1, \dots, a_k)$ for coefficients with $\gcd=1$ (Sylvester 1884; Ramírez Alfonsín 2005)	Foundation condition ($c_1 \equiv 1 \bmod c_2$) as a design principle , not descriptive, but prescriptive
Multiple representations	$g_j(a_1, \dots, a_n)$: largest number with exactly j representations (Beck, Gessel &	Ladder structure $A_k = A_0 + k \cdot c_2$ as a deterministic generator method , not

	Komatsu 2001)	just counting, but producing all representations
Positional systems	Sexagesimal, decimal, binary: unique representation via carry/overflow	Diophantine representation system as a deliberate alternative to positional systems
Modular arithmetic	$N \equiv A \pmod{q}$ as a residue class property	Global mod operation $A_0 = N \bmod c_2$ as a structure-determining axiom
Canonical number systems	Studied in algebraic number theory (Kovács & Pethő 1991; Scheicher & Thuswaldner 2002)	D^3 conditions as design criteria for optimal denomination systems, explicit coupling to currency design (Euro, Dollar)
Digital root	$10 \equiv 1 \pmod{9} \Rightarrow \text{digital sum} = N \bmod 9$	$19 \equiv 1 \pmod{9}$, $25 \equiv 1 \pmod{12}$ as a generalized principle : every (p,q) with $p \equiv 1 \pmod{q}$ generates a "digital root"-like structure

Core distinction: The literature describes *what happens* with given coefficients (Frobenius number, number of representations). This work inverts the question: *choose* coefficients so that desired properties (Foundation, Chain, ladder) are guaranteed to arise. It is **design mathematics** rather than **analytical mathematics**.

§10 Conclusion

Theorem 10.1 (Structural Incomparability):

The clock $[3600,60,1]$ and the $(25,12)$ -system are **structurally incomparable** as Diophantine representation systems. The clock is canonical (unique representation); the $(25,12)$ -system is non-canonical (multiple representations). The clock as metaphor (the 12-hour cycle) is comparable with the modular principle of the $(25,12)$ -system; the clock as structure is not.

Formulated Analogy:

"The clock illustrates the principle of cyclic reduction ($13 \equiv 1 \pmod{12}$), which in the $(25,12)$ -system is algebraically realized by $25 \equiv 1 \pmod{12}$. The clock $[3600,60,1]$ itself is a canonical positional system that does **not** share this principle, but the underlying 12-hour cycle forms the **intuitive basis** for the modular structure."

Summary in three points:

1. **Purpose differs:** $(25,12)$ -system = designed for optimization; Clock = universal uniqueness.
2. **Mod works differently:** $(25,12)$ -system = global-single ($A_0 = N \bmod c_2$); Clock = local-cascading (S, then M, then H).
3. **Foundation is not a flaw:** $3600 \equiv 0 \pmod{60}$ is **precisely correct** for a positional system; it is the **opposite** of what Foundation aims to achieve.