

fN=50

fN =
50

$\omega_N = 2\pi \cdot f_N$

$\omega_N =$
314.1593

$u_r = 0.002$ % ohmic part of the short circuit reactance

$u_r =$
0.0020

$u_x = 0.2$ % inductive part of the short circuit reactance

$u_x =$
0.2000

$i_0 = 0.002$ % relative no load current

$i_0 =$
0.0020

$p_0 = 0.0004$ % relative power loss

$p_0 =$
4.0000e-04

$S_{1N} = 40 \times 10^6 / 3$ % apparent absolut power per phase

$S_{1N} =$
1.3333e+07

$U_{1N} = 110000 / 1.73205$ % nominal primary voltage

$U_{1N} =$
6.3509e+04
 $U_{20} =$
10600

$I_{1N} = S_{1N} / U_{1N}$ % nominal primary current

$I_{1N} =$
209.9455

$Z_{1N} = U_{1N} / I_{1N}$ % nominal impedance

$Z_{1N} =$
302.5003

$R_1 = Z_{1N} \cdot u_r / 2$ % absolut copper resistance of primary side

$R_1 =$
0.3025

$L_{1s} = Z_{1N} \cdot u_x / 2 / \omega_N$ % absolut leakage inductance of primary side

$L_{1s} =$
0.0963

$X_{1s} = L_{1s} \cdot \omega_N$ % absolut leakage reactance of primary side

$X_{1s} =$
30.2500