

Wiring Connections

Microcontroller (Seeed Studio XIAO ESP32C6)

GPIO	Connected To
GPIO0	Pushbutton 1 - Pin 1
GPIO1	Pushbutton 2 - Pin 1
GPIO2	Pushbutton 3 - Pin 4
GPIO16	TRRS Jack - Tip
GPIO17	SD Card Module - MOSI
GPIO18	SD Card Module - CS
GPIO19	SD Card Module - SCK
GPIO20	SD Card Module - MISO
GPIO21	OLED Display - SCL
GPIO22	OLED Display - SDA
GPIO23	Resistor - pin2
GND	SD Module, OLED, Pushbuttons (Pin 2), TRRS Sleeve, Capacitor pin1
3V3	SD Card Module - VCC, OLED Display - VDD

♦ SD Card Module (SPI)

Pin	Connected To
MOSI	XIAO GPIO17
MISO	XIAO GPIO20
SCK	XIAO GPIO19
CS	XIAO GPIO18

VCC	XIAO 3V3
GND	XIAO GND

◆ 0.96" OLED Display (I2C)

Pin	Connected To
SDA	XIAO GPIO22
SCL	XIAO GPIO21
VDD	XIAO 3V3
GND	XIAO GND

◆ Pushbuttons ×3

Button	Pin 1	Pin 2
1	GPIO0	GND
2	GPIO1	GND
3	GPIO2	GND

◆ TRRS 3.5mm Jack Breakout

Pin	Connected To
Tip	XIAO GPIO16
Ring1	Resistor pin1, Capacitor pin0
Sleeve	XIAO GND
Ring2	(Unused)

◆ Resistor (1kΩ)

Pin	Connected To
pin1	TRRS Ring1

pin2 XIAO GPIO23

◆ Ceramic Capacitor (0.1 μ F)

Pin	Connected To
-----	--------------

pin0	TRRS Ring1
------	------------

pin1	XIAO GND
------	----------