

Linear Combination of Non-Unitaries

Theory, Computation and Applications

Session 2: Generalized constructions and Burgers' equation

Thomas Hogancamp Reuben Demirdjian

U.S. Naval Research Laboratory

Abeynaya Gnanasekaran (IonQ)

Amit Surana (RTX Technology Research Center)

September 18, 2026

Structured matrix loading

An LCNU represents a matrix using terms that need not be unitary:

$$A = \sum_{\ell=1}^K c_{\ell} L_{\ell}.$$

- A direct Pauli expansion can require many terms.
- Sparse, structured matrices often admit shorter descriptions using special matrix classes (e.g. projectors and permutations arise in Finite Difference applications).
- Each term still needs an efficiently implementable unitary embedding.

Goal: Extend the LCNU construction of Session 1 (Kronecker products of simple projectors) to more general products of structured factors.

Notation and register order

$$\mathbb{P} = \{I, X, Y, Z\}, \quad \mathbb{S} = \{I, \rho_0, \rho_1, \rho_2, \rho_3\}.$$

Rho notation	Outer product	Sigma notation	Completion
ρ_0	$ 0\rangle\langle 0 $	$\sigma_+\sigma_-$	I
ρ_1	$ 0\rangle\langle 1 $	σ_+	X
ρ_2	$ 1\rangle\langle 0 $	σ_-	X
ρ_3	$ 1\rangle\langle 1 $	$\sigma_-\sigma_+$	I

The “sigma basis” was used in Session 1. We adopt ρ notation for more compact expressions.

Unitary completions and complements

Definition (Unitary Completion/Complement)

Suppose that $V \subset \mathbb{C}^N$ and $Q : V \rightarrow V$ is a linear operator such that $Q : W \rightarrow V$ is a unitary transformation into its image, where $W := \ker(Q)^\perp$. Then, a unitary operator $\overline{Q} : V \rightarrow V$ is said to be a unitary completion of Q if $\overline{Q}(w) = Q(w)$ for all $w \in W$. The unitary complement of Q is defined by $Q^\perp := \overline{Q} - Q$.

Comment. Such a Q is sometimes called a **partial isometry**. We will use this terminology when discussing products of operators.

The completion fills in the missing action on the kernel to obtain a unitary operator.

One ancilla gives a unitary block encoding

Let $R = LL^*$ and let $\bar{L}$ be a unitary completion. Then

$$U = \begin{pmatrix} L & L^\perp \\ L^\perp & L \end{pmatrix} = \underbrace{\begin{pmatrix} I - R & R \\ R & I - R \end{pmatrix}}_{U_1} \underbrace{\begin{pmatrix} 0 & \bar{L} \\ \bar{L} & 0 \end{pmatrix}}_{U_2}.$$


- $U_2 = X_a \otimes \bar{L}$: Depends on the choice of completion $\bar{L}$.
- $U_1 = I_a \otimes (I - R) + X_a \otimes R$: Depends only on L .

$$(\langle 0 |_a \otimes I) U (|0 \rangle_a \otimes I) = L.$$

The LCNU theory of Session 1 presented a systematic way to compute $\bar{L}$ and implement U for Kronecker products of sigma terms.

Recap: a sigma-product circuit

$$L = \rho_0 \otimes I \otimes \rho_2, \quad \bar{L} = I \otimes I \otimes X, \quad R = \rho_0 \otimes I \otimes \rho_3.$$



First gate column: U_2 . Second gate column: U_1 .

U_1 requires a control for each ρ term (ρ_0 open, ρ_3 closed).

Products and permutations

We want to retain the same completion and block-encoding construction while allowing

$$L = B_1 B_2 \cdots B_m, \quad B_i = \bigotimes_j P_{i,j}.$$

Each factor $P_{i,j}$ may be a Pauli matrix, a rho matrix ρ_r , or a permutation matrix on several qubits.

Every layer B_i acts on the **same n -qubit register**. Its factors may partition that register differently.

Existence of a completion and cost of its circuit are separate questions.

Completions of structured products

Theorem. For a product of the allowed factors,

$$\overline{L} = \overline{B}_1 \cdots \overline{B}_m, \quad \overline{B}_i = \bigotimes_j \overline{P}_{i,j}$$

is a unitary completion, where

$$\overline{P} = \begin{cases} I, & P \in \{\rho_0, \rho_3\}, \\ X, & P \in \{\rho_1, \rho_2\}, \\ P, & P \text{ is Pauli or a permutation.} \end{cases}$$

Easy extension. For unitary V, W , a completion of VLW is $V\overline{L}W$.

Why arbitrary intermediate unitaries fail

$$\rho_0 H \rho_0 = \frac{1}{\sqrt{2}} \rho_0, \quad \|\rho_0 H \rho_0 |0\rangle\| = \frac{1}{\sqrt{2}}.$$

This product is not an isometry on its nonzero initial space, so it has no unitary completion in the sense used here.

For partial isometries A, B , the product AB is a partial isometry exactly when

$$[A^* A, B B^*] = 0.$$

The structured matrices considered here satisfy this condition.

I. Erdelyi, "On Partial Isometries in Finite-Dimensional Euclidean Spaces,"
SIAM J. Appl. Math. **14**(3), 453–467 (1966).

Results on efficient implementation

Define the coordinate projectors

$$\mathcal{R}_n = \left\{ \bigotimes_{k=0}^{n-1} r_k : r_k \in \{\rho_0, \rho_3, I\} \right\}.$$

Theorem. If $LL^* = \sum_{j=1}^r R_j$, where r is a constant and $R_j \in \mathcal{R}_n$ and $R_j R_k = 0$ for $j \neq k$, then U_1 uses r multicontrol not gates.

LL^* factor	Circuit control
ρ_0	Open control
ρ_3	Closed control
I	No control

We want LL^* to be a sum of coordinate projectors. When does this happen?

A useful class of matrices

On n qubits, let

$$\mathcal{O}_n = \left\{ P_f \left(\bigotimes_{k=0}^{n-1} X^{b_k} \right) : f \in \text{Sym}(n), b_k \in \{0, 1\} \right\}.$$

These operations permute qubits and flip individual bits. They map a coordinate projector to another coordinate projector under conjugation.

$$O = P_{\text{swap}}(I \otimes X), \quad O(\rho_0 \otimes \rho_0)O^* = \rho_3 \otimes \rho_0.$$

Corollary. Products built from Pauli matrices, rho terms, and such permutations (also on subregisters) have $LL^* \in \mathcal{R}_n$.

U_1 needs at most one multi-controlled X for this special class.

Circuit construction

1. **Complete the factors.** Replace each ρ_r by I or X and preserve the product order to obtain $\bar{L}$.
2. **Find R .** Compute $R = LL^*$ and express it as disjoint coordinate projectors.
3. **Apply U_2 .** Implement $\bar{L}$ on the system and X on the ancilla.
4. **Apply U_1 .** Add a multicontrol NOT gate with a control for each ρ term (open or closed as needed).

Efficiency also requires an efficient circuit for $\bar{L}$. Arbitrary basis permutations can be expensive. Multi-controlled gates must also be synthesized into the chosen elementary gate set.

Four-qubit example: the completion

Let $S_2|x\rangle = |x + 1 \bmod 4\rangle$. Consider

$$L = (S_2 \otimes \rho_0 \otimes \rho_2)(\rho_0 \otimes \rho_0 \otimes I \otimes I).$$

Note that S_2 is a permutation (an incrementer). A little algebra shows that


$$R = LL^* = \rho_0 \otimes \rho_3 \otimes \rho_0 \otimes \rho_3,$$

$$\bar{L} = S_2 \otimes I \otimes X.$$

U_2 and U_1 can be built using R and $\bar{L}$.

Four-qubit example: the full circuit

$$R = \rho_0 \otimes \rho_3 \otimes \rho_0 \otimes \rho_3, \quad \bar{L} = S_2 \otimes I \otimes X.$$



Burgers' equation and spatial discretization

On a periodic interval, with $N = 2^s$ grid points,

$$u_t = \nu u_{xx} - uu_x, \quad x_j = j\Delta x, \quad \Delta x = L_x/N.$$

Centered differences give, with indices modulo N ,

$$\dot{u}_j = \frac{\nu}{\Delta x^2}(u_{j+1} - 2u_j + u_{j-1}) - \frac{u_j}{2\Delta x}(u_{j+1} - u_{j-1}).$$

For $\mathbf{u} = (u_0, \dots, u_{N-1})^T$,

$$\dot{\mathbf{u}} = F_1 \mathbf{u} + F_2 \mathbf{u}^{\otimes 2}, \quad \mathbf{u}(0) = \mathbf{u}^0,$$

where $F_1 \in \mathbb{R}^{N \times N}$ and $F_2 \in \mathbb{R}^{N \times N^2}$.

Carleman linearization

Lifting to tensor powers produces a linear hierarchy:

$$\frac{d}{dt} \mathbf{u}^{\otimes j} = A_j^j \mathbf{u}^{\otimes j} + A_{j+1}^j \mathbf{u}^{\otimes(j+1)}.$$

$$A_j^j = \sum_{k=0}^{j-1} I_N^{\otimes k} \otimes F_1 \otimes I_N^{\otimes(j-k-1)},$$

$$A_{j+1}^j = \sum_{k=0}^{j-1} I_N^{\otimes k} \otimes F_2 \otimes I_N^{\otimes(j-k-1)}.$$

Truncate at order α by dropping the coupling to order $\alpha + 1$.

The finite linear system approximates the nonlinear dynamics.

R. Demirdjian, T. Hogancamp, D. Gunlycke,

An Efficient Decomposition of the Carleman Linearized Burgers' Equation, arXiv:2505.00285.


The truncated linear system

$$\dot{\mathbf{y}} = A\mathbf{y}, \quad \mathbf{y}(0) = (\mathbf{u}^0, (\mathbf{u}^0)^{\otimes 2}, \dots, (\mathbf{u}^0)^{\otimes \alpha})^T.$$

$$A = \begin{pmatrix} A_1^1 & A_2^1 & 0 & \cdots & 0 \\ 0 & A_2^2 & A_3^2 & \ddots & \vdots \\ \vdots & \ddots & \ddots & \ddots & 0 \\ 0 & \cdots & 0 & A_{\alpha-1}^{\alpha-1} & A_{\alpha}^{\alpha-1} \\ 0 & \cdots & \cdots & 0 & A_{\alpha}^{\alpha} \end{pmatrix}.$$

The j th block of $\mathbf{y}$ has N^j entries:

$$\Delta = \sum_{j=1}^{\alpha} N^j.$$



$$N = 4, \alpha = 4, \Delta = 340.$$

Structured blocks with nontrivial sparsity patterns.

Zero-padding to a qubit register

Set $D = 2N^\alpha = 2^{n'}$, $n' = 1 + \alpha s$, and

$$N_0 = D - \Delta = 2N^\alpha - \sum_{j=1}^{\alpha} N^j.$$

Then

$$A^{(e)} = \begin{pmatrix} 0_{N_0 \times N_0} & 0_{N_0 \times \Delta} \\ 0_{\Delta \times N_0} & A \end{pmatrix} \in \mathbb{R}^{D \times D}, \quad \mathbf{y}^{(e)} = \begin{pmatrix} 0 \\ \mathbf{y} \end{pmatrix}.$$

The padded coordinates remain zero when initialized to zero.

Example: $N = 4$, $\alpha = 2$ gives $\Delta = 20$, $D = 32$, $N_0 = 12$.

Backward Euler as one linear system

Use $M = 2^m$ stored time levels, including the initial state:

$$(I_D - \Delta t A^{(e)}) \mathbf{y}_k^{(e)} = \mathbf{y}_{k-1}^{(e)}, \quad k = 1, \dots, M-1.$$

$$\underbrace{\begin{pmatrix} I_D & 0 & \cdots & 0 \\ -I_D & I_D - \Delta t A^{(e)} & \ddots & \vdots \\ 0 & \ddots & \ddots & 0 \\ 0 & \cdots & -I_D & I_D - \Delta t A^{(e)} \end{pmatrix}}_{L^{(e)}} \underbrace{\begin{pmatrix} \mathbf{y}_0^{(e)} \\ \mathbf{y}_1^{(e)} \\ \vdots \\ \mathbf{y}_{M-1}^{(e)} \end{pmatrix}}_{\mathbf{Y}^{(e)}} = \begin{pmatrix} \mathbf{y}^{(e)}(0) \\ 0 \\ \vdots \\ 0 \end{pmatrix}.$$

First level LCNU decomposition

The cyclic increment matrix

$$S_m = \begin{pmatrix} 0 & 0 & \cdots & 0 & 1 \\ 1 & 0 & \cdots & 0 & 0 \\ 0 & 1 & \ddots & \vdots & \vdots \\ \vdots & \ddots & \ddots & 0 & 0 \\ 0 & \cdots & 0 & 1 & 0 \end{pmatrix}_{2^m \times 2^m}$$

$$L^{(e)} = L_1^{(e)} - \Delta t L_2^{(e)}$$

$$L_1^{(e)} = (I_M - S_m + \rho_1^{\otimes m}) \otimes I_D,$$

$$L_2^{(e)} = (I_M - \rho_0^{\otimes m}) \otimes A^{(e)}.$$

Note that ρ terms are used to conveniently remove unwanted (anti) diagonal entries.

Three LCNU terms for $L_1^{(e)}$, structure is independent of the time discretization.

Completions of the $L_1^{(e)}$ terms

c_ℓ	L_I	$\bar{L}_I$	$L_I L_I^*$
+1	$I_M \otimes I_D$	$I_M \otimes I_D$	$I_M \otimes I_D$
-1	$S_m \otimes I_D$	$S_m \otimes I_D$	$I_M \otimes I_D$
+1	$\rho_1^{\otimes m} \otimes I_D$	$X^{\otimes m} \otimes I_D$	$\rho_0^{\otimes m} \otimes I_D$

$$L_1^{(e)} = (I_M - S_m + \rho_1^{\otimes m}) \otimes I_D$$

Placing the first Carleman block

The first block is $A_1^1 = F_1$. Its contribution to $A^{(e)}$ is

$$\left(\rho_0 \otimes \rho_3^{\otimes(s-1)}\right)^{\otimes(\alpha-1)} \otimes \rho_3 \otimes F_1.$$

Example: $N = 4$, $\alpha = 2$. The register has five qubits and $N_0 = 12$.

$$\rho_0 \otimes \rho_3 \otimes \rho_3 \otimes F_1.$$

The projectors locate the block. The remaining factors implement its dynamics.
 F_1 can be further decomposed using two incrementers and an identity.

General construction: Demirdjian et al., Quantum Data Loading for Carleman Linearized Systems, arXiv:2605.00302.

Summary

- Explicit unitary completions for matrix and/or Kronecker products involving Pauli, rho, and Permutation matrices.
- Systematic rule for block-encoding LCNU decomposition using $\bar{L}$ and R .
- Efficiency implementations for structured classes of matrices.
- Our LCNU approach uses permutations and ρ matrices to encode time stepping and embedded Carleman blocks compactly.
- This method can treat general nonlinear dynamical systems (with polynomial nonlinearity).

A short decomposition is one ingredient of an efficient quantum solver.

Conditioning, coefficient normalization, state preparation, truncation error, and readout still determine the end-to-end cost. Future research efforts will investigate these important aspects.

References

1. I. Erdelyi. *On Partial Isometries in Finite-Dimensional Euclidean Spaces*. SIAM Journal on Applied Mathematics **14**(3), 453–467 (1966).
2. R. Demirdjian, T. Hogancamp, D. Gunlycke. *An Efficient Decomposition of the Carleman Linearized Burgers' Equation*. arXiv:2505.00285.
3. R. Demirdjian, T. Hogancamp, A. Gnanasekaran, A. Surana, D. Gunlycke. *Quantum Data Loading for Carleman Linearized Systems: Application to the Lattice-Boltzmann Equation*. arXiv:2605.00302.

LCNU Burgers' equation

Set $T = \rho_0 \otimes \rho_3^{\otimes(s-1)}$. The general decomposition reduces to

$$\begin{aligned}
 A^{(e)} = & \underbrace{\sum_{j=1}^{\alpha} T^{\otimes(\alpha-j)} \otimes \rho_3 \otimes A_j^j}_{\text{Linear contribution}} \\
 & + \underbrace{\sum_{j=1}^{\alpha-1} T^{\otimes(\alpha-j-1)} \otimes \rho_1 \otimes \left[(X^{\otimes s} \otimes I_{N^j}) A_{j+1}^{(e),j} \right]}_{\text{Quadratic contribution}},
 \end{aligned}$$

where

$$A_{j+1}^{(e),j} = \begin{pmatrix} A_{j+1}^j \\ 0_{(N^{j+1}-N^j) \times N^{j+1}} \end{pmatrix}, \quad \mathcal{P}_2 = X^{\otimes s}.$$

We use the general embedding from the lattice-Boltzmann paper to update the earlier Burgers construction.

Demirdjian et al., arXiv:2605.00302v4, Eqs. (26)–(27) and Appendix E.1.