

## 8-BIT MULTIPLICATION

### EXP NO: 3

**AIM:** To write an assembly language program to implement 8-bit multiplication using 8085 processor.

#### ALGORITHM:

- 1)      Start  
the program by loading a register pair with the address of memory location.
- 2)      Move  
the data to a register.
- 3)      Get  
the second data and load it into the accumulator.
- 4)      Add  
the two register contents.
- 5)      Increment  
the value of the carry.
- 6)      Check  
whether the repeated addition is over.
- 7)      Store  
the value of product and the carry in the memory location.
- 8)      Halt.

**PROGRAM:**

LDA 8500

MOV B, A

LDA 8501

MOV C, A

CPI 00

JZ LOOP

XRA A

LOOP1: ADD B

DCR C

JZ LOOP

JMP LOOP1

LOOP: STA 8502

RST



**RESULT:** Thus the program was executed successfully using 8085 processor simulator.