

BRAC UNIVERSITY
Department of Computer Science and Engineering

Quiz 02
Semester: Fall 2025

Duration: 20 min
Full Marks: 15

Name:	ID:	Section:
--------------	------------	-----------------

CSE 260: Digital Logic Design
SET- B

1. [CO2] Consider the following boolean equation and answer the following questions, $F(A,B,C) = AB'C + B'C' + (AB)'C$
 - a. Simplify the boolean expression using boolean algebra (5 Marks)
 - b. Draw the simplified expression using NAND gate only (3 Marks)
2. [CO2] (6 + 1 Marks) Convert the following equation to its canonical SOP form and find the maxterms, $F(a,b,c,d) = a'b' + b'c + a'c$
Note: You can not simplify this equation