Item	Ref	Qty	Description	Mfg	Part Number
1	C1, C11	2	Capacitor, 10uF, 25V, 10%, 0805 X5R	Murata	GRM21BR61E106KA73L
2	C2	1	Capacitor, 22uF, 16V, 20%, 0805 X5R	Samsung	CL21A226MOCLRNC
3		1	Canasitar 1.15 16V 109/ 0905 V7D	Vagaa	CC000EVVV7D7DD10E
3	CS	1	Capacitor, 1uF, 16V, 10%, 0805 X7R	Yageo	CC0805KKX7R7BB105
4	C4, C5, C8, C9, C10	5	Capacitor, 0.1uF, 50V, 10%, 0805 X7R	Yageo	CC0805KRX7R9BB104
5	C6, C7	2	Capacitor, 22pF, 50V, 5%, 0805	Yageo	CC0805JRNPO9BN220
6	D1	1	TVS Diode, 1-channel Unidirectional,	NXP	PESD24VL1BA,115
			24V, SOD323		
7	D2	1	Zener Diode,7.5V, 2%, 200mW, SOD-	ON	MM3Z7V5ST1G
0	D3	1	323 LED 2.1V/10mA, 0603	Semiconductor	LTST-C129GKT
8 9	D4, D5, D6, D7	4	Connector, 0.600" DIP, 2x9, Right-	Lite-On Inc. Mill-Max	299-43-618-10-002000
9	04, 03, 00, 07	4	Angle	IVIIII-IVIAX	299-45-016-10-002000
10	D4, D5, D6, D7	4	LED,7-segment + DP Display,	Broadcom	HDSP-5523
	- 1, - 2, - 2, - 1		2.1V/20mA, DIP-18 0.600"		
11	D8	1	Diode, 1V, 1206	Bourns	CD1206-S01575
12	D9	1	Diode, 1N4148, 1V, Through-Hole	Fairchild	1N4148
13	DC1	1	DC/DC Converter, Non-Isolated, 7-	CUI Inc	V7805-2000R
			18Vin/5Vout, 10W, SIP-3 Right Angle		
14	F1	1	PTC Fuse, 24V, 500mA/1A, 1206	Bel Fuse Inc	0ZCJ0050AF2E
15	IC1	1	IC, MCU, AVR, 20MHz, 32KB, DIP-28	Atmel	ATMEGA328P-PN
13	101	1	10, WEG, AVN, 20WHZ, 32KB, BH 20	Adillel	ATIVIEGASZOFTIV
16	IC2	1	IC, Inverter, 6-Channel Schmitt Trigger,	Texas Instruments	SN74HC14N
			DIP-14		
17	IC3	1	IC, Display Driver, 7-Segment + DP, 8-	Maxim Integrated	MAX7219CNG+
4.0	14	1	digit, SPI, DIP-24	NADD	FIEODA
18	J1	1	Connector, DC Power Jack, 2.10mm,	MPD	EJ508A
			Right-Angle Through Hole		
19	J2	1	Connector, Breakaway, 0.100", 3x2,	TE Connectivity	5-5176264-8
	<del>-</del>		Through-Hole		
20	OK1	1	Optocoupler, 1-channel, 15MBd, DIP-8	Lite-On Inc.	6N137
21	Q1	1	MOSFET, P-channel, 30V, 65mOhm,	Diodes	DMP3099L-7
			SOT-23	Incorporated	
22	R1, R3, R4	3	Resistor, 10K, 0.125W, 5%, 0805	Stackpole	RMCF0805JT10K0
23	R2	1	Resistor, 470, 0.1W, 1%, 0805	Stackpole	RMCF0805FT470R
24	R5, R6, R7, R8, R9, R10, R11	7	Resistor, 220, 0.125W, 5%, 0805	Stackpole	RMCF0805JT220R
25	R12	1	Resistor, 20K, 0.125W, 1%, 0805	Yageo	RC0805FR-0720KL
26	X1, X2, X3, X4	4	Connector, DIN, 5-position, Female,	CUI Inc	SDS-50J
20	12, 12, 13, 14	-	Right-Angle PCB		323 303
27	Y1	1	Crystal, 16MHz, 10ppm, 18pF,	TXC	9B-16.000MEEJ-B
		<u> </u>	HC49/US PCB Do Not Populate (User-Discre	sion)	
Item	Ref	Qty	Description	Mfg	Part Number
28	IC1	1	Connector, IC Socket, DIP-28 0.300"	On Shore	ED28DT
	.51	l -	22200., 10 00 00 00 00 00 00 00 00 00 00 00 00		
				recrimology	
29	IC2	1	Connector, IC Socket, DIP-14 0.300"	Technology On Shore	ED14DT

30	IC3	1	Connector, IC Socket, DIP-24 0.300"	On Shore	ED24DT
				Technology	
31	OK1	1	Connector, IC Socket, DIP-8 0.300"	On Shore	ED08DT
				Technology	