

AAS Comprehensive Flows

Complete Step-by-Step Workflows & Business Processes

Generated: April 02, 2026
Automated Accounting System (AAS)

Table of Contents

- 1. Order Workflow - Complete order lifecycle
- 2. Vendor Operations - Vendor-centric tracking
- 3. Branch Operations - Branch receivables & health
- 4. Billing & Invoice - Customer invoicing process
- 5. Stock Management - Inventory monitoring
- 6. Key Concepts - Statuses, calculations, errors

1. Order Workflow

Core business process from order creation to invoicing.

Status Pipeline

DRAFT => VENDOR_ASSIGNED => VENDOR_PDF_RECEIVED =>
VENDOR_BILL_CAPTURED => SELL_ORDER_CREATED => INVOICED

Step 1: Create Order

Navigate Orders > Create Order. Choose image or item mode.
Upload image/select items. Set branch, company, dates.
POST /api/orders or /api/orders/branch-image.
Order created in DRAFT status.

Step 2: Assign Vendor

Click Assign Vendor. Select from dropdown.
POST /api/orders/{id}/assign-vendor.
Status -> VENDOR_ASSIGNED.

Step 3: Upload Vendor PDF

Upload vendor bill PDF.
POST /api/orders/{id}/vendor-pdf.
Backend parses using AI: extracts items, qty, rates.
Status -> VENDOR_PDF_RECEIVED.

Step 4: Capture Bill

Review parsed data. Enter: Bill Total, Ref, Date, Transport Charge.
POST /api/orders/{id}/vendor-bill.
Status -> VENDOR_BILL_CAPTURED.

Step 5: Preview Sell

GET /api/orders/{id}/sell-preview.
Check margin %. Adjust sell rates if needed.

Step 6: Create Sell Order

POST /api/orders/{id}/sell-order.
Backend creates Purchase Invoice (cost) & Sales Order (sell).
Status -> SELL_ORDER_CREATED.

Step 7: Create Invoice

Bills > Create Invoice > Select Order.
Auto-fill: customer, items, rates.
Apply GST if needed. POST /api/invoices.
Order Status -> INVOICED.

2. Vendor Operations Workflow

Track vendor performance, pending orders, and financial settlement.

Step 1: View Summary

Operations > Vendor Ops.

GET /api/vendor-ops/summary.

Table: all vendors with pending orders, awaiting PDF/bill, pending amount.

Step 2: Identify Issues

Look for: high pending, awaiting PDF, awaiting bill, overdue status.

Prioritize follow-up actions.

Step 3: Drill-Down

Click vendor name.

GET /api/vendor-ops/{id}.

Detailed view: KPIs, template status, exceptions.

Step 4: View Orders

GET /api/vendor-ops/{id}/orders.

Table: order ID, PDF status, parsed items, bill total, mismatch flag.

Step 5: Check Ledger

GET /api/vendor-ops/{id}/ledger.

Double-entry ledger: date, voucher, debit, credit, running balance.

Reconcile payments vs invoices.

Step 6: Assess Settlement

SETTLED = balance ~0. OPEN = money owed. OVERDUE = action needed.

Decide next step: follow-up payment or investigation.

Step 7: Export Ledger

GET /api/vendor-ops/{id}/ledger/export.

Download CSV. Open in Excel for detailed analysis.

3. Branch Operations Workflow

Track branch orders, receivables, payment health, and settlement.

Step 1: View Summary

Operations > Branch Ops.

GET /api/branch-ops/summary.

Table: all branches with pending orders, receivables, payment rate.

Step 2: Analyze Health

Look for: high receivables, low payment rate, overdue status, recent activity.

Assess financial risk.

Step 3: Drill-Down

Click branch name.

GET /api/branch-ops/{id}.

Detailed view: KPIs, billing summary, exceptions, overdue invoices.

Step 4: View Orders

GET /api/branch-ops/{id}/orders.

Table: order ID, vendor, status, dates, PDF status, bill/sell totals, invoice link.

Step 5: Check Ledger

GET /api/branch-ops/{id}/ledger.

Double-entry: date, voucher, debit (invoices), credit (payments), balance.

Track account reconciliation.

Step 6: Outstanding Analysis

Sum open invoices = total outstanding. Review overdue.

Calculate days past due. Determine collection priority.

Step 7: Export & Act

GET /api/branch-ops/{id}/ledger/export -> CSV.

Excel analysis. Send payment reminders, adjust terms, escalate if needed.

4. Billing & Invoice Workflow

Create customer invoices and record payments.

Step 1: Create from Order

Bills > Create Invoice. Select order.

GET /api/orders/{id}. Auto-fill: customer, items, rates.

Step 2: Apply GST

Optional: toggle GST.

Backend creates Item Tax Template, GST account.

Calculates tax per item.

Step 3: Auto Due Date

Backend: Due Date = Invoice Date + Customer.credit_days.

Used for payment tracking.

Step 4: Submit

POST /api/invoices with { fields: {...} }.

Backend creates Sales Invoice in ERPNext.

Step 5: Download PDF

GET /api/invoices/{id}/pdf.

Uses company's aas_sales_invoice_print_format.

Downloads PDF.

Step 6: Record Payment

Bills > Record Payment. Select invoice (auto-fill outstanding).

Enter payment amount. Check for surplus/overpayment.

POST /api/payments.

Step 7: Allocation

Backend allocates min(payment, outstanding) to invoice.

Surplus stored. Creates Payment Entry in ERPNext.

Outstanding amount reduced.

5. Stock Management Workflow

Monitor inventory and set reorder thresholds.

Step 1: View Stock

Inventory > Stock.

GET /api/stock.

Table: item code, qty, threshold, status (Low/OK).

Summary: total items, qty, low count.

Step 2: Set Thresholds

Click item > Edit Threshold. Enter qty threshold.

Save to localStorage (per-device).

Example: 20 = alert when qty < 20.

Step 3: Monitor

System checks: qty <= threshold -> LOW. qty > threshold -> OK.

Low items highlighted. Count shown in summary.

Step 4: Create Order

When low, Orders > Create > select low items.

Submit order through normal workflow.

Status tracked in Vendor/Branch Ops.

Step 5: Receive

Vendor updates qty in ERPNext.

Qty visible in Stock list. Status -> OK.

Cycle repeats.

Key Concepts

Order Statuses

DRAFT: Not confirmed. VENDOR_ASSIGNED: Vendor picked. VENDOR_PDF_RECEIVED: Bill uploaded. VENDOR_BILL_CAPTURED: Bill confirmed. SELL_ORDER_CREATED: Internal documents created. INVOICED: Customer invoice created.

Settlement Statuses

SETTLED: Balance = 0 (all settled). OPEN: Outstanding balance (money owed). OVERDUE: Past due or critical (action needed).

Key Calculations

Margin % = $((\text{Sell} - \text{Cost}) / \text{Cost}) * 100$. Outstanding = Total - Paid. Days Overdue = Today - Due. Balance = Previous + Current.