

Instrucción	LD reg	ST reg	LDI num, reg	LDM dir, reg	STM reg, dir	ADD reg	SUB reg	CMP reg	INC	ADI num	SUI num	CMI num	ANA reg	ORA reg	XRA reg	CMA	ANI num	ORI num	XRI num	JMP dir	BEQ dir	BC dir	LF
Tipo	Transferencia					Aritméticas							Lógicas							Salto y otra			
CO ₄	0					0							1							1			
CO ₃	0					1							0							1			
Bytes	1 ó 2			3		1				2			1				2			3			1
CO ₂	0			1		0				1			0				1			0			1
CO ₁	0	1	1	0	1	0	1	1	0	1	1	0	1	0	1	0	1	1	0	1	0	1	x
CO ₀	0	1	x	x	x	0	1	0	1	0	1	x	0	1	0	1	0	1	x	x	0	1	x

T ₃	T ₂	T ₁	T ₀	Condición del Test
x	0	0	0	CO ₀ = x
x	0	0	1	CO ₁ = x
x	0	1	0	CO ₂ = x
x	0	1	1	CO ₃ = x
x	1	0	0	CO ₄ = x
x	1	0	1	FZero = x
x	1	1	0	FCarry = x
0	1	1	1	Salto incondicional
1	1	1	1	Ejecución secuencial

Operación UAL	UAL ₂	UAL ₁	UAL ₀
A+B (Ca2)	0	0	0
A-B (Ca2)	0	0	1
A and B	0	1	0
A or B	0	1	1
$A \oplus B$	1	0	0
not A	1	0	1
Libre/Reserva	1	1	0
A + 1	1	1	1



