

Shade Shifter - Online Purchases

Parts that should be ordered from a documented online supplier, including later-stage items. Items: 16.

Actual product photo	Purchase	Exact part and source	Qty.	Required specification	Do not buy
	BUY ONLINE NOW â‚¬135 + delivery/import	Ynvisible Evaluation Kit 5.2 Open product/photo source	1	Complete EVKIT301H1F1PV1: 13 displays, Driver 5.2, IÂ°C interface, FPC adapter and instructions.	Do not buy raw electrochromic ink, an unpowered sample sheet, or a seven-segment-only loose display.
	BUY ONLINE NOW â‚¬870â‚¬â‚¬1,100 each	ESP32-C3-DevKitM-1 Open product/photo source	2	Official Espressif board, BLE, 4 MB flash and USB programming. Use for bench development.	Do not buy ESP8266, ESP32-S2 (no Bluetooth), or a board with no documented pinout.
	BUY ONLINE NOW â‚¬800â‚¬â‚¬1,250 each	Seeed XIAO ESP32-C3 Open product/photo source	2	21 Å— 17.8 mm board with BLE, USB-C and onboard single-cell battery charging.	Do not substitute XIAO ESP32-S3 unless firmware and pin mapping are deliberately updated.
	BUY ONLINE NOW â‚¬400â‚¬â‚¬1,000	Addressable RGB LED strip Open product/photo source	1 m	WS2812B or SK6812, 5 V, 60 LEDs/m. Buy one normal-width strip for the bench.	Do not buy a 12 V analog RGB strip, RGBW strip, or non-addressable four-wire strip.
	BUY ONLINE NOW â‚¬500â‚¬â‚¬2,000	SK6805-2020 RGB LED samples Open product/photo source	20â‚¬40	2.0 Å— 2.0 mm, 5 V addressable RGB, individually packaged or on a narrow sample PCB.	Do not buy bare 0201 LEDs, common-anode RGB LEDs, or large WS2812B 5050 packages.
	BUY ONLINE NOW â‚¬250â‚¬â‚¬700 total	74AHCT125 level shifter Open product/photo source	5	74AHCT125N in DIP-14 for breadboard tests; TTL-level input at 5 V supply.	Do not buy 74HC125 or a slow bidirectional IÂ°C level-shifter module for the LED data line.
	BUY ONLINE NOW Request current price	ITO-coated PET sheet Open product/photo source	3	Flexible PET, approximately 100 Å— 200 mm; supplier must state sheet resistance and conductive side.	Do not buy ITO glass, plain clear PET, privacy film, or PDLC smart film.
	BUY ONLINE NOW â‚¬300â‚¬â‚¬1,000	Conductive copper foil tape Open product/photo source	2 rolls	3 mm and 6 mm widths with electrically conductive adhesive.	Do not buy copper-coloured decorative tape or foil whose adhesive is non-conductive.

