

Diagrams and algebraic expressions at order 4 in MBPT

RDL, JR, PA, MD, AT, TD, JPE

May 16, 2018

Valid diagrams: 39
Singles: 4
Doubles: 12
Triples: 16
Quadruples: 7
Quintuples and higher excitation levels: 0

Contents

1	Singles	1
2	Doubles	3
3	Triples	7
4	Quadruples	12

1 Singles

Diagram 1:

$$\frac{1}{4}(-1)^{5-3} \sum \frac{v_{abij} v_{ijak} v_{kclm} v_{lm bc}}{\epsilon_{ab}^{ij} \epsilon_b^k \epsilon_{bc}^{lm}} \quad (1)$$




Diagram 2: Complex conjugate diagram: 3

$$\frac{1}{4}(-1)^{4-3} \sum \frac{v_{abij} v_{ijak} v_{cdbl} v_{klcd}}{\epsilon_{ab}^{ij} \epsilon_b^k \epsilon_{cd}^{kl}} \quad (2)$$




Diagram 3: Complex conjugate diagram: 2

$$\frac{1}{4}(-1)^{4-3} \sum \frac{v_{abij} v_{icab} v_{jdkl} v_{klcd}}{\epsilon_{ab}^{ij} \epsilon_c^j \epsilon_{cd}^{kl}} \quad (3)$$





Diagram 4:

$$\frac{1}{4}(-1)^{3-3} \sum \frac{v_{abij} v_{icab} v_{deck} v_{jkde}}{\epsilon_{ab}^{ij} \epsilon_c^j \epsilon_{de}^{jk}} \quad (4)$$



2 Doubles

Diagram 5:

$$\frac{1}{16}(-1)^{6-2} \sum \frac{v_{abij}v_{ijkl}v_{klmn}v_{mnab}}{\epsilon_{ab}^{ij} \epsilon_{ab}^{kl} \epsilon_{ab}^{mn}} \quad (5)$$




Diagram 6: Complex conjugate diagram: 8

$$\frac{1}{2}(-1)^{5-3} \sum \frac{v_{abij}v_{ijkl}v_{kcam}v_{lmbc}}{\epsilon_{ab}^{ij} \epsilon_{ab}^{kl} \epsilon_{bc}^{lm}} \quad (6)$$




Diagram 7: Complex conjugate diagram: 14

$$\frac{1}{16}(-1)^{4-2} \sum \frac{v_{abij}v_{ijkl}v_{cdab}v_{klcd}}{\epsilon_{ab}^{ij} \epsilon_{ab}^{kl} \epsilon_{cd}^{kl}} \quad (7)$$




Diagram 8: Complex conjugate diagram: 6

$$\frac{1}{2}(-1)^{5-3} \sum \frac{v_{abij}v_{icak}v_{jklm}v_{lmbc}}{\epsilon_{ab}^{ij} \epsilon_{bc}^{jk} \epsilon_{bc}^{lm}} \quad (8)$$




Diagram 9:

$$\frac{1}{1}(-1)^{4-4} \sum \frac{v_{abik}v_{icaj}v_{jdcl}v_{klbd}}{\epsilon_{ab}^{ik} \epsilon_{cb}^{jk} \epsilon_{bd}^{kl}} \quad (9)$$




Diagram 10:

$$\frac{1}{1}(-1)^{4-3} \sum \frac{v_{abij}v_{icak}v_{jdcl}v_{klbd}}{\epsilon_{ab}^{ij} \epsilon_{cb}^{jk} \epsilon_{bd}^{kl}} \quad (10)$$




Diagram 11:

$$\frac{1}{1}(-1)^{4-3} \sum \frac{v_{abik}v_{icaj}v_{jdbl}v_{klcd}}{\epsilon_{ab}^{ik} \epsilon_{bc}^{jk} \epsilon_{cd}^{kl}} \quad (11)$$




Diagram 12:

$$\frac{1}{1}(-1)^{4-4} \sum \frac{v_{abij}v_{icak}v_{jdbl}v_{klcd}}{\epsilon_{ab}^{ij} \epsilon_{bc}^{jk} \epsilon_{cd}^{kl}} \quad (12)$$




Diagram 13: Complex conjugate diagram: 15

$$\frac{1}{2}(-1)^{3-3} \sum \frac{v_{abij}v_{icak}v_{debc}v_{jkde}}{\epsilon_{ab}^{ij} \epsilon_{bc}^{jk} \epsilon_{de}^{jk}} \quad (13)$$




Diagram 14: Complex conjugate diagram: 7

$$\frac{1}{16}(-1)^{4-2} \sum \frac{v_{abij}v_{cdab}v_{ijkl}v_{klcd}}{\epsilon_{ab}^{ij} \epsilon_{cd}^{ij} \epsilon_{cd}^{kl}} \quad (14)$$



Diagram 15: Complex conjugate diagram: 13

$$\frac{1}{2}(-1)^{3-3} \sum \frac{v_{abij}v_{cdab}v_{ieck}v_{jkde}}{\epsilon_{ab}^{ij} \epsilon_{cd}^{ij} \epsilon_{de}^{jk}} \quad (15)$$





Diagram 16:

$$\frac{1}{16}(-1)^{2-2} \sum \frac{v_{abij}v_{cdab}v_{efcd}v_{ijef}}{\epsilon_{ab}^{ij} \epsilon_{cd}^{ij} \epsilon_{ef}^{ij}} \quad (16)$$



3 Triples

Diagram 17:

$$\frac{1}{4}(-1)^{5-1} \sum \frac{v_{abil}v_{icjk}v_{jkcm}v_{lmab}}{\epsilon_{ab}^{il} \epsilon_{cab}^{jkl} \epsilon_{ab}^{lm}} \quad (17)$$




Diagram 18:

$$\frac{1}{2}(-1)^{5-1} \sum \frac{v_{abij}v_{ickl}v_{jkcm}v_{lmab}}{\epsilon_{ab}^{ij} \epsilon_{cab}^{jkl} \epsilon_{ab}^{lm}} \quad (18)$$




Diagram 19:

$$\frac{1}{2}(-1)^{5-3} \sum \frac{v_{abil}v_{icjk}v_{jkam}v_{lm bc}}{\epsilon_{ab}^{il} \epsilon_{abc}^{jkl} \epsilon_{bc}^{lm}} \quad (19)$$




Diagram 20:

$$\frac{1}{1}(-1)^{5-1} \sum \frac{v_{abij}v_{ickl}v_{jkam}v_{lm bc}}{\epsilon_{ab}^{ij} \epsilon_{abc}^{jkl} \epsilon_{bc}^{lm}} \quad (20)$$




Diagram 21: Complex conjugate diagram: 25

$$\frac{1}{1}(-1)^{4-3} \sum \frac{v_{abik}v_{icjl}v_{jdac}v_{klbd}}{\epsilon_{ab}^{ik} \epsilon_{acb}^{jkl} \epsilon_{bd}^{kl}} \quad (21)$$




Diagram 22: Complex conjugate diagram: 26

$$\frac{1}{2}(-1)^{4-2} \sum \frac{v_{abij}v_{ickl}v_{jdac}v_{klbd}}{\epsilon_{ab}^{ij} \epsilon_{acb}^{kl} \epsilon_{bd}^{kl}} \quad (22)$$




Diagram 23: Complex conjugate diagram: 29

$$\frac{1}{2}(-1)^{4-2} \sum \frac{v_{abik}v_{icjl}v_{jdab}v_{klcd}}{\epsilon_{ab}^{ik} \epsilon_{abc}^{jkl} \epsilon_{cd}^{kl}} \quad (23)$$




Diagram 24: Complex conjugate diagram: 30

$$\frac{1}{4}(-1)^{4-1} \sum \frac{v_{abij}v_{ickl}v_{jdab}v_{klcd}}{\epsilon_{ab}^{ij} \epsilon_{abc}^{jkl} \epsilon_{cd}^{kl}} \quad (24)$$




Diagram 25: Complex conjugate diagram: 21

$$\frac{1}{1}(-1)^{4-3} \sum \frac{v_{abik} v_{cdaj} v_{ijcl} v_{klbd}}{\epsilon_{ab}^{ik} \epsilon_{cbd}^{ijk} \epsilon_{bd}^{kl}} \quad (25)$$




Diagram 26: Complex conjugate diagram: 22

$$\frac{1}{2}(-1)^{4-2} \sum \frac{v_{abij} v_{cdak} v_{ijcl} v_{klbd}}{\epsilon_{ab}^{ij} \epsilon_{cbd}^{ijk} \epsilon_{bd}^{kl}} \quad (26)$$




Diagram 27:

$$\frac{1}{4}(-1)^{3-1} \sum \frac{v_{abjk} v_{cdai} v_{iecd} v_{jkbe}}{\epsilon_{ab}^{jk} \epsilon_{cdb}^{ijk} \epsilon_{be}^{jk}} \quad (27)$$




Diagram 28:

$$\frac{1}{2}(-1)^{3-3} \sum \frac{v_{abij}v_{cdak}v_{iecd}v_{jkbe}}{\epsilon_{ab}^{ij} \epsilon_{cdb}^{jk} \epsilon_{be}^{jk}} \quad (28)$$




Diagram 29: Complex conjugate diagram: 23

$$\frac{1}{2}(-1)^{4-2} \sum \frac{v_{abik}v_{cdaj}v_{ijbl}v_{klcd}}{\epsilon_{ab}^{ik} \epsilon_{bcd}^{jk} \epsilon_{cd}^{kl}} \quad (29)$$




Diagram 30: Complex conjugate diagram: 24

$$\frac{1}{4}(-1)^{4-1} \sum \frac{v_{abij}v_{cdak}v_{ijbl}v_{klcd}}{\epsilon_{ab}^{ij} \epsilon_{bcd}^{jk} \epsilon_{cd}^{kl}} \quad (30)$$




Diagram 31:

$$\frac{1}{2}(-1)^{3-1} \sum \frac{v_{abjk}v_{cdai}v_{iebc}v_{jkde}}{\epsilon_{ab}^{jk} \epsilon_{bcd}^{jk} \epsilon_{de}^{jk}} \quad (31)$$





Diagram 32:

$$\frac{1}{1}(-1)^{3-1} \sum \frac{v_{abij}v_{cdak}v_{iebc}v_{jkde}}{\epsilon_{ab}^{ij} \epsilon_{bcd}^{jk} \epsilon_{de}^{jk}} \quad (32)$$



4 Quadruples

Diagram 33:

$$\frac{1}{4}(-1)^{4-1} \sum \frac{v_{abik}v_{cdjl}v_{ijcd}v_{klab}}{\epsilon_{ab}^{ik} \epsilon_{cdab}^{ijkl} \epsilon_{ab}^{kl}} \quad (33)$$




Diagram 34:

$$\frac{1}{16}(-1)^{4-2} \sum \frac{v_{abij}v_{cdkl}v_{ijcd}v_{klab}}{\epsilon_{ab}^{ij} \epsilon_{cdab}^{ijkl} \epsilon_{ab}^{kl}} \quad (34)$$




Diagram 35:

$$\frac{1}{4}(-1)^{4-1} \sum \frac{v_{abkl}v_{cdij}v_{ijac}v_{klbd}}{\epsilon_{ab}^{kl} \epsilon_{acbd}^{ijkl} \epsilon_{bd}^{kl}} \quad (35)$$




Diagram 36:

$$\frac{1}{1}(-1)^{4-4} \sum \frac{v_{abik}v_{cdjl}v_{ijac}v_{klbd}}{\epsilon_{ab}^{ik} \epsilon_{acbd}^{ijkl} \epsilon_{bd}^{kl}} \quad (36)$$




Diagram 37:

$$\frac{1}{4}(-1)^{4-3} \sum \frac{v_{abij}v_{cdkl}v_{ijac}v_{klbd}}{\epsilon_{ab}^{ij} \epsilon_{acbd}^{ijkl} \epsilon_{bd}^{kl}} \quad (37)$$




Diagram 38:

$$\frac{1}{16}(-1)^{4-2} \sum \frac{v_{abkl}v_{cdij}v_{ijab}v_{klcd}}{\epsilon_{ab}^{kl} \epsilon_{abcd}^{ijkl} \epsilon_{cd}^{kl}} \quad (38)$$




Diagram 39:

$$\frac{1}{4}(-1)^{4-3} \sum \frac{v_{abik}v_{cdjl}v_{ijab}v_{klcd}}{\epsilon_{ab}^{ik} \epsilon_{abcd}^{ijkl} \epsilon_{cd}^{kl}} \quad (39)$$

