

//www.teencoders.com.ng

//+2348039558839

//ARDUINO TUTORIAL - 2 TRAFFIC LIGHT PROJECT

//Create the variables and assign the pins to them.

int REDPIN=13;

int YELLOWPIN=12;

int GREENPIN=11;

void setup() {

 //Set the pins to output pins using pinMode

 pinMode(REDPIN, OUTPUT);

 pinMode(YELLOWPIN, OUTPUT);

 pinMode(GREENPIN, OUTPUT);

}

void loop() {

 //Make the LEDs blink in turn:

 //Turn on the red led, and turn off the yellow and green leds.

 digitalWrite(REDPIN, HIGH);

 digitalWrite(YELLOWPIN, LOW);

 digitalWrite(GREENPIN, LOW);

 delay(2000);

 //Turn on the yellow led, and turn off the red and green leds.

```
digitalWrite(REDPIN, LOW);\ndigitalWrite(YELLOWPIN, HIGH);\ndigitalWrite(GREENPIN, LOW);\ndelay(2000);
```

```
//Turn on the green led, and turn off the red and yellow leds.
```

```
digitalWrite(REDPIN, LOW);\ndigitalWrite(YELLOWPIN, LOW);\ndigitalWrite(GREENPIN, HIGH);\ndelay(2000);\n}
```