

Creating a Ladder Diagram Program in CODESYS

1. Open the **CODESYS** software.
 2. Create a **new project**, then click **OK**.
 3. Select **LD (Ladder Diagram)** as the programming language, then click **OK**.
 4. Click **Ladder Diagram** and create the program.
 5. For simulation, go to **Online** → **Login**, then **Online** → **Run**.
-

Visualization

1. Go to **Online** → **Logout**.
 2. In the **bottom-left corner** of the project tree, select the **third item (Visualization Manager)**.
 3. Right-click and select **Add Object** → **Visualization**.
 4. Enter a name and click **OK**.
-

Drawing a Switch

1. Double-click the switch object to open **Properties**.
 2. Under **Colors**, set the **Alarm Color** to any desired color.
 3. Go to **Variables** → **Change Color** and enter the **input address**.
 4. In **Input**, select **Toggle Variable** and enter the **input address**.
-

Output

1. Open the output object **Properties**.
2. Under **Colors**, set the **Alarm Color** to any desired color, then click **OK**.
3. Go to **Variables** → **Change Color**, enter the **output address**, then click **OK**.