

$$\begin{aligned}MMF_i &= H_i \cdot l_i \\&= \frac{2 \times 0.5}{4\pi \times 10^{-7} \times 2000} \\&= 398 \text{ AT}\end{aligned}$$

$$H_g = \frac{B}{\mu_0}$$

$$\begin{aligned}MMF_g &= H_g \cdot l_g \\&= \frac{2 \times 0.001}{4\pi \times 10^{-7}} \\&= 1592 \text{ AT}\end{aligned}$$

$$\begin{aligned}MMF &= MMF_i + MMF_g \\&= 398 + 1592 \\&= 1990 \text{ AT}\end{aligned}$$