

Magnetic: Reluctanceiv) Law Similarity:-Ohm's law $\longleftrightarrow$ Magnetic circuit law

$$5) L = 40 \text{ cm} = 0.4 \text{ m}$$

$$A = 5 \text{ cm}^2 = 5 \times 10^{-4} \text{ m}^2$$

$$\mu_r = 1000$$

$$N = 500$$

$$I = 2 \text{ A}$$

$$a) H = \frac{NI}{L} = \frac{500 \times 2}{0.4}$$

$$= 2500 \text{ A/m}$$

$$b) B = \mu_0 \mu_r H$$

$$= (4\pi \times 10^{-7}) \times 1000 \times 2500$$

$$= 3.14 \text{ T}$$

$$c) \phi = B \cdot A$$

$$= 3.14 \times 5 \times 10^{-4}$$

$$= 1.57 \times 10^{-3} \text{ Wb}$$

$$6) \mu_r = 2000$$

$$L_i = 50 \text{ cm} = 0.5 \text{ m}$$

$$I_g = 1 \text{ mm} = 0.001 \text{ m}$$

$$A = 4 \text{ cm}^2 = 4 \times 10^{-4} \text{ m}^2$$

$$\phi = 0.8 \text{ mWb} = 0.8 \times 10^{-3}$$

$$B = \frac{\phi}{A} = \frac{0.8 \times 10^{-3}}{4 \times 10^{-4}}$$

$$= 2 \text{ T}$$

$$H_i = \frac{B}{\mu_0 \mu_r}$$

$$\mu_0 \mu_r$$