

PE-EC603B — Bio-Medical Electronics

Semester VI • 3L:0T:0P • 3 Credits

Module 4 Exam Notes: Prostheses, Therapeutic Devices and Electrical Safety

CGEC | B.Tech ECE (2023–27) | *Biraj Sarkar*

Contents


1	Cardiac Pacemakers	2
1.1	Pacemaker Block Diagram	2
1.2	Types of Pacemakers	2
1.3	Pacemaker Timing Parameters	2
2	Defibrillators	3
2.1	Principle and Types	3
2.2	Defibrillator Circuit and Waveforms	4
3	Heart-Lung Machine (Cardiopulmonary Bypass)	4
3.1	Components and Operation	4
4	Artificial Kidney (Dialysis)	5
4.1	Principles of Dialysis	5
4.2	Haemodialysis Circuit	5
5	Aids for the Handicapped	6
5.1	Cochlear Implant	6
5.2	Prosthetic Limbs	6
5.3	Other Assistive Devices	6
6	Electrical Safety in Medical Environments	7
6.1	Macroshock and Microshock	7
6.2	Sources of Leakage Current	7
6.3	Safety Methods and Standards	8
6.4	IEC 60601 Equipment Classification	8

1. Cardiac Pacemakers

Definition: Cardiac Pacemaker

A **cardiac pacemaker** is an implantable electronic device that delivers controlled electrical stimuli to the heart muscle to maintain an adequate heart rate when the natural conduction system (SA node, AV node) fails or is too slow (bradycardia, heart block, sick sinus syndrome).

1.1 Pacemaker Block Diagram



1.2 Types of Pacemakers

Type	Description	Use
Single-chamber (AAI / VVI)	Senses and paces one chamber only (atrium or ventricle).	Sick sinus syndrome (AAI); complete heart block (VVI).
Dual-chamber (DDD)	Senses and paces both atrium and ventricle; maintains AV synchrony.	AV block with intact SA node.
Rate-responsive (DDDR)	Uses sensor (accelerometer, minute ventilation) to increase rate during exercise.	Chronotropic incompetence, active patients.
CRT (Biventricular)	Paces both ventricles simultaneously to resynchronize contraction.	Heart failure with left bundle branch block.
Leadless pacemaker	Capsule implanted directly in right ventricle; no transvenous lead.	Single-chamber pacing without lead complications.

1.3 Pacemaker Timing Parameters

Pacemaker Timing Intervals

Pacing Rate	$\text{Rate (bpm)} = \frac{60\,000}{\text{Pacing Interval (ms)}}$
AV Delay	Time from atrial pace/sense to ventricular pace ($\approx 120\text{--}200$ ms; mimics PR interval).
Refractory Period	Time after a sensed/paced event during which the pacemaker ignores signals ($\approx 250\text{--}400$ ms).
Escape Interval	Time from a sensed beat to the next paced beat if no intrinsic beat occurs.
Pulse Width	Duration of pacing pulse ($\approx 0.4\text{--}1.0$ ms).
Pulse Amplitude	Voltage of pacing pulse ($\approx 2.5\text{--}5$ V; must exceed stimulation threshold).

Energy Source: Lithium–iodide (LiI) battery; longevity 5–15 years. Elective Replacement Indicator (ERI) detects end-of-battery voltage (2.4 V from 2.8 V nominal).

2. Defibrillators

Definition: Defibrillator


A **defibrillator** is a device that delivers a controlled, high-energy electrical shock to the heart to terminate life-threatening arrhythmias such as **ventricular fibrillation (VF)** and **ventricular tachycardia (VT)**, depolarizing all cardiac cells simultaneously so that the SA node can resume normal pacemaker control.

2.1 Principle and Types

Ventricular fibrillation is chaotic, uncoordinated cardiac electrical activity — the heart quivers rather than pumping. Without defibrillation within $\approx 4\text{--}6$ minutes, brain death ensues.

Type	Description	Energy
External	Paddle or adhesive pad electrodes on chest wall.	150–360 J (monophasic); 120–200 J (biphasic).
Internal	Used during cardiac surgery; paddles placed directly on heart.	20–50 J.
ICD (Implantable Cardioverter Defibrillator)	Permanently implanted; monitors rhythm continuously; delivers therapy automatically.	25–40 J; also provides anti-tachycardia pacing.
AED (Automated External Defibrillator)	Portable; analyses rhythm and advises/delivers shock automatically. Designed for lay-rescuer use.	120–200 J (biphasic).


2.2 Defibrillator Circuit and Waveforms




Energy stored in capacitor: $E = \frac{1}{2}CV^2$. For $C = 32 \mu\text{F}$ and $V = 3000 \text{ V}$: $E = \frac{1}{2} \times 32 \times 10^{-6} \times (3000)^2 = 144 \text{ J}$.

Biphasic vs. Monophasic: Biphasic waveforms reverse polarity partway through the shock. They are more effective at lower energies ($\approx 150\text{--}200 \text{ J}$ vs. 360 J) and cause less myocardial injury. All modern defibrillators use biphasic waveforms.

3. Heart-Lung Machine (Cardiopulmonary Bypass)



3.1 Components and Operation



Key components:

- **Oxygenator (Membrane type):** Blood flows past a semipermeable membrane; O_2 diffuses in and CO_2 diffuses out. Replaces the lungs.
- **Roller Pump / Centrifugal Pump:** Provides non-pulsatile (roller) or pulsatile (centrifugal) blood flow. Replaces the heart.

- **Heat Exchanger:** Lowers body temperature (hypothermia, 28–32°C) during surgery to reduce metabolic demand; rewarms blood before weaning from bypass.
- **Arterial Filter:** Removes air bubbles and particulate emboli from the arterial return line.
- **Cardioplegia system:** Cold potassium-rich solution delivered to coronary arteries to arrest the heart in diastole (electromechanical quiescence).

4. Artificial Kidney (Dialysis)

Haemodialysis (Artificial Kidney)

Haemodialysis is a renal replacement therapy for patients with End-Stage Renal Disease (ESRD). Blood is withdrawn, passed through a **dialyser** (artificial kidney) containing a semipermeable membrane, and returned to the body. The dialyser removes metabolic waste products (urea, creatinine, excess electrolytes) and excess water by the processes of **diffusion** and **ultrafiltration**.

4.1 Principles of Dialysis

Mass Transport Mechanisms in Haemodialysis

Diffusion	Movement of solutes across membrane from high to low concentration. Main mechanism for small solutes (urea, creatinine, potassium).
Ultrafiltration	Hydraulic pressure drives water (and dissolved solutes) across the membrane. Controlled to remove excess fluid (1–3 L/session).
Clearance (K)	$K = \frac{Q_{Bi} \cdot C_{Bi} - Q_{Bo} \cdot C_{Bo}}{C_{Bi}} \quad (\text{mL/min})$
KT/V	Urea dialysis adequacy measure: $Kt/V = -\ln(R - 0.008t) + (4 - 3.5R) \times \frac{UF}{W}$ target ≥ 1.2 .

4.2 Haemodialysis Circuit

Blood is withdrawn from a vascular access (arteriovenous fistula, graft, or central venous catheter), anticoagulated with heparin, pumped through the dialyser at 200–500 mL/min and returned. The dialysate (purified water + electrolytes) flows counter-current to blood at 500–800 mL/min.

Safety alarms in a dialysis machine:

- Air bubble detector (ultrasonic).
- Venous pressure monitor (clot detection).
- Blood leak detector (photometric — detects red blood cells in dialysate).
- Conductivity monitor (ensures correct dialysate concentration).

- Temperature alarm ($\pm 1^\circ\text{C}$ from 37°C).

Peritoneal Dialysis (PD): Dialysate is instilled into the peritoneal (abdominal) cavity; the peritoneal membrane acts as the dialyser. No blood circuit required; performed at home. Less efficient than haemodialysis but better for residual renal function preservation.

5. Aids for the Handicapped

5.1 Cochlear Implant

Cochlear Implant

A **cochlear implant** is an electronic device that bypasses damaged hair cells in the cochlea and directly stimulates the auditory nerve fibres with electrical impulses, enabling profoundly deaf or severely hard-of-hearing individuals to perceive sound.

Components:

1. **Microphone** — picks up sound from environment.
2. **Speech Processor** (external, worn behind the ear) — digitizes and filters sound into frequency bands; encodes into stimulation commands.
3. **Transmitter Coil** (external) — sends encoded signals transcutaneously via radiofrequency link to the internal receiver.
4. **Internal Receiver/Stimulator** (implanted under skin) — decodes RF signal, generates electrical pulses.
5. **Electrode Array** (implanted in cochlea) — 12–22 electrodes arranged tonotopically; each electrode stimulates a different frequency region of the auditory nerve.

5.2 Prosthetic Limbs

Type	Control Mechanism	Application
Passive prosthesis	Cosmetic only; no powered movement.	Upper/lower limb amputation cosmetic restoration.
Body-powered	Harness and cable system; shoulder/elbow movement activates hook or hand.	Upper limb; robust, low cost, proprioceptive feedback.
Myoelectric (EMG-controlled)	Surface EMG from residual muscles controls motor-driven hand/elbow.	Upper limb; intuitive control; electrically powered.
Microprocessor knee	Sensors and microcontroller adjust damping in real time for variable gait.	Trans-femoral (above-knee) amputation.

5.3 Other Assistive Devices

- **Visual prosthesis (Bionic eye):** Electrode array on retina or visual cortex stimulated by camera-processed signals to restore partial vision.

- **Deep Brain Stimulator (DBS):** Electrodes implanted in subthalamic nucleus; high-frequency (130–180 Hz) electrical stimulation treats Parkinson's disease tremor.
- **Functional Electrical Stimulation (FES):** External electrodes stimulate paralysed muscles in paraplegic patients for assisted hand grasp or standing.
- **Hearing Aid:** Amplifies sound; does not bypass cochlea (unlike cochlear implant). Uses Class D amplifiers; ITE (in-the-ear) or BTE (behind-the-ear) form factors.

6. Electrical Safety in Medical Environments

Importance of Electrical Safety

Medical instruments are directly connected to or in close contact with patients. Even small leakage currents that are harmless in everyday life can be lethal in medical situations where electrodes bypass skin resistance or are in contact with the heart. Electrical safety standards (IEC 60601) define acceptable limits to protect both patients and operators.

6.1 Macroshock and Microshock

Electric Shock Thresholds

Macroshock	Current entering through skin. Skin resistance ($\approx 10\text{ k}\Omega$ – $1\text{ M}\Omega$ dry) limits current.
Perception threshold	$\approx 1\text{ mA}$ (50 Hz AC).
Let-go threshold	≈ 10 – 20 mA (muscle tetany; cannot release conductor).
Ventricular fibrillation	$\approx 100\text{ mA}$ (chest surface current).
Cardiac arrest / Burns	≈ 1 – 10 A .
Microshock	Current applied directly to heart (via catheter, pacemaker leads). Skin resistance bypassed.
VF threshold (intracardiac)	As low as 10 – $50\text{ }\mu\text{A}$ (cardiac catheter, pacemaker wire).
IEC 60601 limit (patient leakage)	$\leq 10\text{ }\mu\text{A}$ (Type CF equipment connected to heart).

6.2 Sources of Leakage Current

- **Capacitive leakage:** Power line coupling through stray capacitance between mains wiring and equipment chassis.
- **Resistive leakage:** Insulation degradation due to aging, moisture, or damage.
- **Inductive leakage:** Magnetic coupling from transformers or motors.

6.3 Safety Methods and Standards

Protection Method	Description
Earth (Ground) connection	Chassis connected to protective earth; fault current diverted away from patient.
Double insulation	Two separate insulation layers between mains and chassis; no earth required.
Galvanic isolation	Patient circuit isolated from mains via transformer, optocouplers, or RF links; leakage path broken.
Right-Leg Drive (ECG)	Driven shield reduces common-mode interference; active cancellation of body surface potentials.
Equipotential bonding	All metal surfaces in the patient's area bonded to a common potential to eliminate voltage differences.
GFCI / RCD	Ground Fault Circuit Interrupter detects mains leakage $> 5 \text{ mA}$ and trips the supply.

6.4 IEC 60601 Equipment Classification

Class	Description	Max. Patient Leakage
Type B	General body contact; not directly connected to heart.	$100 \mu\text{A}$
Type BF	Floating (isolated) patient connection; body contact.	$100 \mu\text{A}$ (isolated)
Type CF	Directly connected to heart (e.g., intracardiac catheter).	$10 \mu\text{A}$

Quick Revision — Module 4

Prostheses, Therapeutic Devices and Electrical Safety | PE-EC603B

Key Formulas and Thresholds

Pacemaker rate	$\text{Rate} = 60000/\text{interval}(\text{ms})$
Defibrillator energy	$E = \frac{1}{2}CV^2 \quad (\text{J})$
Dialysis adequacy	$Kt/V \geq 1.2$ for adequate haemodialysis
Macroshock VF	$\approx 100 \text{ mA}$ (skin current, 50 Hz)
Microshock VF	$\approx 10\text{--}50 \mu\text{A}$ (intracardiac)
IEC CF leakage limit	$\leq 10 \mu\text{A}$ (direct cardiac contact)
IEC B/BF leakage limit	$\leq 100 \mu\text{A}$

One-Line Definitions

- **Pacemaker:** Implantable device delivering timed electrical pulses to maintain adequate heart rate.
- **Defibrillator:** Device delivering high-energy shock to terminate VF/VT by simultaneous depolarization of all cardiac cells.
- **AED:** Automated External Defibrillator; public-access defibrillator that analyses rhythm and advises shock delivery.
- **ICD:** Implantable Cardioverter Defibrillator; automatic implantable device sensing and treating VF/VT.
- **Heart-Lung Machine:** Cardiopulmonary bypass device replacing heart and lung function during open-heart surgery.
- **Haemodialysis:** Extracorporeal blood purification via diffusion through semipermeable membrane for renal failure.
- **Ultrafiltration:** Pressure-driven removal of water across a dialysis membrane.
- **Cochlear Implant:** Electronic device directly stimulating auditory nerve fibres to restore hearing in profound deafness.
- **Macroshock:** Dangerous electrical current entering body through skin ($> 100 \text{ mA}$ causes VF).
- **Microshock:** Tiny current ($10\text{--}50 \mu\text{A}$) directly reaching the heart via catheter/pacemaker wire; causes VF.
- **Galvanic Isolation:** Breaking the electrical connection between mains and patient circuit to eliminate leakage path.

Frequently Asked / Viva Questions

Q1. What is a cardiac pacemaker? When is it indicated?

A pacemaker is an implanted electronic device delivering controlled electrical stimuli to the heart to maintain an adequate rate. It is indicated in bradycardia, sick sinus syndrome, complete (3rd degree) AV block, and heart failure (CRT).

Q2. What are the modes of a DDD pacemaker?

DDD: first D = paces both chambers (atrium + ventricle); second D = senses both; third D = dual response (inhibited if intrinsic beat sensed, triggered if not). It maintains AV synchrony, mimicking natural conduction.

Q3. What is the difference between a pacemaker and a defibrillator?

A pacemaker delivers low-energy ($< 5\text{ V}$, $0.4\text{--}1\text{ ms}$) pulses repeatedly to sustain a minimum heart rate (treats *too slow*). A defibrillator delivers a single high-energy shock ($120\text{--}360\text{ J}$) to terminate fibrillation (treats *chaotic fast*). An ICD combines both functions.

Q4. Why are biphasic defibrillation waveforms preferred over monophasic?

Biphasic waveforms reverse polarity partway through discharge. This “tidies up” residual charge-related effects on cell membranes, achieving the same defibrillation threshold at $\approx 40\%$ lower energy, reducing post-shock myocardial injury compared to monophasic waveforms.

Q5. Explain the working of a heart-lung machine during open-heart surgery.

Venous blood is drained from the right atrium into a reservoir, passed through a membrane oxygenator (adds O_2 , removes CO_2) and a heat exchanger (induces hypothermia to reduce metabolic demand), then pumped back into the aorta. The heart is stopped with cold cardioplegia, allowing surgery on a bloodless, still field.

Q6. What is haemodialysis? Explain diffusion and ultrafiltration.

Haemodialysis removes metabolic waste from blood by passing it through a dialyser. *Diffusion*: small solutes (urea, creatinine, K^+) move down their concentration gradient across the semipermeable membrane into dialysate. *Ultrafiltration*: transmembrane pressure removes excess water from blood.

Q7. How does a cochlear implant differ from a conventional hearing aid?

A hearing aid only amplifies sound; it requires residual functional hair cells in the cochlea. A cochlear implant completely bypasses the damaged cochlea and directly stimulates auditory nerve fibres with electrical pulses, providing hearing even in profound/total deafness where no hair cells survive.

Q8. Define macroshock and microshock. Give the VF threshold for each.

Macroshock: current entering through intact skin ($> 100\text{ mA}$ at 50 Hz causes VF). Skin resistance ($10\text{ k}\Omega$ to $1\text{ M}\Omega$ dry) limits the current. *Microshock*: current reaching heart directly via catheter or pacemaker lead; VF threshold as low as $10\text{--}50\text{ }\mu\text{A}$ (skin resistance bypassed).

Frequently Asked / Viva Questions (contd.)

Q9. What is galvanic isolation and why is it essential in medical equipment?

Galvanic isolation electrically separates the patient circuit from the mains supply using a transformer, optocoupler, or RF link. Any fault current or leakage from the mains cannot reach the patient, preventing both macroshock and microshock. IEC 60601 Type CF equipment must have $\leq 10 \mu\text{A}$ patient leakage.

Q10. What is an ICD? How does it detect and treat ventricular fibrillation?

An Implantable Cardioverter Defibrillator continuously monitors the cardiac electrogram via a right ventricular lead. On detecting VF (rate > 200 bpm with disorganized waveform), it charges an internal capacitor and delivers a shock (25–40 J) within 10–20 s. It also provides anti-tachycardia pacing for slower VT to avoid a shock.

Q11. What is functional electrical stimulation (FES)?

FES applies controlled electrical pulses to surface or implanted electrodes over paralysed muscles in spinal cord injury patients. By selecting the stimulation sequence, it can activate leg muscles for assisted walking, hand muscles for grasp, or respiratory muscles for diaphragmatic pacing.

Therapeutic Device Comparison

Device	Energy Delivered	Purpose	Indication
Pacemaker	$< 5 \text{ V}, < 1 \text{ ms}$ pulses	Maintain heart rate	Bradycardia, AV block
ICD	25–40 J shock	Terminate VF/VT	VF, VT, SCD prevention
External defibrillator	120–360 J shock	Terminate VF	Cardiac arrest (VF)
CRT (BiV pacing)	Same as pacemaker	Resynchronize LV	Heart failure, LBBB
Dialysis machine	None (physical)	Remove waste, fluid	ESRD, acute renal failure
Heart-lung machine	Mechanical pump	Bypass heart/lungs	Open-heart surgery