



IVY METERING CO.,LTD

Add: Room 1206, AFC Grand Hongqiao International, No.999/1009 Li'an Rd, Minhang District,
Shanghai 201100, China Tel:86 21 62201708 Fax:86 21 62209608

读数据Read data

功能名称 Feature name	控制码 (1个字节) Control code (1 byte)	数据长度 (字节) Data length (bytes)	标识码 Identification code	数据格式 Data format	举例 For example	解析 Parse	单位 Unit
有功总电量 Active total power	0x11	4	0x00000000	XXXXXX.XX(BCD)	12 34 56 78	785634.12	Kwh
有功费率1 Active Tariff 1	0x11	4	0x00000100	XXXXXX.XX(BCD)	12 34 56 78	785634.12	Kwh
有功费率2 Active Tariff 2	0x11	4	0x00000200	XXXXXX.XX(BCD)	12 34 56 78	785634.12	Kwh
有功费率3 Active Tariff 3	0x11	4	0x00000300	XXXXXX.XX(BCD)	12 34 56 78	785634.12	Kwh
有功费率4 Active Tariff 4	0x11	4	0x00000400	XXXXXX.XX(BCD)	12 34 56 78	785634.12	Kwh
有功电量数据块 Active energy data block	0x11	4*5	0x0000FF00	XXXXXX.XX(BCD)	同上, 顺序为总、1234 Same as above, in the order of total, 1234	/	Kwh
电压 Voltage	0x11	2	0x02010100	XXX.X(BCD)	12 34	341.2	V
电流 Current	0x11	3	0x02020100	XXX.XXX(BCD)	12 34 56	563.412	A
日期及星期 Date and week	0x11	4	0x04000101	YYMMDDWW(BCD)	02 21 04 19	19-04-21星期二 19-04-21 Tuesday	/
时间 Time	0x11	3	0x04000102	hhmmss(BCD)	45 23 12	12:23:45	/
轮显时间 Scroll display time	0x11	1	0x04000302	XX(BCD)	34	34	秒 Second
序列号 Serial No.	0x11	6	0x04000401	XXXXXXXXXX(BCD)	23 43 67 89 54 27	275489674323	/
时段表 Time interval sheet	0x11	3*8	0x04010001	HHMMRR*8(BCD)	02 45 21	21:45费率2 21:45 Tariff 2	/
软件版本号 Software version No.	0x11	32	0x04800001	ASCII	/	/	/
硬件版本号 Hardware version No.	0x11	32	0x04800002	ASCII	/	/	/
过压事件记录 Overvoltage event record	0x11	12	0x50000400-0x50000413	YYMMDDhhmmssYYMMDDhhmmss	34 22 13 12 01 19 32 35 13 12 01 19	事件开始:19-01-12 13:22:34 事件恢复:19-01-12 13:35:32 Event start: 19-01-12 13:22:34 Event resumed: 19-01-12 13:35:32	/
过压阈值+过压触发时间 Overvoltage threshold + overvoltage trigger time	0x11	2+1	0x50000420	XXXX(BCD)+XX(BCD)	34 02 12	234V+12s	/
欠压事件记录 Undervoltage event record	0x11	12	0x50000500-0x50000513	YYMMDDhhmmssYYMMDDhhmmss	34 22 13 12 01 19 32 35 13 12 01 19	事件开始:19-01-12 13:22:34 事件恢复:19-01-12 13:35:32 Event start: 19-01-12 13:22:34 Event resumed: 19-01-12 13:35:32	/
欠压阈值+欠压触发时间 Undervoltage threshold + undervoltage trigger time	0x11	2+1	0x50000520	XXXX(BCD)+XX(BCD)	34 02 12	234V+12s	/
过流事件记录 Overcurrent event record	0x11	12	0x50000600-0x50000613	YYMMDDhhmmssYYMMDDhhmmss	34 22 13 12 01 19 32 35 13 12 01 19	事件开始:19-01-12 13:22:34 事件恢复:19-01-12 13:35:32 Event start: 19-01-12 13:22:34 Event resumed: 19-01-12 13:35:32	/
过流阈值+过流触发时间 Overcurrent threshold + overcurrent trigger time	0x11	2+1	0x50000620	XXXX(BCD)+XX(BCD)	34 02 12	234A+12s	/

阈值统一读取 Threshold uniform read	0x11	9	0x50000640	XXXX(BCD)	顺序为过压、欠压、过流 The sequence is overvoltage, undervoltage, overcurrent	/	/
停电事件记录 Power outage event record	0x11	12	0x50000700-0x50000713	YYMMDDhhmmssYYMMDDhhmmss	34 22 13 12 01 19 32 35 13 12 01 19	事件开始:19-01-12 13:22:34 事件恢复:19-01-12 13:35:32 Event start: 19-01-12 13:22:34 Event resumed: 19-01-12 13:35:32	/

PS:D613001不支持

D613001 not supported