

POWERBOX · CALCULATION NOTE

PowerBox sizing calculations

Open Hardware Portfolio · amishchadha.com

DOCUMENT CONTROL

Document ID	PBX-CAL-001	Version	0.1
Status	Draft	Date	2026-09-25
Author	Amish Chadha	License	CERN-OHL-S-2.0
Project TRL	TRL 3 Proof of concept		
Repository	github.com/BoujeeEnjinia1701/powerbox		
Source	docs/04-calcs/01-sizing.md @ uncommitted		

REVISION HISTORY

Version	Date	Author	Change
0.1	2026-09-25	Amish Chadha	First TRL 3 sizing note (energy, charging, converter efficiency, outputs, fuses, pre-charge, station mode, standby, wake, thermal, mass, cost) against SwapCell interface v0.3

PowerBox sizing calculations

On paper, PowerBox meets eight of its twelve requirements. **R2 is not met**: one SwapCell pack runs the reference evening 1.87 times, not twice. R6 (DC input efficiency) and R11 (budget, \$449 against \$450) are **at risk**, and R12 (swap time) cannot be verified until users try it. Two TRL 2 figures were wrong and are corrected here: the 48 V to 12 V converter was too small for the full DC output set (26.5 A needed, 20 A fitted, now 30 A), and the mass rises from about 8.3 to 8.6 kg with the SwapCell v0.3 pack and the real sheet areas. SwapCell interface v0.3 removes both TRL 2 interface blockers: PowerBox wakes the pack through its INTERLOCK loop and runs loads while charging in station mode.

Every number here is printed by `docs/04-calcs/sizing.py` (run from the repo root: `python docs/04-calcs/sizing.py`), which also writes `docs/04-calcs/results.csv`. The script reads the case dimensions from `cad/src/model.py` and the costs from `bom/bom.csv`. All values are first-principles estimates; nothing is measured.

■ 1. Assumptions

Table 1. Inputs. All are assumptions for a paper design.

Input	Value	Basis
Pack	13S2P, 46.8 V nominal, 39.0 to 54.6 V, 10 Ah, 468 Wh nameplate, 466 Wh at 0.2C (452 Wh with minimum cells), 110 mΩ, 2.85 kg, 393 mm overall	SwapCell interface v0.3, SWC-CAL-001
Pack current limits	20 A continuous, 35 A for 10 s, 15 A legacy, 5.0 A charge	SWC-PRC-001 v0.3
Charge at 5 A	CC to 85 % state of charge, then 0.6 h CV	SWC-CAL-001
Discharge window	10 to 100 % state of charge	PBX-REQ-001 R1
Cell charge efficiency	95 %	SWC-CAL-001
48 V to 12 V buck	94 %	Typical non-isolated buck
USB modules from 12 V	93 %	Typical USB-C PD and USB-A modules
Grid charger	90 %	Certified 54.6 V, 5 A unit
Charge controller loss	1.2 W fixed, 2.5 % of power, 45 mΩ on the input path, 20 mΩ on the output path	Typical 200 W synchronous buck-boost; no datasheet yet
Inverter	75 % at 20 W, 78 % at 25 W, 85 % at 60 W, 88 % at 200 to 300 W, 8 W idle, 600 W for 1 s at 85 %	Typical 48 V, 300 W pure sine units; no datasheet yet
Standby	Ready 0.6 W (ESP32 0.2, CAN and BMS awake 0.2, display 0.2); converters idle with outputs on 0.4 W; BMS sleep 100 μA; self-discharge 2.5 % per month	Typical parts; SwapCell v0.3 sleep limit
Solar	4.5 peak sun hours, 0.75 derating for heat, dust and angle	Clear day in a sunny region
Evening profile	155 Wh on 12 V, 48 Wh on USB, 5 h	PBX-REQ-001 Table 1 (203 Wh at the loads)
Heat loss from the case	9 W/(m ² K)	Still air, natural convection plus radiation
Fan	16 L/s free air, half of that through the filter and grilles	Typical 80 mm, 12 V fan
Aluminium	2,700 kg/m ³ , 1.2 mm sheet	Decided enclosure material

■ 2. Energy (R1, R2)

The pack holds 419 Wh between 10 and 100 % state of charge (407 Wh with cells at their datasheet minimum), which meets R1.

The reference evening draws 224.8 Wh from the pack: 164.9 Wh for the 12 V loads through the buck, 54.9 Wh for phone charging through the buck and USB modules, and 5.0 Wh for the host, display and idle converters over 5 h. One pack therefore gives **1.87 evenings (1.81 with minimum cells), and R2 is not met**. Two evenings need 449.6 Wh, which means discharging to 3.5 % state of charge. The TRL 2 note said a 5 % cut-off would reach 2.0 evenings;

with the SwapCell v0.3 energy of 466 Wh it reaches 1.97, so that option alone does not meet R2 either. At the 10 % cut-off the evening would have to fall to 209.7 Wh from the pack, about 189 Wh at the loads. The choice between these is open (see PBX-DDR-001).

■ 3. Charging (R3 to R6)

Sources (R3). The DC input (12 to 60 V, 200 W, MPPT), the charger input, a pack swap and SunSpoke's panel on the DC input cover all four sources. Met by design review.

Grid (R4). From 10 % the CC phase takes $(0.85 - 0.10) \times 10 \text{ Ah} / 5 \text{ A} = 1.50 \text{ h}$, then 0.6 h of CV: **2.1 h**, against 3 h. The pack takes 441 Wh at its terminals and the charger draws about 492 Wh from the wall, peaking at 303 W. Met.

Solar (R5). A 200 W panel gives $200 \times 4.5 \times 0.75 \times 0.94 = \mathbf{634 \text{ Wh per clear day}}$ at the pack terminals (603 Wh stored). A full charge from 10 % needs 441 Wh, or 3.13 peak sun hours: 0.70 of a clear day. Met. SunSpoke's 100 W panel gives 317 Wh per clear day, so one evening's energy takes 0.75 day.

DC input efficiency (R6). With the loss model in Table 1 the charge controller stays above 90 % over the whole range, but only just at a 12 V source and full power:

Table 2. Charge controller efficiency, loss model.

Input voltage	40 W	100 W	200 W
12 V	93.2 %	93.1 %	90.5 %
18 V	93.9 %	94.8 %	93.9 %
36 V	94.3 %	95.9 %	96.0 %

At 12 V and 200 W the input current is 16.7 A, and conduction loss dominates. Typical 12 V nominal panels run at 17 to 20 V at maximum power, where the margin is about 4 points. The model parameters are assumptions, and MPPT stability (no stall or hunting) cannot be analysed without the chosen converter and firmware. **R6 is at risk** until a converter datasheet is in hand.

■ 4. Station mode and wake (SwapCell interface v0.3)

Charge-discharge mode (item C). PowerBox is a SwapCell station host (host type 3) and requests mode 4 when a source and a load are both present. The worst net charge current is $200 \text{ W} \times 0.94$ into a pack at 42 V with no load: **4.48 A**, inside the pack's 5.0 A limit. On a typical clear day with the router running the net current is about 2.74 A. The grid charger delivers a fixed 5 A, so when it is connected the host limits the MPPT output to the present load current; net charge then stays at or below 5.0 A. The host sends a 5.0 A charge limit in HOST_HEARTBEAT and follows the pack's PACK_LIMITS.

Wake (item W). The PowerBox receptacle fits the $10 \text{ k}\Omega \pm 1 \%$ coding resistor in the INTERLOCK loop, so the node sits at $3.3 \times 10 / 110 = \mathbf{0.30 \text{ V}}$, inside the pack's 0.24 to 0.37 V window. Inserting a pack gives the falling edge that wakes it. To wake a pack that fell asleep in the bay, a recessed, normally closed wake button in series with the coding resistor opens the loop (node 3.3 V, which re-arms the comparator); releasing it gives a new falling edge. PowerBox needs no keep-alive cell and does not use the WAKE pin.

The pack's output is dead until it hears a heartbeat, but the PowerBox host is powered from the pack. Under the v0.3 rules a valid loop with no heartbeat for 2 s puts the pack in legacy discharge (15 A limit), which boots the host (about 1 W). The host then sends a station heartbeat. Interface v0.3 does not state whether a pack in legacy discharge accepts a heartbeat and moves to mode 2 or 4 without opening its output. PowerBox depends on that, so it is raised with SwapCell as a clarification, not changed locally.

Latch. PowerBox is not a vehicle, so the bay uses a class D catch, with the closed bay door as a second stop behind the handle. Carrying the box gives accelerations of a few g at most: about 84 N at 3 g on a 2.85 kg pack, against the 1.72 kN proof load of the pack latch.

■ 5. Outputs and pack current (R7)

With every DC output at its rating the 12 V bus must supply 120 W to the sockets plus $184 \text{ W} / 0.93 = 198 \text{ W}$ to the USB modules: **318 W, or 26.5 A**. The TRL 2 design had a 20 A (240 W) buck, which could not carry this. The buck is now **30 A (360 W)**; `bom/bom.csv` line 10 is updated.

The host limits total output to 400 W. At 300 W AC plus 100 W DC the pack supplies $341 + 106 + 1 \text{ W}$; at the 39.0 V minimum that is **11.5 A**, within the 20 A continuous rating, with 1.26 V of sag and 14.5 W of heat in the pack. A 600 W, 1 s inverter surge with 100 W of DC load draws 20.9 A, inside the 35 A, 10 s peak rating. R7 is met by design review; the RCD function depends on the inverter (section 8).

■ 6. Protection

Table 3. Fuse and breaker ratings.

Circuit	Design current	Rating
Main fuse, pack to bus	11.5 A continuous, 20.9 A for 1 s	30 A, 60 V DC or higher, 1 kA breaking
Inverter feed	8.7 A continuous, 18.1 A for 1 s	20 A DC breaker
Buck input	9.8 A at 360 W	15 A
DC input	16.7 A at 12 V, 200 W	20 A
Charge controller output	4.8 A	10 A
USB-C 100 W, USB-C 60 W, USB-A pair (12 V side)	9.0, 5.4, 2.2 A	10, 7.5, 5 A
12 V sockets	10 A	10 A

A bolted short at the pack terminals could draw about 496 A (54.6 V over 110 m Ω), so every fuse on the 48 V side needs a DC voltage rating of 60 V or more and a breaking capacity of at least 1 kA. The 10 AWG main wiring drops 23 mV over a 0.6 m loop at 11.5 A.

Pre-charge. At enable the pack pre-charges only the host and buck input capacitance (about 1,000 μF), matching the SwapCell assumption of 1,000 μF through 100 Ω (99 % in 461 ms). The inverter (about 2,200 μF) is switched in later by its own relay through a 47 Ω resistor: time constant 103 ms, 99 % in 476 ms, 3.3 J in the resistor and a peak of 1.16 A.

■ 7. Standby (R8)

Off, the pack sleeps at 100 μ A: 3.42 Wh per month, or 0.73 %, on top of about 2.5 % self-discharge, for **3.2 % per month** against 5 %. Ready (display on, outputs off) draws 0.6 W, against 1.0 W, but that is still 14.4 Wh per day, so the host returns to off after 30 min idle. With the DC outputs on and no load the draw is 1.0 W. An inverter left idling at 8 W would use 192 Wh per day, 46 % of the usable energy; the 10 min auto-off wastes 1.3 Wh per event. R8 is met.

■ 8. Back-feed and RCD (R9)

There is no AC inlet, grid charging goes through a certified charger with a DC plug, and the DC bus peaks at 54.6 V, below 60 V. R9 is met by design review. The 30 mA RCD only trips if the inverter output neutral is bonded to the case and earth pin, which requires an inverter whose output is isolated from its DC input. This is a purchasing specification (bom/bom.csv line 9) to confirm from a datasheet.

■ 9. Thermal

At full output while charging at 200 W, the case holds 41 W from the inverter, 6.4 W from the buck, 12 W from the charge controller and 1 W from the host: **60 W**. The fan moves about 8 L/s through the filter and grilles, so the air warms by about 6.2 K. On a typical evening the losses are 4.4 W; over the case's 0.556 m² at 9 W/(m² K) (UA 5.0 W/K) that is a 0.9 K rise, so the fan stays off. The pack sheds 2.75 W at 5 A of charge and 14.5 W at the 11.5 A maximum; the SwapCell thermal risk (R3 of SWC-REQ-001) applies at 20 A, well above what PowerBox draws.

■ 10. Mass and size (R10)

Table 4. Mass budget.

Part	Mass (kg)	Basis
SwapCell pack	2.85	SWC-CAL-001
Enclosure body	1.41	1.2 mm aluminium over 0.436 m ²
Lid	0.44	1.2 mm aluminium, 12 mm skirt
Handle	0.20	Estimate
Inverter	1.20	Typical 300 W unit
Bay, runners and receptacle	0.40	Estimate
Charge controller	0.30	Estimate
DC-DC converter, 30 A	0.35	Estimate
Panels, sockets and outlet	0.40	Estimate
Wiring and fuses	0.60	Estimate
Fan, host and display	0.30	Estimate
Door and hardware	0.15	Estimate
Total	8.61 (19.0 lb)	R10 limit 10 kg

The parametric model gives an overall envelope of **482 x 276 x 278 mm** (460 x 260 x 220 mm body, 12 mm lid, 46 mm handle), which meets the 500 x 300 x 280 mm limit, with 2 mm to spare in height. The pack needs 393 mm plus 22 mm for the receptacle and 8 mm of clearance: 423 mm of the 458 mm inside. The charger brick adds about 0.8 kg when carried. R10 is met.

■ 11. Cost (R11)

bom/bom.csv totals **\$449** for 18 lines, excluding the SwapCell pack, which Amish decided on 2026-09-25 is priced once in the SwapCell BOM (about \$414). The margin against the \$450 budget is \$1, and every price is indicative, so **R11 is at risk**. A household or charging point with a SwapCell dock can omit the grid charger, bringing the parts to \$399. For reference only, one PowerBox with its own pack is about \$863.

■ 12. Runtime

Table 5. Runtime on one full pack (419 Wh usable), single loads.

Load	Drawn from the pack	Runtime
Router and fibre terminal, 12 W on 12 V	12.8 W	32.9 h
Three 5 W LED bulbs on 12 V	16.0 W	26.3 h
Radio, 5 W on 12 V	5.3 W	78.8 h
Phone charge, 12 Wh on USB	13.7 Wh	31 charges
Laptop, 45 W on USB-C	51.5 W	8.1 h
Small TV, 60 W on AC	70.6 W	5.9 h
Desk fan, 25 W on AC	32.1 W	13.1 h
Maximum AC load, 300 W	340.9 W	1.2 h

Energy flow per usable cycle (DC input to loads, evening mix): 470 Wh at the DC input, 441 Wh out of the controller, 419 Wh usable, 379 Wh at the loads; losses of 28, 22 and 41 Wh.

■ 13. Results against requirements

Table 6. Requirement status (not met and at risk first).

ID	Value	Target	Status
R2	1.87 evenings (225 Wh per evening from the pack)	2 evenings	Not met
R6	90.5 % worst case (model); MPPT stability not analysed	90 % or more from 40 to 200 W; stable MPPT	At risk
R11	\$449 excluding the pack	\$450 or less	At risk
R12	Door, runners and class D catch; display reads PACK_STATUS and PACK_LIMITS	30 s swap; status display	Not verifiable at TRL 3
R1	419 Wh usable (407 Wh with minimum cells)	400 Wh or more	Met
R3	DC in 12 to 60 V 200 W MPPT; charger in; pack swap; SunSpoke panel	Four sources	Met (design review)
R4	2.1 h	3 h or less	Met
R5	634 Wh per clear day; full in 0.70 day	Full in one clear day	Met
R7	Outputs as specified; 30 A buck for 26.5 A; pack 11.5 A at 400 W	R7 output set, 400 W total	Met (design review)
R8	Off 3.2 % per month; ready 0.6 W; inverter auto-off	5 % per month; 1.0 W; auto-off	Met
R9	No AC inlet; DC bus 54.6 V; RCD needs a bonded inverter neutral	No back-feed path; 60 V or less	Met (design review)
R10	8.6 kg; 482 x 276 x 278 mm	10 kg; 500 x 300 x 280 mm	Met

■ 14. Checks against earlier documents

The TRL 2 figures in PBX-PRC-001 v0.3 were checked against this script and corrected in v0.4: usable energy 421 to 419 Wh (SwapCell v0.3 gives 466 Wh at 0.2C, not 468 Wh); evenings 1.9 to 1.87; the 5 % cut-off option 2.0 to 1.97 evenings; mass 8.3 to 8.6 kg; buck 20 A to 30 A; PowerBox parts \$435 to \$449; pack price \$370 to \$414 and with-pack cost \$805 to \$863; SunSpoke panel days per evening 0.7 to 0.75; router runtime 33 h and phone charges 30 to 31; wall energy for a grid charge 490 to 492 Wh.

Safety: These are paper estimates for a box that holds a 468 Wh lithium-ion pack able to deliver about 500 A into a short, and a 230 V AC outlet. They do not replace protection design review, datasheet checks or testing. Nothing may be built or energized from this note; building and testing are TRL 4 work and on hold by Amish's instruction.