



LS350 SPICE Simulation Model

This document provides the SPICE simulation model for the Linear Systems LS350 Monolithic Dual PNP Transistor for use in SPICE-compatible circuit simulators.

Document Information

Device	LS350
Document	SPICE Simulation Model
Revision	Rev. 2
Release Date	July 27, 2026
Manufacturer	Linear Systems

SPICE Model

```
.model LS350 (PNP IS=3.82645e-15 XTI=3 EG=1.17 VAF=37.2934 BF=500 NE=1.45387 ISE=1.4506e-15 NR=1  
IKF=0.03 XTB=1.5 BR=0.637555 IKR=0.000489083 VAR=20 IsC=1e-18 NC=1.9 RB=200 RE=0.909091 RC=231.405  
CJC=2.5286e-12 CJE=1.9932e-12 MJC=0.1795208 MJE=0.2174719 VJC=0.4 VJE=0.6034061 TF=7.255581E-10  
TR=1e-08 VTF=5 XTF=2.04 RBM=10 IRB=1e-05 PTF=20 FC=0.5 ITF=0.018 mfg=Linear_Systems)
```

Legal Notice

The **LS350** SPICE simulation model is provided to assist circuit simulation and design evaluation. While representative of typical device behavior, simulation results should be verified in the intended application. For technical assistance, contact support@linearsystems.com.