

Electrical Pinout of the Wiper Stalk on the Audi A6 4F

Wires in Stalk:

rot
gelb
grün

Connector:

1	red
2	yellow
3	green
4	no PIN
5	nc
6	nc

Resistor Network for the Buttons:

Red
Green

Resistor Network for the Rotary Switch:

Red
Yellow

Button Presses & Measured Resistances:

Function	Wires	Resistance
Reset	Red-Green	330 Ohms
Up	Red-Green	1.0 kOhm
Down	Red-Green	2.5 kOhm
Step 1 (bottom)	Red-Yellow	330 Ohms
Step 2	Red-Yellow	1.0 kOhm
Step 3	Red-Yellow	2.5 kOhm
Step 4 (top)	Red-Yellow	8.7 kOhm

ADC Input Voltages with a 3.3 kΩ Series Resistor / Voltage Divider:

Function	Wires	Voltage (V)
Reset	Red-Green	0.298 V
Up	Red-Green	0.773 V
Down	Red-Green	1.422 V
Step 1 (bottom)	Red-Yellow	0.307 V
Step 2	Red-Yellow	0.779 V
Step 3	Red-Yellow	1.429 V
Step 4 (top)	Red-Yellow	2.391 V