

First Name:
Last Name: Answer

School of Computer Science
CS 2614: Computer Organization
Spring 2025
Quiz -3

Q.1 Simplify the following expression using Boolean algebra:

$$A'BC + AB'C + ABC' + ABC$$

$$A'BC + AD'C + ABC' + ABC + ABC + ABC$$

$$(A'BC + ABC) + (AB'C + ABC) + (ABC' + ABC)$$

$$BC(A' + A) + AC(B' + B) + AB(C' + C)$$

$$BC + AC + AB$$

Q.2 Construct a logic diagram for the following Boolean expression:

$$AB + BC(B + C)$$

