FEMALE BASE v2 / CONTINUOUS WIRING

Revision D reading copy | Same circuit and physical pin numbers | No label-based connections

Shared supply rails

J7 / RACK

DA-15 connector

Pins grouped by function

DXL DATA

12 V

+5 V

GND

Shell / pad 0

PHOTOSENSOR

Unused

MICROPHONE

NEOPIXEL DATA

LINE IN

AUDIO RETURN

C1 220uF / 10V SMD

C2 100nF

Local amplifier decoupling: C1 value provisional

All crossing wires without a dot are separate.

Dots mark electrical joins: X marks an unused pin.

J2
MIRROR SERVO

DATA

12V

GND

J4
PHOTOSENSOR

OUT

5V

GND

J3
MICROPHONE

OUT

5V

GND

J5
NEOPIXELS

DATA

5V

GND

LOCAL AUDIO AMPLIFIER

R1 22K

R2 3K3

M1 / GF1002

1 x 11 plug-in socket

5 V ONLY

R_IN

INPUT_G

VDD

SUPPLY_GND

ROUT_P_VERIFY

ROUT_N_VERIFY

L_IN_NC

GAP_NC

GAP_NC

LOUT_A_NC

LOUT_B_NC

M1 unused: 3 = L input; 4/7 = gaps; 8/9 = L outputs.

J6 / SPEAKER

ROUT+ / verify

ROUT- / verify

Neither output goes to GND.

AUDIO_RETURN and GND stay separate on this PCB.

Confirm their expected bond inside the actual module.

Insulating module supports / nominal 11 mm

H1

H2

Rack J7.12/J7.4 must supply line-level audio / return; disconnect the old remote speaker output first.

Reading copy — existing circuit unchanged; see comparison.md

Colloquy of Mobiles

Sheet: /

File: female-base-v2-wired.kicad_sch

Title: Female base v2 / continuous wiring / revision D

Size: A3	Date: 2026-10-20	**Rev: D wired**
KiCad E.D.A. 9.0.7		Id: 1/1