MICROPHONE FLEX / WIRED SCHEMATIC

Rev C reading copy | Continuous wires | Fit ONE MAX9814 module only

JP1 GAIN: 1–2 = 50dB / 2–3 = 40dB / no shunt = 60dB

JP2 A/R: 1–2 = 1:500 / 2–3 = 1:2000 / no shunt = 1:4000

Initial shunts: JP1 2–3; JP2 1–2. Power off before changing.

01 HARNESS & FILTER

02 THREE ALTERNATIVE SOCKETS — SHARED SIGNALS

M1
UP / vertical
Vdd
Gain
AR
Out
GND

J2
LEFT / right angle
VDD
GAIN
AR
MICOUT
GND

J3
RIGHT / right angle
VDD
GAIN
AR
MICOUT
GND

J1
+5V_IN
AUDIO_OUT
GND

33R / supply filter
R4

JP1
VDD
GAIN
GND

JP2
VDD
AR
GND

470R / output
R5

VDD
GAIN
AR
MICOUT
GND

03 POWER INDICATOR

R6
2K2
D1
GREEN LED

04 DECOUPLING

C7
22uF / 10V X5R
C6
100nF

TP1
MICOUT
TP2
GND

Dots join wires. Crossings without dots are separate. Pins are arranged by signal; numbers match the PCB.

Mounting only:

H1 H2 H3 H4 H5 H6 H7 H8

H1/H2: M5 slots | H3/H4: top M2 | H5–H8: side M2

Electrical reading copy — original PCB and schematic retained
Colloquy of Mobiles
Sheet: /
File: microphone-flex-wired.kicad_sch

Title: Microphone flex — continuous wiring

Size: A3	Date: 2026-10-20	**Rev: C-J wired**
KiCad E.D.A. 9.0.7		Id: 1/1