FEMALE BASE v2 / CONTINUOUS WIRING

Revision D reading copy | Same circuit and physical pin numbers | No label-based connections

Shared supply rails

J7 / RACK

DA-15 connector

Pins grouped by function

DXL DATA — 14

12 V — 7

+5 V — 15

GND — 8

Shell / pad 0 — 0

PHOTOSENSOR — 5

MICROPHONE — 6

NEOPIXEL DATA — 13

LINE IN — 12

AUDIO RETURN — 4

Unused: 1, 2, 3, 9, 10, 11

C1 220uF / 10V SMD

C2 100nF

Local amplifier decoupling: C1 value provisional

All crossing wires without a dot are separate.

Dots mark electrical joins: X marks an unused pin.

J2 MIRROR SERVO

DATA — 3

12V — 2

GND — 1

J4 PHOTOSENSOR

OUT — 3

5V — 2

GND — 1

J3 MICROPHONE

OUT — 3

5V — 2

GND — 1

J5 NEOPIXELS

DATA — 3

5V — 2

GND — 1

LOCAL AUDIO AMPLIFIER

R1 22K

R2 3K3

M1 / GF1002

1 x 11 plug-in socket

5 V ONLY

VDD — 5

SUPPLY_GND — 6

R_IN — 1

INPUT_G — 2

L_IN_NC — 3

GAP_NC — 4

GAP_NC — 7

LOUT_A_NC — 8

LOUT_B_NC — 9

ROUT_P_VERIFY — 10

ROUT_N_VERIFY — 11

M1 unused: 3 = L input; 4/7 = gaps; 8/9 = L outputs.

J6 / SPEAKER

ROUT+ / verify — 1

ROUT- / verify — 2

Neither output goes to GND.

AUDIO_RETURN and GND stay separate on this PCB.

Confirm their expected bond inside the actual module.

Rack J7.12/J7.4 must supply line-level audio / return; disconnect the old remote speaker output first.

Reading copy — existing circuit unchanged; see comparison.md

Colloquy of Mobiles

Sheet: /

File: female-base-v2-wired.kicad_sch

Title: Female base v2 / continuous wiring / revision D

Size: A3	Date: 2026-10-21	**Rev: D wired**
KiCad E.D.A. 9.0.7		Id: 1/1