

Interfaces Quiz

What is the output?

```
type Speaker interface {  
    Speak() string  
}  
type Dog struct{}  
  
func (d *Dog) Speak() string {  
    return "Woof"  
}  
  
func main() {  
    var s Speaker = Dog{}  
    fmt.Println(s.Speak())  
}
```

Compilation Error: cannot use Dog{} (value of type Dog) as Speaker value in variable declaration: Dog does not implement Speaker (method Speak has pointer receiver)

Correct it by use: -

var s Speaker = &Dog{}

```
func main() {  
    var a interface{} = int32(5)  
    var b interface{} = int64(5)  
    fmt.Println(a == b)  
}
```

False

• هنا النوع الأول int32 والثاني int64 ورغم أن القيمة في الاثنين هي 5 لكن اختلاف الأنواع بتخلي الناتج false.

```
func main() {  
    var a interface{} = []int{1, 2, 3}  
    var b interface{} = []int{1, 2, 3}  
    fmt.Println(a == b)  
}
```

panic: runtime error: comparing uncomparable type []int

الـ Slices غير قابلة للمقارنة المباشرة باستخدام علامة ==
الا اذا ساوينا الحجم

```
var a interface{} = [3]int{1, 2, 3}  
var b interface{} = [3]int{1, 2, 3}
```