今日作业:

一、跟着飞书笔记完成触发器 insert 实验.

```
mysql> CREATE TABLE shops(
    -> id int UNSIGNED  auto_increment PRIMARY KEY,
    -> name VA
VALUE         VAR_POP       VARBINARY     VARCHARACTER VARIANCE
VALUES        VAR_SAMP      VARCHAR       VARIABLES    VARYING
    -> name VARCHAR(50),
    -> stock int UNSIGNED not null
    -> );
Query OK, 0 rows affected (0.03 sec)

mysql> INSE
INSENSITIVE   INSERT        INSERT_METHOD
mysql> INSERT
INSERT        INSERT_METHOD
mysql> INSERT INTO shops(name,stock) VALUES ('MySQL核心技术指南',10);
Query OK, 1 row affected (0.01 sec)
```

```
mysql> CREATE TABLE orders(
    -> id int UNSIGNED AUTO_INCREMENT
Display all 756 possibilities? (y or n)
    -> id int UNSIGNED AUTO_INCREMENT PRIMARY KEY,
    -> code VARCHAR(100) not null,
    -> shops_id int UNSIGNED NOT NULL,
    -> number int UNSIGNED not null,
    -> time int UNSIGNED not null);
Query OK, 0 rows affected (0.02 sec)
```

```
mysql> CREATE TRIGGER tr_after_insert_order
    -> AFTER INSERT ON orders
    -> FOR EACH ROW
    -> BEGIN
    ->     UPDATE shops
    ->     SET stock = stock - NEW.number
    ->     WHERE id = NEW.shops_id;
    -> END //
Query OK, 0 rows affected (0.01 sec)

mysql> DELIMITER ;
mysql> INSERT INTO orders (code, shops_id, number, time) VALUES ('a123456', 1, 5, unix_times
tamp());
Query OK, 1 row affected (0.00 sec)
```

```
mysql> SELECT * FROM shops;
+----+--------------------------+-------+
| id | name                     | stock |
+----+--------------------------+-------+
|  1 | MySQL核心技术指南        |     5 |
+----+--------------------------+-------+
1 row in set (0.00 sec)
```

```
mysql> SELECT * FROM orders;
+----+---------+----------+--------+------------+
| id | code    | shops_id | number | time       |
+----+---------+----------+--------+------------+
|  1 | a123456 |        1 |      5 | 1791979686 |
+----+---------+----------+--------+------------+
1 row in set (0.00 sec)
```

二、自己完成触发器 update 实验，包括完整实验图文.

```
mysql> DELIMITER //
mysql> CREATE TRIGGER tr_before_update_order
    -> BEFORE UPDATE ON orders
    -> FOR EACH ROW
    -> BEGIN
    ->     UPDATE shops SET stock = stock + OLD.number WHERE id = OLD.shops_id;
    ->     UPDATE shops SET stock = stock - NEW.number WHERE id = NEW.shops_id;
    -> END //
Query OK, 0 rows affected (0.02 sec)

mysql> DELIMITER ;
mysql> UPDATE orders SET number = 6 WHERE code = 'a123456';
Query OK, 1 row affected (0.00 sec)
Rows matched: 1  Changed: 1  Warnings: 0

mysql> SELECT * FROM orders;
+----+---------+----------+--------+------------+
| id | code    | shops_id | number | time       |
+----+---------+----------+--------+------------+
|  1 | a123456 |        1 |      6 | 1791979686 |
+----+---------+----------+--------+------------+
1 row in set (0.00 sec)

mysql> SELECT * FROM shops;
+----+-------------------------+-------+
| id | name                    | stock |
+----+-------------------------+-------+
|  1 | MySQL核心技术指南       |     4 |
+----+-------------------------+-------+
1 row in set (0.00 sec)
```

三、自己完成触发器 delete 实验，包括完整实验图文.

```
mysql> DELIMITER //
mysql> CREATE TRIGGER tr_after_delete_order
    -> AFTER DELETE ON orders
    -> FOR EACH ROW
    -> BEGIN
    ->
Display all 756 possibilities? (y or n)
    -> UPDATE shops SET stock = stock + OLD.number WHERE id = OLD.shops_id;
    -> END //
Query OK, 0 rows affected (0.01 sec)

mysql> DELIMITER ;
```

```
mysql> DELETE FROM orders WHERE code = 'a123456';
Query OK, 1 row affected (0.00 sec)

mysql> SELECT * FROM oredrs;
ERROR 1146 (42S02): Table 'mydb.oredrs' doesn't exist
mysql> SELECT * FROM orders;
Empty set (0.01 sec)

mysql> SELECT * FROM shops;;
+----+-------------------------+-------+
| id | name                    | stock |
+----+-------------------------+-------+
|  1 | MySQL核心技术指南       |    10 |
+----+-------------------------+-------+
1 row in set (0.00 sec)
```