

The following three 'C' language statements is equivalent to which single statement? $y=y+1$; $z=x+y$; $x=x+1$

- (A) $z = x + y + 2$;
- (B) $z = (x++) + (++y)$;
- (C) $z = (x++) + (y++)$;
- (D) $z = (x++) + (++y) + 1$;

Predict the output of following program?

```
#include <stdio.h>
```



```
int main() {  
    int x = 10;  
    int y = 20;  
    x += (y += 10);  
    printf("%d %d", x, y);  
    return 0;  
}
```

(A) 40 20

(B) 40 30

(C) 30 30

(D) 30 40

```
#include <stdio.h>
int main()
{
    int i = 3;
    printf("%d", (++i)++);
    return 0;
}
```



What is the output of the above program?

- ☐ (A) 3
- ☐ (B) 4
- ☐ (C) 5
- ☐ (D) Compile-time error

Output of following C code will be?

```
#include <stdio.h>
```



```
int main() {  
    int x = 10;  
    int y = (x++, x++, x++);  
    printf("%d %d\n", x, y);  
    return 0;  
}
```

- (A) 13 12
- (B) 13 13
- (C) 10 10
- (D) Compiler Dependent

Which of the following is not a logical operator?

(A) &&

(B) !

(C) ||

(D) |

```
#include <stdio.h>
int main()
{
    int i = 5, j = 10, k = 15;
    printf("%d ", sizeof(k /=
i + j));
    printf("%d", k);
    return 0;
}
```

Assume size of an integer as 4 bytes.
What is the output of above program?

- (A) 4 1
- (B) 4 15
- (C) 2 1
- (D) Compile-time error

```
#include<stdio.h>
int main(void)
{
    int a = 1;
    int b = 0;
    b = a++ + a++;
    printf("%d %d",a,b);
    return 0;
}
```



- (A) 3 6
- (B) Compiler Dependent
- (C) 3 4
- (D) 3 3

What is the output of following program?

```
#include <stdio.h>

int main()
{
    int a = 1;
    int b = 1;
    int c = a || --b;
    int d = a-- && --b;
    printf("a = %d, b = %d, c = %d, d = %d", a, b, c, d);
    return 0;
}
```

- (A) a = 0, b = 1, c = 1, d = 0
- (B) a = 0, b = 0, c = 1, d = 0
- (C) a = 1, b = 1, c = 1, d = 1
- (D) a = 0, b = 0, c = 0, d = 0

Output of following C code will be?

```
#include <stdio.h>

int main() {
    int y = 0;
    int x = (y != 0);
    printf("%d", x);
    return 0;
}
```

- (A) 0
- (B) 1
- (C) A bog negative Number
- (D) Compiler Error