www.tntextbooks.in

Electrical energy = power × time of usage = P × t

$= 75 \text{ watt} \times 240 \text{ hour}$

$= 18000 \text{ watt hour}$

$= 18 \text{ kilowatt hour} = 18 \text{ kWh}$

1 electrical unit = 1 kWh

Electrical energy = 18 unit



Incandescent lamps glow for 1000 hours. CFL lamps glow for 6000 hours. But LED lamps glow for 50000 hrs (almost 25 years at 5.5 hour per day).

4.3.3 Relation between power and velocity

The work done by a force $\vec{F}$ for a displacement $d\vec{r}$ is

$$W = \int \vec{F} \cdot d\vec{r} \qquad (4.40)$$

Left hand side of the equation (4.40) can be written as

$$W = \int dW = \int \frac{dW}{dt} dt$$

(multiplied and divided by dt) (4.41)

Since, velocity is $\vec{v} = \frac{d\vec{r}}{dt}$; $d\vec{r} = \vec{v}\, dt$. Right hand side of the equation (4.40) can be written as

$$\int \vec{F} \cdot d\vec{r} = \int \left(\vec{F} \cdot \frac{d\vec{r}}{dt} \right) dt = \int \left(\vec{F} \cdot \vec{v} \right) dt \quad \left[\vec{v} = \frac{d\vec{r}}{dt} \right] \qquad (4.42)$$

Substituting equation (4.41) and equation (4.42) in equation (4.40), we get

$$\int \frac{dW}{dt} dt = \int \left(\vec{F} \cdot \vec{v} \right) dt$$

$$\int \left(\frac{dW}{dt} - \vec{F} \cdot \vec{v} \right) dt = 0$$

This relation is true for any arbitrary value of dt. This implies that the term within the bracket must be equal to zero, i.e.,

$$\frac{dW}{dt} - \vec{F} \cdot \vec{v} = 0$$

Or

$$\frac{dW}{dt} = \vec{F} \cdot \vec{v} \qquad (4.43)$$

EXAMPLE 4.19

A vehicle of mass 1250 kg is driven with an acceleration 0.2 m s^{-2} along a straight level road against an external resistive force 500 N. Calculate the power delivered by the vehicle's engine if the velocity of the vehicle is 30 $\text{m } s^{-1}$.

Solution

The vehicle's engine has to do work against resistive force and make vechile to move with an acceleration. Therefore, power delivered by the vehicle engine is

P = (resistive force + mass × acceleration) (velocity)

$P = \vec{F}_{-\text{tot}} \vec{v} = (F_{\text{resistive}} + F)\vec{v}$

$P = \vec{F}_{\text{tot}} \cdot \vec{v} = (F_{\text{resistive}} + ma)\vec{v}$

$= (500 \text{ N} + (1250 \text{ kg}) \times (0.2\ ms^{-2}))$ $(30 \text{ ms}^{-1}) = 22.5 \text{ kW}$