Table 4.2 Energy in two oscillatory systems

LC oscillator		Spring-mass system	
Element	**Energy**	**Element**	**Energy**
Capacitor	Electrical Energy = $\frac{1}{2}\left(\frac{1}{C}\right)q^2$	Spring	Potential energy = $\frac{1}{2}kx^2$
Inductor	Magnetic energy = $\frac{1}{2}Li^2$ $i=\frac{dq}{dt}$	Mass	Kinetic energy = $\frac{1}{2}mv^2$ $v=\frac{dx}{dt}$

Likewise, the mechanical energy of the spring-mass system exists in two forms; the potential energy of the compressed or extended spring and the kinetic energy of the mass. The Table 4.2 lists these two pairs of energy.

By examining the Table 4.2, the analogies between the various quantities can be understood and these correspondences are given in Table 4.3.

The angular frequency of oscillations of a spring-mass is given by (Refer equation 10.22 of section 10.4.1 of XI physics text book).

$$\omega=\sqrt{\frac{k}{m}}$$

From Table 4.3, $k \rightarrow 1/C$ and $m \rightarrow L$. Therefore, the angular frequency of LC oscillations is given by

$$\omega=\frac{1}{\sqrt{LC}} \qquad (4.59)$$

Table 4.3 Analogies between electrical and mechanical quantities

Electrical system	Mechanical system
Charge q	Displacement x
Current $i=\frac{dq}{dt}$	Velocity $v=\frac{dx}{dt}$
Inductance L	Mass m
Reciprocal of capacitance $\frac{1}{C}$	Force constant k
Electrical energy $=\frac{1}{2}\left(\frac{1}{C}\right)q^2$	Potential energy $=\frac{1}{2}kx^2$
Magnetic energy $=\frac{1}{2}Li^2$	Kinetic energy $=\frac{1}{2}mv^2$
Electromagnetic energy $U=\frac{1}{2}\left(\frac{1}{C}\right)q^2+\frac{1}{2}Li^2$	Mechanical energy $E=\frac{1}{2}kx^2+\frac{1}{2}mv^2$

12th Physics_Vol-1_Unit 4_English Medium.indd 254 23-12-2022 17:59:17