Since electric field is normal to the surface of the conductor, the curved part of the cylinder has zero electric flux. Also inside the conductor, the electric field is zero. Hence the bottom flat part of the Gaussian surface has no electric flux.

Therefore the top flat surface alone contributes to the electric flux. The electric field is parallel to the area vector and the total charge inside the surface is σA. By applying Gaus's law,

$$EA = \frac{\sigma A}{\varepsilon_0}$$

In vector form, $$\vec{E} = \frac{\sigma}{\varepsilon_0}\hat{n} \qquad (1.79)$$

Here $\hat{n}$ represents the unit vector outward normal to the surface of the conductor. Suppose σ < 0, then electric field points inward perpendicular to the surface.

(iv) The electrostatic potential has the same value on the surface and inside of the conductor.

We know that the conductor has no parallel electric component on the surface which means that charges can be moved on the surface without doing any work. This is possible only if the electrostatic potential is constant at all points on the surface and there is no potential difference between any two points on the surface.

Since the electric field is zero inside the conductor, the potential is the same as the surface of the conductor. Thus at electrostatic equilibrium, the conductor is always at equipotential.

1.7.2 Electrostatic shielding

Using Gauss law, we proved that the electric field inside the charged spherical shell is zero, Further, we showed that the electric field inside both hollow and solid conductors is zero. It is a very interesting property which has an important consequence.

Consider a cavity inside the conductor as shown in Figure 1.48 (a). Whatever the charges at the surfaces and whatever the electrical disturbances outside, the electric field inside the cavity is zero. A sensitive electrical instrument which is to be protected from external electrical disturbance is kept inside this cavity. This is called electrostatic shielding.

Faraday cage is an instrument used to demonstrate this effect. It is made up of metal bars configured as shown in Figure1.48 (b). If an artificial lightning jolt is created outside, the person inside is not affected.

IENFYM




Figure 1.48 (a) Electric field inside the cavity (b) Faraday cage

UNIT-1(XII-Physics_Vol-1).indd 50 04-03-2019 10:26:19