- Ampère's circuital law is $\oint_C \vec{B} \cdot d\vec{l} = \mu_\circ I_{enclosed}$.
- Magnetic field inside the solenoid is $B = \mu_\circ nI$, where n is the number of turns per unit length.
- Magnetic field interior to the toroid is $B = \mu_\circ nI$, where n is the number of turns per unit length.
- Lorentz force is $\vec{F} = q\left(\vec{E} + \vec{v} \times \vec{B}\right)$.
- Charged particle moving in a uniform magnetic field will undergo circular motion.
- Fleming's Left Hand Rule: Stretch forefinger, the middle finger and the thumb of the left hand such that they are in mutually perpendicular directions. If we keep the forefinger in the direction of magnetic field, the middle finger in the direction of the electric current, then the thumb points in the direction the force experienced by the conductors.
- One ampere is defined as that current when it is passed through each of the two infinitely long parallel straight conductors kept at a distance of one meter apart in vacuum causes each conductor to experience a force of 2×10^{-7} newton per meter length of the conductor.
- When a current carrying coil is placed in a uniform magnetic field, the net force on it is always zero but net torque is not zero. The magnitude of net torque is τ = NABI sin θ.
- Moving coil galvanometer is an instrument used for the detection and measurement of small currents.
- In moving coil galvanometer, current passing through the galvanometer is directly proportional to the deflection. Mathematically, I = Gθ, where $G = \frac{K}{NAB}$ is called galvanometer constant or current reduction factor of the galvanometer.
- Current sensitivity is defined as the deflection produced per unit current flowing through it, $I_s = \frac{\theta}{I} = \frac{NAB}{K} \Rightarrow I_s = \frac{1}{G}$.
- Voltage sensitivity is defined as the deflection produced per unit voltage which is applied across it, $V_s = \frac{\theta}{V} = \frac{1}{GR_g} = \frac{I_S}{R_g}$, where, R_g is the resistance of galvanometer.
- Ammeter is an instrument used to measure current in an electrical circuit.
- A galvanometer can be converted into an ammeter of given range by connecting a suitable low resistance S called shunt in parallel to the given galvanometer.
- An ideal ammeter has zero resistance.
- Voltmeter is an instrument used to measure potential difference across any element in an electrical circuit.
- A galvanometer can be converted into suitable voltmeter of given range by connecting a suitable resistance R in series with the given galvanometer.
- An ideal voltmeter has infinite resistance.

UNIT-3(XII-Physics_Vol-1).indd 197 04-03-2019 10:35:59