

EMFS and Circuits

Elias Xu

April 23, 2025

Contents

1	Introduction	1
2	Forces	1
2.1	Lorentz Force	1
2.2	Currents and Torques of Wires	2
3	Law of BS	2
4	Ampere's Law	2
5	Magnetic Flux	2
6	Forces on Parallel Currents	2
6.1	On Two Wires	2
6.2	Wrapped Wires	2

1 Introduction

The test will have the following topics:

- Forces on Parallel Currents
- Toroids and Solenoids
- Magnetic Fields of Moving Charge Particles
- Law of BS
- Current and Torques on Charge Carrying Wires
- Magnetic Forces and Magnet Fundamentals
- Right Hand Rule (RHR)

2 Forces

2.1 Lorentz Force

Forces from a moving particles (Lorentz Forces). Bend $\vec{v}$ into $\vec{b}$ to get the direction for $\vec{F}_B$

$$\vec{F}_B = q(\vec{v} \times \vec{b})$$

Objects moving in a circle.

- $\vec{F}_B = \vec{F}_C$
- $r = \frac{mv}{qb}$
- Pitch: Distance parallel to the magnetic field
- Period of Orbit $v = \frac{2\pi r}{T}$; $T = \frac{2\pi r}{v}$

2.2 Currents and Torques of Wires

$\vec{L}$ is in direction of the current. Field wraps around a wire (RHR it).

$$F_b = i|\vec{L} \times \vec{B}|$$

Torque in a wire loop (probably derivable), with a and b being width and height respectively:

$$\tau = ib(\text{area of loop})$$

3 Law of BS

$$\delta\vec{B} = \frac{\mu_0}{4\pi} \frac{i\delta\vec{L} \times \hat{r}}{r^2}$$

Where $\delta\vec{L}$ is the vectorized length of wire, $\hat{r}$ is the unit vector from $\delta\vec{L}$ to point, and r is the distance from the point to the wire. Field of a wire on a point:

$$\vec{B} = \frac{\mu_0 i}{2\pi R}$$

Field of an enclosed wire loop:

$$\vec{B} = \frac{\mu_0}{2R}$$

4 Ampere's Law

$$\oint \vec{B} \cdot d\vec{s} = \mu_0 i_{\text{enc}}$$

Amperian Loop: draw a path around an object that mimics the symmetry of the emitter.

5 Magnetic Flux

NOTE: Be able to find flux from relate to velocity, change in area, work, and other forces

1. (Law of Flux) The voltage induced in a coil is equal to negative of the rate of change of magnetic flux through a coil
($\epsilon = -N \frac{\delta\Phi}{\delta t} = -N \frac{\int B \delta A}{t}$)
2. (Lenz's Law) An induced current has a direction such that the magnetic field due to the current opposes the change in the magnetic flux that induces the current.

6 Forces on Parallel Currents

6.1 On Two Wires

$$\left| \frac{F}{L} \right| = \frac{\mu_0 i_1 i_2}{2\pi d}$$

6.2 Wrapped Wires

1. Solenoid: $B = \mu_0 i n$, where the direction is through the solenoid
2. Toroids: $B = \frac{\mu_0 n i}{2\pi r}$