

J2:

Q2Q1/Q0X	00	01	11	10
00	1	0	0	1
01	1	0	0	1
11	0	0	0	0
10	0	0	0	0

$$J2 = (\text{NOT } Q2) \text{ AND } (\text{NOT } X);$$

K2:

Q2Q1/Q0X	00	01	11	10
00	0	0	0	0
01	0	0	0	0
11	1	0	0	1
10	1	0	0	1

$$K2 = Q2 \text{ AND } (\text{NOT } X);$$

J1:

Q2Q1/Q0X	00	01	11	10
00	0	0	1	0
01	0	0	0	0
11	0	0	0	0
10	0	0	1	0

$$J1 = (\text{NOT } Q1) \text{ AND } Q0 \text{ AND } X$$

K1:

Q2Q1/Q0X	00	01	11	10
00	0	0	0	0
01	0	0	1	0
11	0	0	1	0
10	0	0	0	0

$$K1 = Q1 \text{ AND } Q0 \text{ AND } X$$

J0:

Q2Q1/Q0X	00	01	11	10
00	0	1	0	0
01	0	1	0	0
11	0	1	0	0
10	0	1	0	0

$$J0 = (\text{NOT } Q0) \text{ AND } X$$

K0:

Q2Q1/Q0X	00	01	11	10
00	0	0	1	0
01	0	0	1	0
11	0	0	1	0
10	0	0	1	0

$$K0 = Q0 \text{ AND } X$$

Z(MOORE):

Q2Q1/Q0X	00	01	11	10
00	0	0	0	0
01	0	0	0	0
11	0	0	0	0
10	1	1	0	0

$$Z = Q2 \text{ AND } (\text{NOT } Q1) \text{ AND } (\text{NOT } Q0)$$

Z(MEALY):

Q2Q1/Q0X	00	01	11	10
00	1	0	0	0
01	0	0	0	0
11	0	0	1	0
10	0	0	0	0

$$Z = ((\text{NOT } Q2) \text{ AND } (\text{NOT } Q1) \text{ AND } (\text{NOT } Q0) \text{ AND } (\text{NOT } X)) \text{ or } (Q2 \text{ AND } Q1 \text{ AND } Q0 \text{ AND } X)$$