

J2:

Q2Q1/Q0X	00	01	11	10
00	1	0	0	1
01	1	0	0	1
11	X	X	X	X
10	X	X	X	X

J2 = (NOT X);**K2:**

Q2Q1/Q0X	00	01	11	10
00	X	X	X	X
01	X	X	X	X
11	1	0	0	1
10	1	0	0	1

K2 = (NOT X);**J1:**

Q2Q1/Q0X	00	01	11	10
00	0	0	1	0
01	X	X	X	X
11	X	X	X	X
10	0	0	1	0

J1 = Q0 AND X

K1:

Q2Q1/Q0X	00	01	11	10
00	X	X	X	X
01	0	0	1	0
11	0	0	1	0
10	X	X	X	X

K1 = Q0 AND X**J0:**

Q2Q1/Q0X	00	01	11	10
00	0	1	X	X
01	0	1	X	X
11	0	1	X	X
10	0	1	X	X

J0 = X**K0:**

Q2Q1/Q0X	00	01	11	10
00	X	X	1	0
01	X	X	1	0
11	X	X	1	0
10	X	X	1	0

K0 = X

Z(MOORE):

Q2Q1/Q0X	00	01	11	10
00	0	0	0	0
01	0	0	0	0
11	0	0	0	0
10	1	1	0	0

$$Z = Q2 \text{ AND } (\text{NOT } Q1) \text{ AND } (\text{NOT } Q0)$$

Z(MEALY):

Q2Q1/Q0X	00	01	11	10
00	1	0	0	0
01	0	0	0	0
11	0	0	1	0
10	0	0	0	0

$$Z = ((\text{NOT } Q2) \text{ AND } (\text{NOT } Q1) \text{ AND } (\text{NOT } Q0) \text{ AND } (\text{NOT } X)) \text{ or } (Q2 \text{ AND } Q1 \text{ AND } Q0 \text{ AND } X)$$