# BR-6208  BRIDGE RECTIFIER  (INVENTED PART)

| | |
|---|---|
| Maximum repetitive reverse voltage | **600 V** |
| Average forward rectified current | **8.0 A** |
| Forward voltage per diode at 4 A | **1.05 V typical** |
| Peak forward surge, one cycle | **200 A** |
| Operating junction temperature | **-55 to +150 C** |
| Thermal resistance, junction to case | **1.9 C/W** |
| Package | **KBPC, chassis mount** |

Fictional device. Values are internally consistent and describe no real part.

# BR-6208  SELECTION NOTES

| | |
|---|---|
| Derate average current above | **60 C case** |
| Recommended heatsink above 4 A | **Yes - chassis mount** |
| Peak charging current, 10000 uF | **Approx 5x average** |
| Reverse leakage at rated V, 25 C | **5 uA typical** |
| Reverse leakage at rated V, 125 C | **500 uA typical** |
| Minimum PIV for 24 V RMS input | **68 V - choose 200 V or better** |
| Bridge drop in the supply budget | **Allow 1.4 V** |

Choose PIV against the peak, never the RMS. The margin is the point.