

**BRAC University (Department of Computer Science and Engineering) CSE
340(Computer Architecture) Spring**

2026

**Assignment – 3
Marks – 15**

1. 8
Consider $X = (9.321)_{10}$ and $Y = (3.325)_{10}$. Perform $X * Y$ using IEEE754 single precision floating point representation. Your answer should show all the detailed steps.
Note: Consider 4 digits after the floating point while converting from decimal to binary.

2. 7
Subtract -7.0110 from 18.7110 using IEEE-754 single-precision floating-point representation. Check if the result has overflow or underflow.
Note: Consider 4 decimal digits while converting from decimal to binary for the following questions.