



DPUWAGOIO750

The DPU provides an interface to the WAGO CANopen field bus couplers with the model numbers 750-307, 750-337, 750-338, 750-347 and 750-348.

1. Inputs:

<i>~IO.Digital.Out[1...64]</i>	digital outputs (0 or 1)
<i>~IO.Analog.Out[1...64]</i>	analog output, value in Volts

2. Static parameters:

<i>CANMode</i>	Selects a CAN bus channel for the communication (see DPUCANBUS)
<i>ModuleID</i>	Coupler's module ID
<i>Config</i>	Field bus configuration. The configuration contains the model numbers (without the prefix 750-) in the order they have been plugged into the field bus.

3. Outputs:

<i>~IO.Digital.In[1...64]</i>	digital inputs (0 or 1)
<i>~IO.Analog.In[1...64]</i>	analog input, value in Volts

4. Dependencies to other DPUs:

In addition to **DPUWAGOIO750**, a **DPUCANBUS** with the same **CANMode** must be running on the same computer, which is connected to the CAN hardware. The *Index* value of **DPUCANBUS** must be lower than the *Index* value of **DPUWAGOIO750**.

5. Functional principle:

The DPU assigns inputs and outputs in ascending order according to the plugged I/O modules.

6. Example:

The following configuration describes a WAGO coupler with several connected modules:

```
DPUCANBUS CANBUS
{
    Computer = {CAN};
    Index = 1;
    CANMode = 3; # PEAK USB card
    Baud = 1;    # 500 kBaud
}
```



DPUWAGOIO750 WAGOIO

```
{
    Computer = {CAN}
    Index = 2;
    CANMode = 3; # same as in DPUCANBUS
    Config =
    {
        337, # CANOpen coupler
        457, # Analog input, 4 channels, +/- 10 Volt
        476, # Analog input, 2 channels, +/- 10 Volt
        408, # Digital input, 4 channels, DC 24 Volt
        517, # Relay output, 2 channels, AC 230 Volt
        550  # Analog output, 4 channels, 0-10 Volt
    };
};
```

In this example, the following DPU variables are assigned to each of the modules:

- The 750-457 analog input provides the DPU outputs *~IO.Analog.In1 ... In4*.
- The 750-476 analog input provides the DPU outputs *~IO.Analog.In5 and In6*.
- The 750-408 digital input provides the DPU outputs *~IO.Digital.In1 ... In4*.
- The 750-517 relay output can be switched using the DPU inputs *~IO.Digital.Out1 and Out2*.
- The 750-550 analog output uses the value from the DPU inputs *~IO.Analog.Out1 ... Out4*.